

## VPRN Show Commands

### egress-label

**Syntax** `egress-label egress-label1 [egress-label2]`

**Context** show>service

**Description** Display services using the range of egress labels.

If only the mandatory *egress-label1* parameter is specified, only services using the specified label are displayed.

If both *egress-label1* and *egress-label2* parameters are specified, the services using the range of labels X where *egress-label1* <= X <= *egress-label2* are displayed.

Use the **show router ldp bindings** command to display dynamic labels.

**Parameters** *egress-label1* — The starting egress label value for which to display services using the label range. If only *egress-label1* is specified, services only using *egress-label1* are displayed.

**Values** 0, 2049 — 131071

*egress-label2* — The ending egress label value for which to display services using the label range.

**Default** The *egress-label1* value.

**Values** 2049 — 131071

**Output** **Show Service Egress Command Output** — The following table describes show service egress label output fields.

Label	Description
Svc Id	The ID that identifies a service.
Sdp Id	The ID that identifies an SDP.
Type	Indicates whether the SDP binding is a spoke or a mesh.
I. Lbl	The VC label used by the far-end device to send packets to this device in this service by the SDP.
E. Lbl	The VC label used by this device to send packets to the far-end device in this service by the SDP.
Number of bindings found	The total number of SDP bindings that exist within the specified egress label range.

**Sample Output**

```
*A:ALA-12# show service egress-label 0 10000
=====
Martini Service Labels
=====
Svc Id      Sdp Id          Type I.Lbl      E.Lbl
-----
1           10:1            Mesh 0         0
1           20:1            Mesh 0         0
1           30:1            Mesh 0         0
1           100:1           Mesh 0         0
...
1           107:1           Mesh 0         0
1           108:1           Mesh 0         0
1           300:1           Mesh 0         0
1           301:1           Mesh 0         0
1           302:1           Mesh 0         0
1           400:1           Mesh 0         0
1           500:2           Spok 131070    2001
1           501:1           Mesh 131069    2000
100         300:100         Spok 0         0
200         301:200         Spok 0         0
300         302:300         Spok 0         0
400         400:400         Spok 0         0
-----
Number of Bindings Found : 23
=====
*A:ALA-12#
```

**ingress-label**

**Syntax** `ingress-label start-label [end-label]`

**Context** `show>service`

**Description** Display services using the range of ingress labels.

If only the mandatory *start-label* parameter is specified, only services using the specified label are displayed.

If both *start-label* and *end-label* parameters are specified, the services using the range of labels X where *start-label* <= X <= *end-label* are displayed.

Use the **show router vprn-service-id ldp bindings** command to display dynamic labels.

**Parameters** *start-label* — The starting ingress label value for which to display services using the label range. If only *start-label* is specified, services only using *start-label* are displayed.

**Values** 0, 2048 — 131071

*end-label* — The ending ingress label value for which to display services using the label range.

**Default** The *start-label* value.

**Values** 2048 — 131071

**Output** **Show Service Ingress-Label** — The following table describes show service ingress-label output fields:

Label	Description
Svc ID	The service identifier.
SDP Id	The SDP identifier.
Type	Indicates whether the SDP is a spoke or a mesh.
I.Lbl	The ingress label used by the far-end device to send packets to this device in this service by the SDP.
E.Lbl	The egress label used by this device to send packets to the far-end device in this service by the SDP.
Number of Bindings Found	The number of SDP bindings within the label range specified.

### Sample Output

```
*A:ALA-12# show service ingress-label 0
=====
Martini Service Labels
=====
Svc Id      Sdp Id      Type I.Lbl      E.Lbl
-----
1           10:1        Mesh 0          0
1           20:1        Mesh 0          0
1           30:1        Mesh 0          0
1           50:1        Mesh 0          0
1           100:1       Mesh 0          0
1           101:1       Mesh 0          0
1           102:1       Mesh 0          0
1           103:1       Mesh 0          0
1           104:1       Mesh 0          0
1           105:1       Mesh 0          0
1           106:1       Mesh 0          0
1           107:1       Mesh 0          0
1           108:1       Mesh 0          0
1           300:1       Mesh 0          0
1           301:1       Mesh 0          0
1           302:1       Mesh 0          0
1           400:1       Mesh 0          0
100        300:100     Spok 0          0
200        301:200     Spok 0          0
300        302:300     Spok 0          0
400        400:400     Spok 0          0
-----
Number of Bindings Found : 21
-----
*A:ALA-12#
```

## sap-using

**Syntax** **sap-using** [**msap**] [**dyn-script**] [**description**]  
**sap-using** [**sap** *sap-id*] [**vlan-translation** | **anti-spoof**] [**description**]  
**sap-using** [**sap** *sap-id*]  
**sap-using** **interface** [*ip-address* | *ip-int-name*]  
**sap-using** [**ingress** | **egress**] **atm-td-profile** *td-profile-id*  
**sap-using** [**ingress** | **egress**] **filter** *filter-id*  
**sap-using** [**ingress** | **egress**] **qos-policy** *qos-policy-id*  
**sap-using** **authentication-policy** *policy-name*

**Context** show>service

**Description** This command displays SAP information.  
 If no optional parameters are specified, the command displays a summary of all defined SAPs.  
 The optional parameters restrict output to only SAPs matching the specified properties.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

**interface** — Specifies matching SAPs with the specified IP interface.

*ip-address* — The IP address of the interface for which to display matching SAPs.

**Values** 1.0.0.0 — 223.255.255.255

*ip-int-name* — The IP interface name for which to display matching SAPs.

**dyn-script** — Displays dynamic service SAPs information.

**ingress** — Specifies matching an ingress policy.

**egress** — Specifies matching an egress policy.

**qos-policy** *qos-policy-id* — The ingress or egress QoS Policy ID for which to display matching SAPs.

**Values** 1 — 65535

**atm-td-profile** *td-profile-id* — Displays SAPs using this traffic description.

**filter** *filter-id* — The ingress or egress filter policy ID for which to display matching SAPs.

**Values** 1 — 65535

**authentication-policy** *policy name* — Specifies an existing authentication policy.

**Output** **Show Service SAP** — The following table describes show service SAP output fields:

Label	Description
Port ID	The ID of the access port where the SAP is defined.
Svc ID	The service identifier.
SapMTU	The SAP MTU value.
I.QoS	The SAP ingress QoS policy number specified on the ingress SAP.
I.MAC/IP	The MAC or IP filter policy ID applied to the ingress SAP.

Label	Description (Continued)
E.QoS	The SAP egress QoS policy number specified on the egress SAP.
E.Mac/IP	The MAC or IP filter policy ID applied to the egress SAP
A.Pol	The accounting policy ID assigned to the SAP.
Adm	The desired state of the SAP.
Opr	The actual state of the SAP.

### Sample Output

```
*A:ALA-12# show service sap-using sap 1/1
=====
Service Access Points
=====
PortId          SvcId      SapMTU  I.QoS  I.Mac/IP  E.QoS  E.Mac/IP  A.Pol  Adm  Opr
-----
1/1/7:0         1          1518   10     8         10     none     none   Up   Up
1/1/11:0        100        1514   1     none      1     none     none   Down Down
1/1/7:300       300        1518   10     none      10     none     1000  Up   Up
-----
Number of SAPs : 3
-----

*A:ALA-12#

*A:ALA-12# show service sap-using egress atm-td-profile 2
=====
Service Access Point Using ATM Traffic Profile 2
=====
PortId SvcId I.QoS I.Fltr E.QoS E.Fltr  A.Pol Adm Opr
-----
5/1/1:0/11 511111 2 none 2 none none Up Up
5/1/1:0/12 511112 2 none 2 none none Up Up
5/1/1:0/13 511113 2 none 2 none none Up Up
5/1/1:0/14 511114 2 none 2 none none Up Up
5/1/1:0/15 511115 2 none 2 none none Up Up
5/1/1:0/16 511116 2 none 2 none none Up Up
5/1/1:0/17 511117 2 none 2 none none Up Up
5/1/1:0/18 511118 2 none 2 none none Up Up
5/1/1:0/19 511119 2 none 2 none none Up Up
5/1/1:0/20 511120 2 none 2 none none Up Up
5/1/1:0/21 511121 2 none 2 none none Up Up
5/1/1:0/22 511122 2 none 2 none none Up Up
5/1/1:0/23 511123 2 none 2 none none Up Up
5/1/1:0/24 511124 2 none 2 none none Up Up
5/1/1:0/25 511125 2 none 2 none none Up Up ...
-----

*A:ALA-12#
```

## sdp

**Syntax** `sdp [sdp-id | far-end ip-address] [detail | keep-alive-history]`

**Context** `show>service`

## Show, Clear, Debug Commands

**Description** Displays SDP information.  
If no optional parameters are specified, a summary SDP output for all SDPs is displayed.

**Parameters** *sdp-id* — The SDP ID for which to display information.

**Default** All SDPs.

**Values** 1 — 17407

**far-end** *ip-address* — Displays only SDPs matching with the specified far-end IP address.

**Default** SDPs with any far-end IP address.

**detail** — Displays detailed SDP information.

**Default** SDP summary output.

**keep-alive-history** — Displays the last fifty SDP keepalive events for the SDP.

**Default** SDP summary output.

**Output** **Show Service SDP** — The following table describes show service SDP output fields:

Label	Description
SDP Id	The SDP identifier.
Adm MTU	Specifies the largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Opr MTU	Specifies the actual largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
IP address	Specifies the IP address of the remote end of the GRE or MPLS tunnel defined by this SDP.
Adm Admin State	Specifies the state of the SDP.
Opr Oper State	Specifies the operating state of the SDP.
Flags	Specifies all the conditions that affect the operating status of this SDP.
Signal Signaling	Specifies the signaling protocol used to obtain the ingress and egress labels used in frames transmitted and received on the SDP.
Last Status Change	Specifies the time of the most recent operating status change to this SDP.
Last Mgmt Change	Specifies the time of the most recent management-initiated change to this SDP.
Number of SDPs	Specifies the total number of SDPs displayed according to the criteria specified.
Hello Time	Specifies how often the SDP echo request messages are transmitted on this SDP.

Label	Description (Continued)
Deliver Delivered	Specifies the type of delivery used by the SDP: GRE or MPLS.
Number of SDPs	Specifies the total number of SDPs displayed according to the criteria specified.
Hello Time	Specifies how often the SDP echo request messages are transmitted on this SDP.
Hello Msg Len	Specifies the length of the SDP echo request messages transmitted on this SDP.
Hello Timeout	Specifies the number of seconds to wait for an SDP echo response message before declaring a timeout.
Unmatched Replies	Specifies the number of SDP unmatched message replies.
Max Drop Count	Specifies the maximum number of consecutive SDP echo request messages that can be unacknowledged before the keepalive protocol reports a fault.
Hold Down Time	Specifies the maximum number of consecutive SDP echo request messages that can be unacknowledged before the keepalive protocol reports a fault.
TX Hello Msgs	Specifies the number of SDP echo request messages transmitted since the keepalive was administratively enabled or the counter was cleared.
Rx Hello Msgs	Specifies the number of SDP echo request messages received since the keepalive was administratively enabled or the counter was cleared.
Associated LSP List	When the SDP type is MPLS, a list of LSPs used to reach the far-end router displays. All the LSPs in the list must terminate at the IP address specified in the far end field. If the SDP type is GRE, then the following message displays: SDP delivery mechanism is not MPLS

### Sample Output

```
*A:ALA-12# show service sdp
=====
Services: Service Destination Points
=====
SdpId   Adm MTU   Opr MTU   IP address   Adm  Opr       Deliver Signal
-----
10      4462     4462     10.20.1.3    Up   Dn NotReady MPLS   TLDP
40      4462     1534     10.20.1.20   Up   Up        MPLS   TLDP
60      4462     1514     10.20.1.21   Up   Up        GRE    TLDP
100     4462     4462     180.0.0.2    Down Down      GRE    TLDP
500     4462     4462     10.20.1.50   Up   Dn NotReady GRE    TLDP
-----
Number of SDPs : 5
=====
*A:ALA-12#
```

## Show, Clear, Debug Commands

```
*A:ALA-12# show service sdp 2 detail
=====
Service Destination Point (Sdp Id : 2) Details
=====
-----
Sdp Id 2 -(10.10.10.104)
-----
Description          : GRE-10.10.10.104
SDP Id               : 2
Admin Path MTU       : 0                Oper Path MTU       : 0
Far End              : 10.10.10.104      Delivery            : GRE
Admin State          : Up                Oper State           : Down
Flags                : SignalingSessDown TransportTunnDown
Signaling            : TLDP              VLAN VC Etype       : 0x8100
Last Status Change   : 02/01/2007 09:11:39 Adv. MTU Over.      : No
Last Mgmt Change     : 02/01/2007 09:11:46

KeepAlive Information :
Admin State          : Disabled          Oper State           : Disabled
Hello Time           : 10                Hello Msg Len        : 0
Hello Timeout        : 5                Unmatched Replies    : 0
Max Drop Count       : 3                Hold Down Time       : 10
Tx Hello Msgs        : 0                Rx Hello Msgs        : 0

Associated LSP LIST :
SDP Delivery Mechanism is not MPLS
=====
*A:ALA-12#

*A:ALA-12# show service sdp 8
=====
Service Destination Point (Sdp Id : 8)
=====
-----
SdpId   Adm MTU   Opr MTU   IP address   Adm  Opr       Deliver Signal
-----
8       4462     4462     10.10.10.104  Up   Dn NotReady MPLS   TLDP
-----
Service Destination Point (Sdp Id : 8) Details
-----
-----
Sdp Id 8 -(10.10.10.104)
-----
Description          : MPLS-10.10.10.104
SDP Id               : 8
Admin Path MTU       : 0                Oper Path MTU       : 0
Far End              : 10.10.10.104      Delivery            : MPLS
Admin State          : Up                Oper State           : Down
Flags                : SignalingSessDown TransportTunnDown
Signaling            : TLDP              VLAN VC Etype       : 0x8100
Last Status Change   : 02/01/2007 09:11:39 Adv. MTU Over.      : No
Last Mgmt Change     : 02/01/2007 09:11:46

KeepAlive Information :
Admin State          : Disabled          Oper State           : Disabled
Hello Time           : 10                Hello Msg Len        : 0
Hello Timeout        : 5                Unmatched Replies    : 0
Max Drop Count       : 3                Hold Down Time       : 10
Tx Hello Msgs        : 0                Rx Hello Msgs        : 0

Associated LSP LIST :
Lsp Name             : to-104
Admin State          : Up                Oper State           : Down
Time Since Last Tran* : 01d07h36m
```



```
=====
* indicates that the corresponding row element may have been truncated.
*A:ALA-12#
```

## sdp-using

**Syntax** `sdp-using [sdp-id[:vc-id] | far-end ip-address]`

**Context** `show>service`

**Description** Display services using SDP or far-end address options.

**Parameters** *sdp-id* — Displays only services bound to the specified SDP ID.

**Values** 1 — 17407

*vc-id* — The virtual circuit identifier.

**Values** 1 — 4294967295

**far-end ip-address** — Displays only services matching with the specified far-end IP address.

**Default** Services with any far-end IP address.

**Output** **Show Service SDP Using X** — The following table describes show service sdp-using output fields.

Label	Description
Svc ID	The service identifier.
Sdp ID	The SDP identifier.
Type	Type of SDP: spoke or mesh.
Far End	The far end address of the SDP.
Oper State	The operational state of the service.
Ingress Label	The label used by the far-end device to send packets to this device in this service by this SDP.
Egress Label	The label used by this device to send packets to the far-end device in this service by this SDP.

### Sample Output

```
*A:ALA-1# show service sdp-using 300
=====
Service Destination Point (Sdp Id : 300)
=====
```

SvcId	SdpId	Type	Far End	Opr State	I.Label	E.Label
1	300:1	Mesh	10.0.0.13	Up	131071	131071
2	300:2	Spok	10.0.0.13	Up	131070	131070
100	300:100	Mesh	10.0.0.13	Up	131069	131069
101	300:101	Mesh	10.0.0.13	Up	131068	131068
102	300:102	Mesh	10.0.0.13	Up	131067	131067

```
-----
```

## Show, Clear, Debug Commands

```

Number of SDPs : 5
-----
*A:ALA-1#

A:ALA-48# show service sdp-using
=====
SDP Using
=====
SvcId      SdpId                Type Far End      Opr State I.Label  E.Label
-----
3          2:3                  Spok 10.20.1.2     Up      n/a      n/a
103       3:103                Spok 10.20.1.3     Up      131067  131068
103       4:103                Spok 10.20.1.2     Up      131065  131069
105       3:105                Spok 10.20.1.3     Up      131066  131067
-----
Number of SDPs : 4
-----
A:ALA-48

```

### service-using

**Syntax** **service-using** [**epipe**] [**ies**] [**vpls**] [**vprn**] [**mirror**] [**apipe**] [**fpipe**] [**ipipe**]<sub>[\_]</sub>[**sdp** *sdp-id*] [**customer** *customer-id*]

**Context** show>service

**Description** Displays the services matching certain usage properties.

If no optional parameters are specified, all services defined on the system are displayed.

**Parameters** **epipe** — Displays matching Epipe services.

**ies** — Displays matching IES instances.

**vpls** — Displays matching VPLS instances.

**vprn** — Displays matching VPRN services.

**mirror** — Displays mirror services.

**apipe** — Displays matching Apipe services.

**fpipe** — Displays matching Fpipe services.

**ipipe** — Displays matching Ipipe services.

**sdp** *sdp-id* — Displays only services bound to the specified SDP ID.

**Default** Services bound to any SDP ID.

**Values** 1 — 17407

**customer** *customer-id* — Displays services only associated with the specified customer ID.

**Default** Services associated with an customer.

**Values** 1 — 2147483647

**Output** **Show Service Service-Using** — The following table describes show service service-using output fields:

Label	Description
Service Id	The service identifier.
Type	Specifies the service type configured for the service ID.
Adm	The desired state of the service.
Opr	The operating state of the service.
CustomerID	The ID of the customer who owns this service.
Last Mgmt Change	The date and time of the most recent management-initiated change to this service.

### Sample Output

```
*A:ALA-12# show service service-using customer 10
=====
Services
=====
ServiceId   Type      Adm   Opr      CustomerId  Last Mgmt Change
-----
1           VPLS     Up    Up        10          09/05/2006 13:24:15
100        IES      Up    Up        10          09/05/2006 13:24:15
300        Epipe    Up    Up        10          09/05/2006 13:24:15
900        VPRN     Up    Up        2           11/04/2006 04:55:12
-----
Matching Services : 4
=====
*A:ALA-12#

*A:ALA-12# show service service-using epipe
=====
Services [epipe]
=====
ServiceId   Type      Adm   Opr      CustomerId  Last Mgmt Change
-----
6           Epipe    Up    Up        6           06/22/2006 23:05:58
7           Epipe    Up    Up        6           06/22/2006 23:05:58
8           Epipe    Up    Up        3           06/22/2006 23:05:58
103        Epipe    Up    Up        6           06/22/2006 23:05:58
-----
Matching Services : 4
=====
*A:ALA-12#

A:de14# show service service-using
=====
Services
=====
ServiceId   Type      Adm   Opr      CustomerId  Last Mgmt Change
-----
1           uVPLS    Up    Up        1           10/26/2006 15:44:57
2           Epipe    Up    Down      1           10/26/2006 15:44:57
10          mVPLS    Down  Down      1           10/26/2006 15:44:57
11          mVPLS    Down  Down      1           10/26/2006 15:44:57
100        mVPLS    Up    Up        1           10/26/2006 15:44:57
```

## Show, Clear, Debug Commands

```
101          mVPLS      Up      Up      1          10/26/2006 15:44:57
102          mVPLS      Up      Up      1          10/26/2006 15:44:57
999          uVPLS      Down   Down   1          10/26/2006 16:14:33
-----
Matching Services : 8
-----
A:del14#
```

### id

**Syntax** `id service-id {all | arp | base | fdb | labels | mfib | sap | sdp | split-horizon-group | stp}`

**Context** show>service

**Description** This command displays information for a particular service-id.

**Parameters** *service-id* — The unique service identification number that identifies the service in the service domain.

**all** — Display detailed information about the service.

**arp** — Display ARP entries for the service.

**base** — Display basic service information.

**fdb** — Display FDB entries.

**interface** — Display service interfaces.

**labels** — Display labels being used by this service.

**sap** — Display SAPs associated to the service.

**sdp** — Display SDPs associated with the service.

**split-horizon-group** — Display split horizon group information.

**stp** — Display STP information.

### all

**Syntax** `all`

**Context** show>service>id

**Description** Displays detailed information for all aspects of the service.

**Show All Service-ID Output** — The following table describes the show all service-id command output fields:

Label	Description
Service Detailed Information	
Service Id	The service identifier.
VPN Id	The number which identifies the VPN.

Label	Description
Customer Id	The customer identifier.
Last Status Change	The date and time of the most recent change in the administrative or operating status of the service.
Last Mgmt Change	The date and time of the most recent management-initiated change to this customer.
Admin State	The current administrative state.
Oper State	The current operational state.
Route Dist.	Displays the route distribution number.
AS Number	Displays the autonomous system number.
Router Id	Displays the router ID for this service.
ECMP	Displays equal cost multipath information.
ECMP Max Routes	Displays the maximum number of routes that can be received from the neighbors in the group or for the specific neighbor.
Max Routes	Displays the maximum number of routes that can be used for path sharing.
Auto Bind	Specifies the automatic binding type for the SDP assigned to this service.
Vrf Target	Specifies the VRF target applied to this service.
Vrf Import	Specifies the VRF import policy applied to this service.
Vrf Export	Specifies the VRF export policy applied to this service.
SDP Id	The SDP identifier.
Description	Generic information about the service.
SAP Count	The number of SAPs specified for this service.
SDP Bind Count	The number of SDPs bound to this service.
Split Horizon Group	Name of the split horizon group for this service.
Description	Description of the split horizon group.
Last Changed	The date and time of the most recent management-initiated change to this split horizon group.
Service Destination Points (SDPs)	
SDP Id	The SDP identifier.
Type	Indicates whether this Service SDP binding is a spoke or a mesh.

Label	Description
Admin Path MTU	The desired largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Oper Path MTU	The actual largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Delivery	Specifies the type of delivery used by the SDP: GRE or MPLS.
Admin State	The administrative state of this SDP.
Oper State	The operational state of this SDP.
Ingress Label	The label used by the far-end device to send packets to this device in this service by this SDP.
Egress Label	The label used by this device to send packets to the far-end device in this service by this SDP.
Ingress Filter	The ID of the ingress filter policy.
Egress Filter	The ID of the egress filter policy.
Far End	Specifies the IP address of the remote end of the GRE or MPLS tunnel defined by this SDP.
Last Changed	The date and time of the most recent change to this customer.
Signaling	Specifies the signaling protocol used to obtain the ingress and egress labels used in frames transmitted and received on this SDP.
Admin State	Specifies the operating status of the keepalive protocol.
Oper State	The current status of the keepalive protocol.
Hello Time	Specifies how often the SDP echo request messages are transmitted on this SDP.
Hello Msg Len	Specifies the length of the SDP echo request messages transmitted on this SDP.
Max Drop Count	Specifies the maximum number of consecutive SDP Echo Request messages that can be unacknowledged before the keepalive protocol reports a fault.
Hold Down Time	Specifies the amount of time to wait before the keepalive operating status is eligible to enter the alive state.
SDP Delivery Mechanism	When the SDP type is MPLS, a list of LSPs used to reach the far-end router displays. All the LSPs in the list must terminate at the IP address specified in the far end field. If the SDP type is GRE, then the following message displays: SDP delivery mechanism is not MPLS

<b>Label</b>	<b>Description</b>
Max Drop Count	Specifies the maximum number of consecutive SDP Echo Request messages that can be unacknowledged before the keepalive protocol reports a fault.
Number of SDPs	The total number SDPs applied to this service ID.
Service Access Points	
Service Id	The service identifier.
Port Id	The ID of the access port where this SAP is defined.
Description	Generic information about the SAP.
Encap Value	The value of the label used to identify this SAP on the access port.
Admin State	The desired state of the SAP.
Oper State	The operating state of the SAP.
Last Changed	The date and time of the last change.
Admin MTU	The desired largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Oper MTU	The actual largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Ingress qos-policy	The SAP ingress QoS policy ID.
Egress qos-policy	The SAP egress QoS policy ID.
Ingress Filter-Id	The SAP ingress filter policy ID.
Egress Filter-Id	The SAP egress filter policy ID.
Multi Svc Site	Indicates the multi-service site that the SAP is a member.
Ingress sched-policy	Indicates the ingress QoS scheduler for the SAP.
Egress sched-policy	Indicates the egress QoS scheduler for the SAP.
Acct. Pol	Indicates the accounting policy applied to the SAP.
Collect Stats	Specifies whether accounting statistics are collected on the SAP.
SAP Statistics	
Dropped	The number of packets or octets dropped.
Offered Hi Priority	The number of high priority packets, as determined by the SAP ingress QoS policy.

## Show, Clear, Debug Commands

Label	Description
Offered Low Priority	The number of low priority packets, as determined by the SAP ingress QoS policy.
Forwarded In Profile	The number of in-profile packets or octets (rate below CIR) forwarded.
Forwarded Out Profile	The number of out-of-profile packets or octets (rate above CIR) forwarded.
Queueing Stats	
Dropped In Profile	The number of in-profile packets or octets discarded.
Dropped Out Profile	The number of out-of-profile packets or octets discarded.
Forwarded In Profile	The number of in-profile packets or octets (rate below CIR) forwarded.
Forwarded Out Profile	The number of out-of-profile packets or octets (rate above CIR) forwarded.
SAP per Queue stats	
Ingress Queue 1	The index of the ingress QoS queue of this SAP.
High priority offered	The packets or octets count of the high priority traffic for the SAP.
High priority dropped	The number of high priority traffic packets/octets dropped.
Low priority offered	The packets or octets count of the low priority traffic.
Low priority dropped	The number of low priority traffic packets/octets dropped.
In profile forwarded	The number of in-profile packets or octets (rate below CIR) forwarded.
Out profile forwarded	The number of out-of-profile octets (rate above CIR) forwarded.
Egress Queue 1	The index of the egress QoS queue of the SAP.
In profile forwarded	The number of in-profile packets or octets (rate below CIR) forwarded.
In profile dropped	The number of in-profile packets or octets dropped for the SAP.
Out profile forwarded	The number of out-of-profile packets or octets (rate above CIR) forwarded.
Out profile dropped	The number of out-of-profile packets or octets discarded.
State	Specifies whether DHCP relay is enabled on this SAP.



Label	Description
Info Option	Specifies whether Option 82 processing is enabled on this SAP.
Action	Specifies the Option 82 processing on this SAP or interface: keep, replace or drop.
Circuit ID	Specifies whether the If index is inserted in circuit ID sub-option of Option 82.
Remote ID	Specifies whether the far-end MAC address is inserted in Remote ID sub-option of Option 82.
Service Access Points	
Managed by Service	Specifies the service-id of the management VPLS managing this SAP.
Managed by SAP	Specifies the sap-id inside the management VPLS managing this SAP.
Prune state	Specifies the STP state inherited from the management VPLS.
Spoke SDPs	
Managed by Service	Specifies the service-id of the management VPLS managing this spoke SDP.
Managed by Spoke	Specifies the sap-id inside the management VPLS managing this spoke SDP.
Prune state	Specifies the STP state inherited from the management VPLS.
Peer Pw Bits	Indicates the bits set by the LDP peer when there is a fault on its side of the pseudowire. LAC failures occur on the SAP that has been configured on the pipe service, PSN bits are set by SDP-binding failures on the pipe service. The pwNotForwarding bit is set when none of the above failures apply, such as an MTU mismatch failure. This value is only applicable if the peer is using the pseudowire status signalling method to indicate faults. pwNotForwarding — Pseudowire not forwarding lacIngressFault Local — Attachment circuit RX fault lacEgressFault Local — Attachment circuit TX fault psnIngressFault Local — PSN-facing PW RX fault psnEgressFault Local — PSN-facing PW TX fault pwFwdingStandby — Pseudowire in standby mode
IPCP Address Extension Details	
Peer IP Addr	Specifies the remote IP address to be assigned to the far-end of the associated PPP/MLPPP link via IPCP extensions.
Peer Pri DNS Addr	Specifies a unicast IPv4 address for the primary DNS server to be signaled to the far-end of the associate PPP/MLPPP link via IPCP extensions.
Peer Sec DNS Addr	Specifies a unicast IPv4 address for the secondary DNS server to be signaled to the far-end of the associate PPP/MLPPP link via IPCP extensions.

## Show, Clear, Debug Commands

### Sample Output

```
A:ALA-48# show service id 1 all
=====
Service Detailed Information
=====
Service Id      : 1                Vpn Id          : 0
Service Type    : VPRN
Customer Id     : 1
Last Status Change: 06/18/2007 10:07:01
Last Mgmt Change  : 06/18/2007 10:07:01
Admin State     : Up                Oper State      : Up

Route Dist.     : 10001:1          VPRN Type      : regular
AS Number       : 10000            Router Id       : 10.10.10.103
ECMP            : Enabled          ECMP Max Routes : 8
Max Routes      : 80              Auto Bind      : LDP
Vrf Target      : target:10001:1
Vrf Import      : vrfImpPolCust1
Vrf Export      : vrfExpPolCust1

SAP Count       : 2                SDP Bind Count  : 3
-----
Service Destination Points(SDPs)
-----
  Sdp Id 1:1  -(10.10.10.49)
-----
Description     : to-GRE-10.10.10.49
SDP Id          : 1:1                Type           : Spoke
VC Type         : n/a              VC Tag         : n/a
Admin Path MTU  : 0                Oper Path MTU  : 0
Far End         : 10.10.10.49       Delivery       : GRE

Admin State     : Up                Oper State     : Down
Acct. Pol       : None              Collect Stats  : Disabled
Ingress Label   : n/a              Egress Label   : n/a
Ing mac Fltr    : n/a              Egr mac Fltr   : n/a
Ing ip Fltr     : n/a              Egr ip Fltr    : n/a
Ing ipv6 Fltr   : n/a              Egr ipv6 Fltr  : n/a
Admin ControlWord : Not Preferred          Oper ControlWord : False
Admin BW(Kbps)  : 0                Oper BW(Kbps)  : 0
Last Status Change : 06/18/2007 10:06:49    Signaling      : n/a
Last Mgmt Change  : 06/18/2007 10:07:01
Class Fwding State : Down
Flags           : SdpOperDown
Peer Pw Bits    : None
Peer Fault Ip   : None
Peer Vccv CV Bits : None
Peer Vccv CC Bits : None

KeepAlive Information :
Admin State      : Disabled          Oper State     : Disabled
Hello Time       : 10                Hello Msg Len  : 0
Max Drop Count   : 3                Hold Down Time : 10

Statistics       :
I. Fwd. Pkts.    : n/a              I. Dro. Pkts.  : n/a
I. Fwd. Octs.    : n/a              I. Dro. Octs.  : n/a
E. Fwd. Pkts.    : n/a              E. Fwd. Octets : n/a

Associated LSP LIST :
SDP Delivery Mechanism is not MPLS
```

```
-----
Sdp Id 1:10  -(10.10.10.49)
-----
```

```
Description      : to-GRE-10.10.10.49
SDP Id           : 1:10                               Type           : Spoke
VC Type          : n/a                               VC Tag         : n/a
Admin Path MTU   : 0                                 Oper Path MTU  : 0
Far End          : 10.10.10.49                       Delivery       : GRE

Admin State      : Up                               Oper State     : Down
Acct. Pol       : None                             Collect Stats  : Disabled
Ingress Label   : 0                                 Egress Label  : 0
Ing mac Fltr    : n/a                             Egr mac Fltr  : n/a
Ing ip Fltr     : n/a                             Egr ip Fltr   : n/a
Ing ipv6 Fltr   : n/a                             Egr ipv6 Fltr : n/a
Admin ControlWord : Not Preferred                 Oper ControlWord : False
Admin BW(Kbps)  : 0                                 Oper BW(Kbps)  : 0
Last Status Change : 06/18/2007 10:06:49         Signaling     : n/a
Last Mgmt Change  : 06/18/2007 10:07:01

Class Fwding State : Down
Flags              : SdpOperDown
                   NoIngVCLabel NoEgrVCLabel

Peer Pw Bits     : None
Peer Fault Ip    : None
Peer Vccv CV Bits : None
Peer Vccv CC Bits : None
```

KeepAlive Information :

```
Admin State      : Disabled                       Oper State     : Disabled
Hello Time       : 10                            Hello Msg Len  : 0
Max Drop Count   : 3                             Hold Down Time : 10
```

Statistics :

```
I. Fwd. Pkts.    : 0                             I. Dro. Pkts.  : 0
I. Fwd. Octs.    : 0                             I. Dro. Octets : 0
E. Fwd. Pkts.    : 0                             E. Fwd. Octets : 0
```

Associated LSP LIST :

```
SDP Delivery Mechanism is not MPLS
-----
```

```
Sdp Id 3:4  -(10.10.10.105)
-----
```

```
SDP Id           : 3:4                               Type           : Spoke
VC Type          : n/a                               VC Tag         : n/a
Admin Path MTU   : 0                                 Oper Path MTU  : 0
Far End          : 10.10.10.105                     Delivery       : GRE

Admin State      : Up                               Oper State     : Down
Acct. Pol       : None                             Collect Stats  : Disabled
Ingress Label   : 3000                            Egress Label  : 2000
Ing mac Fltr    : n/a                             Egr mac Fltr  : n/a
Ing ip Fltr     : 10                               Egr ip Fltr   : 10
Ing ipv6 Fltr   : n/a                             Egr ipv6 Fltr : n/a
Admin ControlWord : Not Preferred                 Oper ControlWord : False
Admin BW(Kbps)  : 0                                 Oper BW(Kbps)  : 0
Last Status Change : 06/18/2007 10:06:49         Signaling     : n/a
Last Mgmt Change  : 06/18/2007 10:07:01

Class Fwding State : Down
Flags              : SdpOperDown

Peer Pw Bits     : None
Peer Fault Ip    : None
Peer Vccv CV Bits : None
Peer Vccv CC Bits : None
```

## Show, Clear, Debug Commands

```
KeepAlive Information :
Admin State           : Disabled           Oper State           : Disabled
Hello Time           : 10                 Hello Msg Len       : 0
Max Drop Count       : 3                 Hold Down Time      : 10
```

```
Statistics           :
I. Fwd. Pkts.       : 0                 I. Dro. Pkts.       : 0
I. Fwd. Octs.       : 0                 I. Dro. Octs.       : 0
E. Fwd. Pkts.       : 0                 E. Fwd. Octets      : 0
```

```
Associated LSP LIST :
SDP Delivery Mechanism is not MPLS
```

```
-----
Number of SDPs : 3
-----
```

```
Service Access Points
-----
```

```
SAP 1/1/21:0
-----
```

```
Service Id           : 1
SAP                  : 1/1/21:0           Encap                : q-tag
Dot1Q Ethertype     : 0x8100           QinQ Ethertype       : 0x8100

Admin State          : Up                Oper State            : Down
Flags                : PortOperDown
Last Status Change  : 06/18/2007 10:06:49
Last Mgmt Change    : 06/18/2007 10:07:01
Admin MTU            : 1518             Oper MTU              : 1518
Ingress qos-policy  : 1                 Egress qos-policy    : 1
Shared Q plcy       : n/a               Multipoint shared     : Disabled
Ingr IP Fltr-Id     : n/a               Egr IP Fltr-Id       : n/a
Ingr Mac Fltr-Id    : n/a               Egr Mac Fltr-Id      : n/a
Ingr IPv6 Fltr-Id   : n/a               Egr IPv6 Fltr-Id     : n/a
tod-suite           : None               qinq-pbit-marking    : both
Egr Agg Rate Limit  : max

Multi Svc Site      : None
Acct. Pol           : None               Collect Stats         : Disabled

Anti Spoofing       : None               Nbr Static Hosts     : 0
-----
```

```
Sap Statistics
-----
```

```
Last Cleared Time    : N/A
                    Packets           Octets
Forwarding Engine Stats
Dropped              : 0                0
Off. HiPrio          : 0                0
Off. LowPrio         : 0                0
Off. Uncolor         : 0                0
```

```
Queueing Stats(Ingress QoS Policy 1)
```

```
Dro. HiPrio          : 0                0
Dro. LowPrio         : 0                0
For. InProf          : 0                0
For. OutProf         : 0                0
```

```
Queueing Stats(Egress QoS Policy 1)
```

```
Dro. InProf          : 0                0
Dro. OutProf         : 0                0
For. InProf          : 0                0
For. OutProf         : 0                0
```

-----  
Sap per Queue stats  
-----

	Packets	Octets
Ingress Queue 1 (Unicast) (Priority)		
Off. HiPrio	: 0	0
Off. LoPrio	: 0	0
Dro. HiPrio	: 0	0
Dro. LoPrio	: 0	0
For. InProf	: 0	0
For. OutProf	: 0	0
Egress Queue 1		
For. InProf	: 0	0
For. OutProf	: 0	0
Dro. InProf	: 0	0
Dro. OutProf	: 0	0

-----  
SAP 1/2/4:0  
-----

Service Id	: 1		
SAP	: 1/2/4:0	Encap	: q-tag
Dot1Q Ethertype	: 0x8100	QinQ Ethertype	: 0x8100
Admin State	: Up	Oper State	: Down
Flags	: PortOperDown		
Last Status Change	: 06/18/2007 10:06:49		
Last Mgmt Change	: 06/18/2007 10:07:01		
Admin MTU	: 1518	Oper MTU	: 1518
Ingress qos-policy	: 1	Egress qos-policy	: 1
Shared Q plcy	: n/a	Multipoint shared	: Disabled
Ingr IP Fltr-Id	: n/a	Egr IP Fltr-Id	: n/a
Ingr Mac Fltr-Id	: n/a	Egr Mac Fltr-Id	: n/a
Ingr IPv6 Fltr-Id	: n/a	Egr IPv6 Fltr-Id	: n/a
tod-suite	: None	qinq-pbit-marking	: both
Egr Agg Rate Limit	: max		
Multi Svc Site	: None		
Acct. Pol	: None	Collect Stats	: Disabled
Anti Spoofing	: Ip-Mac	Nbr Static Hosts	: 0

-----  
Subscriber Management  
-----

Admin State	: Down	MAC DA Hashing	: False
Def Sub-Id	: None		
Def Sub-Profile	: None		
Def SLA-Profile	: None		
Def App-Profile	: None		
Sub-Ident-Policy	: None		
Subscriber Limit	: 1		
Single-Sub-Parameters			
Prof Traffic Only	: False		
Non-Sub-Traffic	: N/A		

-----  
Sap Statistics  
-----

Last Cleared Time	: N/A		
	Packets	Octets	
Forwarding Engine Stats			
Dropped	: 0	0	
Off. HiPrio	: 0	0	

## Show, Clear, Debug Commands

```
Off. LowPrio      : 0          0
Off. Uncolor     : 0          0
```

### Queueing Stats(Ingress QoS Policy 1)

```
Dro. HiPrio      : 0          0
Dro. LowPrio     : 0          0
For. InProf      : 0          0
For. OutProf     : 0          0
```

### Queueing Stats(Egress QoS Policy 1)

```
Dro. InProf      : 0          0
Dro. OutProf     : 0          0
For. InProf      : 0          0
For. OutProf     : 0          0
```

---

### Sap per Queue stats

---

	Packets	Octets
Ingress Queue 1 (Unicast) (Priority)		
Off. HiPrio	: 0	0
Off. LoPrio	: 0	0
Dro. HiPrio	: 0	0
Dro. LoPrio	: 0	0
For. InProf	: 0	0
For. OutProf	: 0	0

### Egress Queue 1

```
For. InProf      : 0          0
For. OutProf     : 0          0
Dro. InProf      : 0          0
Dro. OutProf     : 0          0
```

---

### Service Interfaces

---

#### Interface

---

```
If Name          : to-cel
Admin State      : Up          Oper (v4/v6)     : Down/Down
Protocols        : None
IP Addr/mask     : 11.1.0.1/24   Address Type     : Primary
IGP Inhibit     : Disabled    Broadcast Address: Host-ones
```

---

#### Details

---

```
If Index         : 2          Virt. If Index   : 2
Last Oper Chg   : 06/18/2007 10:07:01 Global If Index  : 96
SAP Id          : 1/1/21:0
TOS Marking     : Trusted     If Type          : VPRN
SNTP B.Cast     : False
MAC Address     : 14:30:01:01:00:15 Arp Timeout      : 14400
IP MTU          : 1500        ICMP Mask Reply  : True
Arp Populate    : Disabled    Host Conn Verify : Enabled
```

#### Proxy ARP Details

```
Rem Proxy ARP   : Disabled    Local Proxy ARP  : Disabled
Policies        : none
```

#### Proxy Neighbor Discovery Details

```
Local Pxy ND    : Disabled
Policies        : none
```

#### DHCP Details

```
Admin State     : Up          Lease Populate   : 1
```

## VPRN Show Commands

```

Gi-Addr          : 11.1.0.1*          Gi-Addr as Src Ip : Disabled
* = inferred gi-address from interface IP address

Action           : Keep                Trusted             : Disabled

DHCP Proxy Details
Admin State      : Down
Lease Time       : N/A
Emul. Server     : Not configured

Subscriber Authentication Details
Auth Policy      : None

DHCP6 Relay Details
Admin State      : Down                Lease Populate      : 0
Oper State       : Down                Nbr Resolution     : Disabled
If-Id Option     : None                Remote Id           : Disabled
Src Addr         : Not configured

DHCP6 Server Details
Admin State      : Down                Max. Lease States  : 8000

ICMP Details
Redirects        : Number - 100        Time (seconds)     - 10
Unreachables    : Number - 100        Time (seconds)     - 10
TTL Expired     : Number - 100        Time (seconds)     - 10

IPCP Address Extension Details
Peer IP Addr     : Not configured
Peer Pri DNS Addr : Not configured
Peer Sec DNS Addr : Not configured
-----
Interface
-----
If Name          : test
Admin State      : Up                  Oper (v4/v6)       : Down/Down
Protocols        : IGMP PIM

IP Addr/mask     : Not Assigned
-----
Details
-----
If Index         : 3                  Virt. If Index     : 3
Last Oper Chg   : 06/18/2007 10:07:01 Global If Index    : 95
Port Id         : n/a
TOS Marking     : Trusted             If Type            : VPRN
SNTP B.Cast     : False
MAC Address      :
IP MTU          : 0                  Arp Timeout        : 14400
Arp Populate    : Disabled            ICMP Mask Reply    : True
Host Conn Verify : Disabled            Host Conn Verify   : Disabled

Proxy ARP Details
Rem Proxy ARP    : Disabled            Local Proxy ARP    : Disabled
Policies         : none

Proxy Neighbor Discovery Details
Local Pxy ND     : Disabled
Policies         : none

DHCP Details
Admin State      : Down                Lease Populate      : 0
Gi-Addr         : Not configured      Gi-Addr as Src Ip  : Disabled
Action          : Keep                Trusted             : Disabled

```

## Show, Clear, Debug Commands

### DHCP Proxy Details

Admin State : Down  
Lease Time : N/A  
Emul. Server : Not configured

### Subscriber Authentication Details

Auth Policy : None

### DHCP6 Relay Details

Admin State : Down Lease Populate : 0  
Oper State : Down Nbr Resolution : Disabled  
If-Id Option : None Remote Id : Disabled  
Src Addr : Not configured

### DHCP6 Server Details

Admin State : Down Max. Lease States : 8000

### ICMP Details

Redirects : Number - 100 Time (seconds) - 10  
Unreachables : Number - 100 Time (seconds) - 10  
TTL Expired : Number - 100 Time (seconds) - 10

### IPCP Address Extension Details

Peer IP Addr : Not configured  
Peer Pri DNS Addr : Not configured  
Peer Sec DNS Addr : Not configured

---

### Interface

---

If Name : SpokeSDP  
Admin State : Up Oper (v4/v6) : Down/Down  
Protocols : None

IP Addr/mask : Not Assigned

---

### Details

---

If Index : 4 Virt. If Index : 4  
Last Oper Chg : 06/18/2007 10:07:01 Global If Index : 94  
SDP Id : spoke-3:4  
TOS Marking : Trusted If Type : VPRN  
SNTP B.Cast : False  
MAC Address : 14:30:ff:00:00:00 Arp Timeout : 14400  
IP MTU : 0 ICMP Mask Reply : True  
Arp Populate : Disabled Host Conn Verify : Disabled

### Proxy ARP Details

Rem Proxy ARP : Disabled Local Proxy ARP : Disabled  
Policies : none

### Proxy Neighbor Discovery Details

Local Pxy ND : Disabled  
Policies : none

### DHCP Details

Admin State : Down Lease Populate : 0  
Gi-Addr : Not configured Gi-Addr as Src Ip : Disabled  
Action : Keep Trusted : Disabled

### DHCP Proxy Details

Admin State : Down



Lease Time : N/A  
Emul. Server : Not configured

Subscriber Authentication Details  
Auth Policy : None

## DHCP6 Relay Details

Admin State : Down Lease Populate : 0  
Oper State : Down Nbr Resolution : Disabled  
If-Id Option : None Remote Id : Disabled  
Src Addr : Not configured

## DHCP6 Server Details

Admin State : Down Max. Lease States : 8000

## ICMP Details

Redirects : Number - 100 Time (seconds) - 10  
Unreachables : Number - 100 Time (seconds) - 10  
TTL Expired : Number - 100 Time (seconds) - 10

## IPCP Address Extension Details

Peer IP Addr : Not configured  
Peer Pri DNS Addr : Not configured  
Peer Sec DNS Addr : Not configured

-----  
Interface

If Name : gizmo  
Admin State : Up Oper (v4/v6) : Down/--  
Protocols : None

IP Addr/mask : Not Assigned

-----  
Details

If Index : 5 Virt. If Index : 5  
Last Oper Chg : 06/18/2007 10:07:01 Global If Index : 93  
SDP Id : spoke-1:10  
TOS Marking : Trusted If Type : VPRN Red  
Egress Filter : none Ingress Filter : none  
SNTP B.Cast : False QoS Policy : 1  
MAC Address : 14:30:ff:00:00:00  
IP MTU : 0 ICMP Mask Reply : True

-----  
Interface

If Name : test123  
Admin State : Up Oper (v4/v6) : Down/--  
Protocols : None

IP Addr/mask : Not Assigned

-----  
Details

If Index : 6 Virt. If Index : 6  
Last Oper Chg : 06/18/2007 10:07:01 Global If Index : 92  
Port Id : n/a  
TOS Marking : Trusted If Type : VPRN Red  
Egress Filter : none Ingress Filter : none  
SNTP B.Cast : False QoS Policy : 1  
MAC Address :  
IP MTU : 0 ICMP Mask Reply : True

## Show, Clear, Debug Commands

```

Interface
-----
If Name           : test1
Admin State       : Up           Oper (v4/v6)       : Down/--
Protocols         : None

IP Addr/mask      : Not Assigned
-----

Details
-----
If Index          : 7           Virt. If Index    : 7
Last Oper Chg    : 06/18/2007 10:07:01 Global If Index   : 91
Port Id          : n/a
TOS Marking      : Trusted      If Type           : VPRN Red
Egress Filter    : none         Ingress Filter    : none
SNTP B.Cast      : False       QoS Policy        : 1
MAC Address      :
IP MTU           : 0           ICMP Mask Reply   : True
-----

Interface
-----
If Name           : bozoclownd
Admin State       : Up           Oper (v4/v6)       : Down/--
Protocols         : None

IP Addr/mask      : Not Assigned
-----

Details
-----
If Index          : 8           Virt. If Index    : 8
Last Oper Chg    : 06/18/2007 10:07:01 Global If Index   : 90
Port Id          : n/a
TOS Marking      : Trusted      If Type           : VPRN Red
Egress Filter    : none         Ingress Filter    : none
SNTP B.Cast      : False       QoS Policy        : 1
MAC Address      :
IP MTU           : 0           ICMP Mask Reply   : True
-----

Interface
-----
If Name           : testabc
Admin State       : Up           Oper (v4/v6)       : Down/--
Protocols         : None

IP Addr/mask      : Not Assigned
-----

Details
-----
If Index          : 9           Virt. If Index    : 9
Last Oper Chg    : 06/18/2007 10:07:01 Global If Index   : 89
If Type          : VPRN Sub

DHCP Details
Gi-Addr          : Not configured   Gi-Addr as Src Ip : Disabled
=====
Interface testabc group-interfaces
=====
Interface-Name   Adm      Opr (v4/v6)  Mode    Port/SapId
  IP-Address                                           PfxState
-----
bozo              Up        Down/--     VPRN G* n/a
-----

Group-Interfaces : 1

```

```
=====
* indicates that the corresponding row element may have been truncated.
-----
```

## Interface

```
-----
If Name           : bozo
Sub If Name       : testabc
Red If Name       :
Admin State       : Up           Oper (v4/v6)       : Down/--
Protocols         : None
-----
```

## Details

```
-----
If Index          : 10           Virt. If Index    : 10
Last Oper Chg    : 06/18/2007 10:07:01 Global If Index   : 88
Port Id          : n/a
TOS Marking      : Trusted       If Type           : VPRN Grp
SNTP B.Cast      : False
MAC Address       :
IP MTU           : 0             Arp Timeout       : 14400
Arp Populate     : Disabled      ICMP Mask Reply   : True
Host Conn Verify : Disabled      -----
```

## Proxy ARP Details

```
Rem Proxy ARP    : Disabled      Local Proxy ARP   : Enabled
Policies         : none
```

## Proxy Neighbor Discovery Details

```
Local Pxy ND     : Disabled
Policies         : none
```

## DHCP Details

```
Admin State      : Down           Lease Populate    : 1
Gi-Addr         : Unknown        Gi-Addr as Src Ip : Disabled
Action          : Keep           Trusted           : Disabled
Match CircId    : Disabled
```

## DHCP Proxy Details

```
Admin State      : Down
Lease Time       : N/A
Emul. Server     : Not configured
```

## Subscriber Authentication Details

```
Auth Policy      : None
```

## DHCP6 Relay Details

```
Admin State      : Down           Lease Populate    : 0
Oper State       : Down           Nbr Resolution   : Disabled
If-Id Option     : None           Remote Id        : Disabled
Src Addr         : Not configured
```

## DHCP6 Server Details

```
Admin State      : Down           Max. Lease States : 8000
```

## ICMP Details

```
Redirects        : Number - 100      Time (seconds)   - 10
Unreachables     : Number - 100      Time (seconds)   - 10
TTL Expired      : Number - 100      Time (seconds)   - 10
```

## IPCP Address Extension Details

```
Peer IP Addr     : Not configured
Peer Pri DNS Addr : Not configured
Peer Sec DNS Addr : Not configured
```

## Show, Clear, Debug Commands

```

PPPoE Details
Last Mgmt Chg: 06/18/2007 10:06:49
Session limit      : 1                SAP session limit : 1
PPPoE Policy      : N/A
User DB           : N/A
=====
Service Access Point(Summary), Service 1 Interface bozo
=====
PortId              SvcId      Ing.  Ing.  Egr.  Egr.  Anti  Adm  Opr
                   :          QoS   Fltr  QoS   Fltr  Spoof
-----
No Service Access Point found.
=====
Interface
-----
If Name              : santa
Admin State          : Up                Oper (v4/v6)       : Down/--
Protocols            : None

IP Addr/mask         : Not Assigned
-----
Details
-----
If Index             : 11                Virt. If Index     : 11
Last Oper Chg       : 06/18/2007 10:07:01 Global If Index    : 87
If Type              : VPRN Sub

DHCP Details
Gi-Addr             : Not configured   Gi-Addr as Src Ip : Disabled
=====
Interface santa group-interfaces
=====
Interface-Name      Adm      Opr (v4/v6)  Mode      Port/SapId
IP-Address          :         :             :          PfxState
-----
interface           Up        Down/--      VPRN G* 1/2/4
-----
Group-Interfaces : 1
=====
* indicates that the corresponding row element may have been truncated.
-----
Interface
-----
If Name              : interface
Sub If Name          : santa
Red If Name          :
Admin State          : Up                Oper (v4/v6)       : Down/--
Protocols            : None

Details
-----
If Index             : 12                Virt. If Index     : 12
Last Oper Chg       : 06/18/2007 10:07:01 Global If Index    : 86
Group Port          : 1/2/4
TOS Marking         : Trusted           If Type            : VPRN Grp
SNTP B.Cast         : False
MAC Address          : 14:30:01:02:00:04 Arp Timeout        : 14400
IP MTU              : 1500             ICMP Mask Reply    : True
Arp Populate        : Disabled          Host Conn Verify   : Disabled

Proxy ARP Details
Rem Proxy ARP        : Disabled          Local Proxy ARP    : Enabled
Policies             : none

```

Proxy Neighbor Discovery Details

Local Pxy ND : Disabled  
Policies : none

DHCP Details

Admin State : Down Lease Populate : 1  
Gi-Addr : Unknown Gi-Addr as Src Ip : Disabled  
Action : Keep Trusted : Disabled  
Match CircId : Disabled

DHCP Proxy Details

Admin State : Down  
Lease Time : N/A  
Emul. Server : Not configured

Subscriber Authentication Details

Auth Policy : None

DHCP6 Relay Details

Admin State : Down Lease Populate : 0  
Oper State : Down Nbr Resolution : Disabled  
If-Id Option : None Remote Id : Disabled  
Src Addr : Not configured

DHCP6 Server Details

Admin State : Down Max. Lease States : 8000

ICMP Details

Redirects : Number - 100 Time (seconds) - 10  
Unreachables : Number - 100 Time (seconds) - 10  
TTL Expired : Number - 100 Time (seconds) - 10

IPCP Address Extension Details

Peer IP Addr : Not configured  
Peer Pri DNS Addr : Not configured  
Peer Sec DNS Addr : Not configured

PPPoE Details

Last Mgmt Chg: 06/18/2007 10:06:49  
Session limit : 1 SAP session limit : 1  
PPPoE Policy : N/A  
User DB : N/A

=====

Service Access Point(Summary), Service 1 Interface interface

=====

PortId	SvcId	Ing. QoS	Ing. Fltr	Egr. QoS	Egr. Fltr	Anti Spoof	Adm	Opr
1/2/4:0	1	1	none	1	none	ip-mac	Up	Down

\*#A:ALA-48#

## authentication

**Syntax** authentication

**Context** show>service>id

**Description** This command enables the context to display subscriber authentication information.

## statistics

**Syntax** **statistics** [*policy name*] [**sap** *sap-id*]

**Context** show>service>id>authentication

**Description** This command displays session authentication statistics for this service.

**Parameters** **policy name** — Specifies the subscriber authentication policy statistics to display.  
**sap sap-id** — Specifies the SAP ID statistics to display. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

### Sample Output

```
*A:ALA-1# show service id 11 authentication statistics
=====
Authentication statistics
=====
Interface / SAP                Authentication Successful  Authentication Failed
-----
abc-11-90.1.0.254              1582                      3
-----
Number of entries: 1
=====
*A:ALA-1#
```

## arp

**Syntax** **arp** [*ip-address*] | [**mac** *ieee-address*] | [**sap** *sap-id*] | [**interface** *ip-int-name*] [**sdp** *sdp-id:vc-id*] [**summary**]

**Context** show>service>id

**Description** Displays the ARP table for the IES instance.

**Parameters** *ip-address* — Displays only ARP entries in the ARP table with the specified IP address.

**Default** All IP addresses.

**mac ieee-address** — Displays only ARP entries in the ARP table with the specified 48-bit MAC address. The MAC address can be expressed in the form *aa:bb:cc:dd:ee:ff* or *aa-bb-cc-dd-ee-ff* where *aa*, *bb*, *cc*, *dd*, *ee* and *ff* are hexadecimal numbers.

**Default** All MAC addresses.

**sap sap-id** — Displays SAP information for the specified SAP ID. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

*port id* — Specifies matching service ARP entries associated with the specified IP interface.

*ip-address* — The IP address of the interface for which to display matching ARP entries.

**Values** 1.0.0.0 — 223.255.255.255

*ip-int-name* — The IP interface name for which to display matching ARPs.

**Output** **Show Service-ID ARP** — The following table describes show service-id ARP output fields.

Label	Description
Service ID	The service ID number.
MAC	The specified MAC address
Source-Identifier	The location the MAC is defined.
Type	Static – FDB entries created by management. Learned – Dynamic entries created by the learning process. OAM – Entries created by the OAM process.
Age	The time elapsed since the service was enabled.
Interface	The interface applied to the service.
Port	The port where the SAP is applied.

### Sample Output

```
*A:ALA-12# show service id 2 arp
=====
ARP Table
=====
IP Address      MAC Address      Type   Age      Interface      Port
-----
190.11.1.1      00:03:fa:00:08:22 Other   00:00:00 ies-100-190.11.1 1/1/11:0
=====
*A:ALA-12#
```

## arp-host

**Syntax** **arp-host** [**wholesaler** *service-id*] [**sap** *sap-id* | **interface** *interface-name* | **ip-address** *ip-address*[/*mask*] | **mac** *ieee-address* | {[**port** *port-id*] [**no-inter-dest-id** | **inter-dest-id** *inter-dest-id*]}] [**detail**]  
**arp-host statistics** [**sap** *sap-id* | **interface** *interface-name*]  
**arp-host summary** [**interface** *interface-name*]

**Context** show>service>id

**Description** This command displays ARP host related information.

### Sample Output

```
*A:Dut-C# show service id 2 arp-host
=====
ARP host table, service 2
=====
IP Address      Mac Address      Sap Id      Remaining      MC
Time           Stdby
-----
128.128.1.2      00:80:00:00:00:01 2/1/5:2      00h04m41s
128.128.1.3      00:80:00:00:00:02 2/1/5:2      00h04m42s
128.128.1.4      00:80:00:00:00:03 2/1/5:2      00h04m43s
128.128.1.5      00:80:00:00:00:04 2/1/5:2      00h04m44s
```

## Show, Clear, Debug Commands

```
128.128.1.6      00:80:00:00:00:05 2/1/5:2      00h04m45s
128.128.1.7      00:80:00:00:00:06 2/1/5:2      00h04m46s
128.128.1.8      00:80:00:00:00:07 2/1/5:2      00h04m47s
128.128.1.9      00:80:00:00:00:08 2/1/5:2      00h04m48s
128.128.1.10     00:80:00:00:00:09 2/1/5:2      00h04m49s
128.128.1.11     00:80:00:00:00:0a 2/1/5:2      00h04m50s
-----
```

```
Number of ARP hosts : 10
=====
```

```
*A:Dut-C#
```

```
*A:Dut-C# show service id 2 arp-host ip-address 128.128.1.2 detail
=====
```

```
ARP hosts for service 2
=====
```

```
Service ID      : 2
IP Address      : 128.128.1.2
MAC Address     : 00:80:00:00:00:01
SAP             : 2/1/5:2
Remaining Time  : 00h04m58s
```

```
Sub-Ident      : "alu_1_2"
Sub-Profile-String : ""
SLA-Profile-String : ""
App-Profile-String : ""
ARP host ANCP-String : ""
ARP host Int Dest Id : ""
RADIUS-User-Name : "128.128.1.2"
```

```
Session Timeout (s) : 301
Start Time          : 02/09/2009 16:35:07
Last Auth           : 02/09/2009 16:36:34
Last Refresh        : 02/09/2009 16:36:38
Persistence Key     : N/A
-----
```

```
Number of ARP hosts : 1
=====
```

```
*A:Dut-C#
```

```
*A:Dut-C# show service id 2 arp-host statistics
=====
```

```
ARP host statistics
=====
```

```
Num Active Hosts      : 20
Received Triggers     : 70
Ignored Triggers      : 10
Ignored Triggers (overload) : 0
SHCV Checks Forced    : 0
Hosts Created         : 20
Hosts Updated         : 40
Hosts Deleted         : 0
Authentication Requests Sent : 40
=====
```

```
*A:Dut-C#
```

```
*A:Dut-C# show service id 2 arp-host summary
=====
```

```
ARP host Summary, service 2
=====
```

Sap	Used	Provided	Admin State
-----	------	----------	-------------



```

-----
sap:2/1/5:2          20          8000          inService
-----
Number of SAPs : 1
-----
=====
*A:Dut-C#

```

## base

**Syntax**    **base**

**Context**    show>service>id

**Description**    Displays basic information about the service ID including service type, description, SAPs and SDPs.

**Output**    **Show Service-ID Base** — The following table describes show service-id base output fields:

Label	Description
Service Id	The service identifier.
Vpn Id	Specifies the VPN ID assigned to the service.
Service Type	Specifies the type of service.
Description	Generic information about the service.
Customer Id	The customer identifier.
Last Mgmt Change	The date and time of the most recent management-initiated change to this customer.
Adm	The desired state of the service.
Oper	The operating state of the service.
Mtu	The largest frame size (in octets) that the service can handle.
Def. Mesh VC Id	This object is only valid in services that accept mesh SDP bindings. It is used to validate the VC ID portion of each mesh SDP binding defined in the service.
SAP Count	The number of SAPs defined on the service.
SDP Bind Count	The number of SDPs bound to the service.
Identifier	Specifies the service access (SAP) and destination (SDP) points.
Type	Specifies the signaling protocol used to obtain the ingress and egress labels used in frames transmitted and received on the SDP.
AdmMTU	Specifies the desired largest service frame size (in octets) that can be transmitted through this SDP to the far-end ESR, without requiring the packet to be fragmented.

## Show, Clear, Debug Commands

Label	Description
OprMTU	Specifies the actual largest service frame size (in octets) that can be transmitted through this SDP to the far-end ESR, without requiring the packet to be fragmented.
Opr	The operating state of the SDP.

### Sample Output

```
*A:SetupCLI# show service id 3 base
=====
Service Basic Information
=====
Service Id      : 3                Vpn Id          : 0
Service Type    : VPRN
Name            : (Not Specified)
Description     : (Not Specified)
Customer Id     : 1
Last Status Change: 10/08/2009 04:55:01
Last Mgmt Change  : 10/08/2009 06:48:38
Admin State     : Down            Oper State      : Down

Route Dist.     : None            VPRN Type      : regular
AS Number       : None            Router Id      : 10.20.30.40
ECMP            : Enabled          ECMP Max Routes : 1
Max IPv4 Routes : No Limit         Auto Bind      : MPLS
Max IPv6 Routes : No Limit
Ignore NH Metric : Disabled
Hash Label     : Enabled
Vrf Target      : None
Vrf Import      : None
Vrf Export      : None
MVPN Vrf Target : None
MVPN Vrf Import : None
MVPN Vrf Export : None

SAP Count       : 0                SDP Bind Count  : 1
-----
Service Access & Destination Points
-----
Identifier                               Type      AdmMTU  OprMTU  Adm  Opr
-----
sdp:2000:1 S(101.101.101.101)            TLDP      1500    1500    Up   Down
=====
*A:SetupCLI#
```

## dhcp

**Syntax** dhcp

**Context** show>service>id

**Description** This command enables the context to display DHCP information for the specified service.

## lease-state

**Syntax** **lease-state** [[**sap** *sap-id*] [**sdp** [*sdp-id[:vc-id]*]] | [**interface** *interface-name*] | [**ip-address** *ip-address[/mask]*] | [**mac** *ieee-address*] | [**wholesaler** *service-id*] ] [**detail**]

**Context** show>service>id>dhcp

**Description** This command displays DHCP lease state related information. Refer to the following for various show command output:

- [Lease State Sample Output on page 2479](#)
- [Routed CO Sample Output on page 2480](#)
- [Wholesaler/Retailer Sample Output on page 2481](#)

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

*sdp-id* — The SDP identifier.

**Values** 1 — 17407

*vc-id* — The virtual circuit ID on the SDP ID for which to display information.

**Values** 1 — 4294967295

**interface** *interface-name* — Displays information for the specified IP interface.

**ip-address** *ip-address* — Displays information associated with the specified IP address.

**detail** — Displays detailed information.

**wholesaler** *service-id* — The VPRN service ID of the wholesaler. When specified in this context, SAP, SDP, interface, IP address and MAC parameters are ignored.

**Values** 1 — 2147483647

### Sample Output

```
*A:ALA-48>config# show service id 101 dhcp lease-state
=====
DHCP lease state table, service 101
=====
IP Address           Mac Address          Sap/Sdp Id           Remaining Lease      MC
                    LifeTime            Origin              Stdby
-----
102.1.1.52           00:00:1f:bd:00:bb   lag-1:101           00h02m56s   DHCP-R
103.3.2.62           00:00:1f:bd:00:c6   lag-1:105           00h02m59s   Radius
-----
Number of lease states : 2
=====
*A:ALA-48>config#

*A:ALA-48>config# show service id 105 dhcp lease-state wholesaler 101
=====
DHCP lease state table, service 105
```

## Show, Clear, Debug Commands

```
=====
IP Address      Mac Address      Sap/Sdp Id      Remaining Lease   MC
                  LifeTime      Origin      Stdbby
-----
Wholesaler 101 Leases
-----
103.3.2.62      00:00:1f:bd:00:c6 lag-1:105      00h00m39s  Radius
-----
Number of lease states : 1
=====
*A:ALA-48>config#
```

### Routed CO Sample Output

```
A:ALA-_Dut-A# show service id 13 dhcp lease-state
=====
DHCP lease state table, service 13
=====
IP Address      Mac Address      Sap/Sdp Id      Remaining Lease   MC
                  LifeTime      Origin      Stdbby
-----
13.13.40.1      00:00:00:00:00:13 1/1/1:13      00h00m58s  Radius
-----
Number of lease states : 1
=====
A:ALA-_Dut-A#

A:ALA-_Dut-A# show service id 13 dhcp lease-state detail
=====
DHCP lease states for service 13
=====
Service ID      : 13
IP Address      : 13.13.40.1
Mac Address     : 00:00:00:00:00:13
Subscriber-interface : ies-13-13.13.1.1
Group-interface : intf-13
SAP             : 1/1/1:13
Remaining Lifetime : 00h00m58s
Persistence Key : N/A

Sub-Ident       : "TEST"
Sub-Profile-String : "ADSL GO"
SLA-Profile-String : "BE-Video"
Lease ANCP-String : ""

Sub-Ident origin : Radius
Strings origin   : Radius
Lease Info origin : Radius

Ip-Netmask      : 255.255.0.0
Broadcast-Ip-Addr : 13.13.255.255
Default-Router  : N/A
Primary-Dns     : 13.13.254.254
Secondary-Dns   : 13.13.254.253

ServerLeaseStart : 12/24/2006 23:48:23
ServerLastRenew  : 12/24/2006 23:48:23
ServerLeaseEnd   : 12/24/2006 23:49:23
Session-Timeout  : 0d 00:01:00
DHCP Server Addr : N/A

Persistent Relay Agent Information
```

```

Circuit Id       : ancstb6_Dut-A|13|intf-13|0|13
Remote Id        : stringtest
-----
Number of lease states : 1
=====
A:ALA-_Dut-A#

```

### Wholesaler/Retailer Sample Output

```

A:ALA-_Dut-A# show service id 2000 dhcp lease-state detail
=====
DHCP lease states for service 2000
=====
Wholesaler 1000 Leases
-----
Service ID       : 1000
IP Address       : 13.13.1.254
Mac Address      : 00:00:00:00:00:13
Subscriber-interface : whole-sub
Group-interface  : intf-13
Retailer         : 2000
Retailer If      : retail-sub
SAP              : 1/1/1:13
Remaining Lifetime : 00h09m59s
Persistence Key   : N/A

Sub-Ident        : "TEST"
Sub-Profile-String : "ADSL GO"
SLA-Profile-String : "BE-Video"
Lease ANCP-String : ""

Sub-Ident origin : Retail DHCP
Strings origin   : Retail DHCP
Lease Info origin : Retail DHCP

Ip-Netmask       : 255.255.0.0
Broadcast-Ip-Addr : 13.13.255.255
Default-Router   : N/A
Primary-Dns      : N/A
Secondary-Dns    : N/A

ServerLeaseStart : 12/25/2006 00:29:41
ServerLastRenew  : 12/25/2006 00:29:41
ServerLeaseEnd   : 12/25/2006 00:39:41
Session-Timeout  : 0d 00:10:00
DHCP Server Addr : 10.232.237.2

Persistent Relay Agent Information
  Circuit Id      : 1/1/1:13
  Remote Id       : stringtest
-----
Number of lease states : 1
=====
A:ALA-_Dut-A#

```

## statistics

**Syntax**    **statistics [sap sap-id]**  
**statistics [sdp sdp-id:vc-id]**

## Show, Clear, Debug Commands

**statistics** [**interface** *interface-name*]

**Context** show>service>id>dhcp

**Description** Displays DHCP statistics information.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

*sdp-id* — The SDP identifier.

**Values** 1 — 17407

*vc-id* — The virtual circuit ID on the SDP ID for which to display information.

**Values** 1 — 4294967295

**interface** *interface-name* — Displays information for the specified IP interface.

**Show DHCP Statistics Output** — The following table describes the output fields for DHCP statistics.

Label	Description
Received Packets	The number of packets received from the DHCP clients.
Transmitted Packets	The number of packets transmitted to the DHCP clients.
Received Malformed Packets	The number of corrupted/invalid packets received from the DHCP clients.
Received Untrusted Packets	The number of untrusted packets received from the DHCP clients. In this case, a frame is dropped due to the client sending a DHCP packet with Option 82 filled in before “trust” is set under the DHCP interface command.
Client Packets Discarded	The number of packets received from the DHCP clients that were discarded.
Client Packets Relayed	The number of packets received from the DHCP clients that were forwarded.
Client Packets Snooped	The number of packets received from the DHCP clients that were snooped.
Server Packets Discarded	The number of packets received from the DHCP server that were discarded.
Server Packets Relayed	The number of packets received from the DHCP server that were forwarded.
Server Packets Snooped	The number of packets received from the DHCP server that were snooped.

### Sample Output

```
A:sim1# show service id 11 dhcp statistics
=====
DHCP Global Statistics, service 11
```

```

=====
Rx Packets                : 32
Tx Packets                : 12
Rx Malformed Packets     : 0
Rx Untrusted Packets     : 0
Client Packets Discarded  : 0
Client Packets Relayed    : 11
Client Packets Snooped    : 21
Server Packets Discarded  : 0
Server Packets Relayed    : 0
Server Packets Snooped    : 0
=====
A:sim1#

```

## gsmp

**Syntax** **gsmp**

**Context** show>service>id

**Description** This command displays GSMP information.

## neighbors

**Syntax** **neighbors group** [*name*] [*ip-address*]

**Context** show>service>id>gsmp

**Description** This command displays GSMP neighbor information.

**Parameters** **group** — A GSMP group defines a set of GSMP neighbors which have the same properties.  
*name* — Specifies a GSMP group name is unique only within the scope of the service in which it is defined.  
*ip-address* — Specifies the ip-address of the neighbor.

### Sample Output

These commands show the configured neighbors per service, regardless of the fact there exists an open TCP connection with this neighbor. The admin state is shown because for a neighbor to be admin enabled, the service, gsmp node, group node and the neighbor node in this service must all be in 'no shutdown' state. Session gives the number of session (open TCP connections) for each configured neighbor.

```

A:active>show>service>id>gsmp# neighbors
=====
GSMP neighbors
=====
Group                Neighbor                AdminState  Sessions
-----
dslam1                192.168.1.2            Enabled     0
dslam1                192.168.1.3            Enabled     0
-----
Number of neighbors shown: 2
=====
A:active>show>service>id>gsmp#

```

## Show, Clear, Debug Commands

```
A:active>show>service>id>gsmp# neighbors group dslam1
=====
GSMP neighbors
=====
Group                Neighbor            AdminState  Sessions
-----
dslam1                192.168.1.2        Enabled     0
dslam1                192.168.1.3        Enabled     0
-----
Number of neighbors shown: 2
=====
A:active>show>service>id>gsmp#

A:active>show>service>id>gsmp# neighbors group dslam1 192.168.1.2
=====
GSMP neighbors
=====
Group                Neighbor            AdminState  Sessions
-----
dslam1                192.168.1.2        Enabled     0
=====
A:active>show>service>id>gsmp#
```

## sessions

**Syntax** `sessions [group name] neighbor ip-address [port port-number] [association] [statistics]`

**Context** `show>service>id>gsmp`

**Description** This command displays GSMP sessions information.

**Parameters**

- group** — A GSMP group defines a set of GSMP neighbors which have the same properties.
- name** — Specifies a GSMP group name is unique only within the scope of the service in which it is defined.
- ip-address** — Specifies the ip-address of the neighbor.
- port** — Specifies the neighbor TCP port number use for this ANCP session.

**Values** 0 — 65535

- association** — Displays to what object the ANCP-string is associated.
- statistics** — Displays statistics information about an ANCP session known to the system.

### Sample Output

This show command gives information about the open TCP connections with DSLAMs.

```
A:active>show>service>id>gsmp# sessions
=====
GSMP sessions for service 999 (VPRN)
=====
Port  Ngbr-IPAddr      Gsmp-Group
-----
40590 192.168.1.2      dslam1
-----
Number of GSMP sessions : 1
=====
A:active>show>service>id>gsmp#
```



```
A:active>show>service>id>gsmp# sessions neighbor 192.168.1.2 port 40590
=====
GSMP sessions for service 999 (VPRN), neighbor 192.168.1.2, Port 40590
=====
State           : Established
Peer Instance   : 1                Sender Instance : a3cf58
Peer Port       : 0                Sender Port      : 0
Peer Name       : 12:12:12:12:12:12 Sender Name       : 00:00:00:00:00:00
Timeouts        : 0                Max. Timeouts   : 3
Peer Timer      : 100              Sender Timer     : 100
Capabilities    : DTD OAM
Conf Capabilities : DTD OAM
Priority Marking : dscp nc2
Local Addr.     : 192.168.1.4
Conf Local Addr. : N/A
=====
A:active>show>service>id>gsmp#
```

```
A:active>show>service>id>gsmp# sessions neighbor 192.168.1.2 port 40590 association
=====
ANCP-Strings
=====
ANCP-String                                           Assoc. State
-----
No ANCP-Strings found
=====
A:active>show>service>id>gsmp#
```

```
A:active>show>service>id>gsmp# sessions neighbor 192.168.1.2 port 40590 statistics
=====
GSMP session stats, service 999 (VPRN), neighbor 192.168.1.2, Port 40590
=====
Event                                     Received Transmitted
-----
Dropped                                  0         0
Syn                                       1         1
Syn Ack                                  1         1
Ack                                       14        14
Rst Ack                                  0         0
Port Up                                   0         0
Port Down                                 0         0
OAM Loopback                             0         0
=====
A:active>show>service>id>gsmp#
```

Note: The association command gives an overview of each ANCP string received from this session.

```
A:active>show>service>id>gsmp# sessions neighbor 192.168.1.2 port 40590 association
=====
ANCP-Strings
=====
ANCP-String                                           Assoc.
State
-----
7330-ISAM-E47 atm 1/1/01/01:19425.64048             ANCP    Up
-----
Number of ANCP-Strings : 1
=====
A:active>show>service>id>gsmp#
```

## host

**Syntax** **host** [**sap** *sap-id*] [**detail**]  
**host summary**  
**host** [**detail**] **wholesaler** *service-id*

**Context** show>service>id

**Description** This command displays static host information configured on this service.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

**summary** — Displays summary host information.

**wholesaler** *service-id* — The service ID of the wholesaler.

**Values** 1 — 2147483647

## summary

**Syntax** **summary**

**Context** show>service>id>dhcp

**Description** This command displays DHCP configuration summary information.

**Show Service-ID DHCP Summary** — The following table describes show service-id DHCP summary output fields:

Label	Description
Sap/Sdp	The configuration identification, expressed by a string containing “card/mda/port/:logical-id”.
Snoop	Yes — The packets received from the DHCP clients were snooped. No — The packets received from the DHCP clients were not snooped.
Used/Provided	Used — The number of lease-states that are currently in use on a specific interface, that is, the number of clients on that interface got an IP address by DHCP. This value is always less than or equal to the ‘Provided’ field. Provided — The lease-populate value that is configured for a specific interface.
Arp Reply Agent	Displays whether or not there is proper handling of received ARP requests from subscribers.
Info Option	Keep — The existing information is kept on the packet and the router does not add any additional information. Replace — On ingress, the existing information-option is replaced with the information-option from the router. Drop — The packet is dropped and an error is logged.

Label	Description
Admin State	Indicates the administrative state.

### Sample Output

```
A:ALA-49# show service id 1 dhcp summary
=====
DHCP Summary, service 1
=====
Interface Name          Arp      Used/      Info      Admin
  SapId/Sdp             Populate Provided   Option    State
-----
SpokeSDP                No        0/0        Keep      Up
  sdp:spoke-3:4          0/0
test                    No        0/0        Keep      Up
  sap:1/1/4:50/5        0/0
to-cel                  No        0/0        Keep      Up
  sap:1/1/10:1          0/0
-----
Interfaces: 3
=====
A:ALA-49#
```

## interface

**Syntax** `interface [ip-address | ip-int-name] [interface-type] [detail] [family]} summary]`

**Context** `show>service>id`

**Description** Displays information for the IP interfaces associated with the service.  
If no optional parameters are specified, a summary of all IP interfaces associated to the service are displayed.

**Parameters** *ip-address* — The IP address of the interface for which to display information.

**Values** 1.0.0.0 — 223.255.255.255

*ip-int-name* — The IP interface name for which to display information.

**family** — Specifies the family to display.

**Values** ipv4, ipv6

*interface-type* — Specifies the interface type.

**Values** subscriber, group, redundant

**detail** — Displays detailed IP interface information.

**Default** IP interface summary output.

**Output** **Show Service-ID Interface** — The following table describes show service-id interface output fields:

Label	Description
Interface-Name	The name used to refer to the interface.
Type	Specifies the interface type.
IP-Address	Specifies the IP address/IP subnet/broadcast address of the interface.
Adm	The desired state of the interface.
Opr	The operating state of the interface.
<b>Interface</b>	
If Name	The name used to refer to the interface.
Admin State	The desired state of the interface.
Oper State	The operating state of the interface.
IP Addr/mask	Specifies the IP address/IP subnet/broadcast address of the interface.
<b>Details</b>	
If Index	The index corresponding to this interface. The primary index is 1. For example, all interfaces are defined in the Base virtual router context.
If Type	Specifies the interface type.
Port Id	Specifies the SAP's port ID.
SNTP B.Cast	Specifies whether SNTP broadcast client mode is enabled or disabled.
Arp Timeout	Specifies the timeout for an ARP entry learned on the interface.
MAC Address	Specifies the 48-bit IEEE 802.3 MAC address.
ICMP Mask Reply	Specifies whether ICMP mask reply is enabled or disabled.
Cflowd	Specifies whether Cflowd collection and analysis on the interface is enabled or disabled.
<b>ICMP Details</b>	
Redirects	Specifies the rate for ICMP redirect messages.
Unreachables	Specifies the rate for ICMP unreachable messages.
TTL Expired	Specifies the rate for ICMP TTL messages.

**Sample Output**

```
*A:ALA-12# show service id 321 interface
=====
Interface Table
=====
Interface-Name          Type IP-Address          Adm   Opr   Type
-----
test                    Pri  190.11.1.1/24        Up    Up    IES
=====
```

```

Interfaces : 1
=====
*A:ALA-12#

A:ALA-49# show service id 88 interface detail
=====
Interface Table
=====
Interface
-----
If Name      : Sector A
Admin State  : Up                               Oper State   : Down
Protocols    : None

IP Addr/mask : Not Assigned
-----
Details
-----
Description  :
If Index     : 26                               Virt. If Index : 26
SAP Id       : 7/1/1.2.2
TOS Marking  : Untrusted                       If Type       : IES
SNTP B.Cast  : False                           IES ID        : 88
MAC Address  : Not configured.                 Arp Timeout   : 14400
IP MTU       : 1500                             ICMP Mask Reply : True
Arp Populate : Disabled
Cflowd      : None

Proxy ARP Details
Proxy ARP    : Enabled                           Local Proxy ARP : Disabled
Policies     : ProxyARP

DHCP Details
Admin State  : Up                               Lease Populate : 0
Action       : Keep                             Trusted        : Disabled
ICMP Details
Redirects    : Number - 100                     Time (seconds) - 10
Unreachables : Number - 100                     Time (seconds) - 10
TTL Expired  : Number - 100                     Time (seconds) - 10
-----
Interface
-----
If Name      : test
Admin State  : Up                               Oper State   : Down
Protocols    : None

IP Addr/mask : Not Assigned
-----
Details
-----
Description  :
If Index     : 27                               Virt. If Index : 27
SAP Id       : 10/1/2:0
TOS Marking  : Untrusted                       If Type       : IES
SNTP B.Cast  : False                           IES ID        : 88
MAC Address  : Not configured.                 Arp Timeout   : 14400
IP MTU       : 1500                             ICMP Mask Reply : True
Arp Populate : Disabled
Cflowd      : None

Proxy ARP Details
Proxy ARP    : Disabled                           Local Proxy ARP : Disabled

```

## Show, Clear, Debug Commands

```
DHCP Details
Admin State : Up
Action      : Keep
Lease Populate : 0
Trusted     : Disabled

ICMP Details
Redirects   : Number - 100
Unreachables : Number - 100
TTL Expired : Number - 100
Time (seconds) - 10
Time (seconds) - 10
Time (seconds) - 10
-----
Interfaces : 2
=====
A:ALA-49#

*A:SetupCLI# show service id 3 interface "ab" detail
=====
Interface Table
-----
Interface
-----
If Name      : ab
Admin State  : Up
Oper (v4/v6) : Down/--
Protocols    : None

IP Addr/mask : Not Assigned
-----
Details
-----
Description  : (Not Specified)
If Index     : 2
Last Oper Chg: 10/08/2009 07:07:58
SDP Id       : spoke-2000:1
Virt. If Index : 2
Global If Index : 329

Spoke-SDP Details
Admin State  : Up
Oper State   : Down
Hash Label   : Enabled
Flags        : SvcAdminDown SdpOperDown
              NoIngVCLLabel NoEgrVCLLabel

TOS Marking  : Trusted
SNTP B.Cast  : False
MAC Address  : 76:6d:ff:00:00:00
IP Oper MTU  : 0
Arp Populate : Disabled
Cflowd       : None
LdpSyncTimer : None
LSR Load Bal* : system
uRPF Chk     : disabled
uRPF Fail By* : 0
If Type      : VPRN
Arp Timeout  : 14400
ICMP Mask Reply : True
Host Conn Verify : Disabled
uRPF Chk Fail Pk* : 0

Proxy ARP Details
Rem Proxy ARP: Disabled
Policies     : none
Local Proxy ARP : Disabled

Proxy Neighbor Discovery Details
Local Pxy ND : Disabled
Policies     : none

DHCP no local server

DHCP Details
Description  : (Not Specified)
```

## VPRN Show Commands

```

Admin State   : Down
Gi-Addr      : Not configured
Action       : Keep
Lease Populate : 0
Gi-Addr as Src Ip: Disabled
Trusted      : Disabled
  
```

### DHCP Proxy Details

```

Admin State   : Down
Lease Time    : N/A
Emul. Server  : Not configured
  
```

### Subscriber Authentication Details

```
Auth Policy   : None
```

### DHCP6 Relay Details

```

Description   : (Not Specified)
Admin State   : Down
Oper State    : Down
If-Id Option  : None
Src Addr      : Not configured
Lease Populate : 0
Nbr Resolution : Disabled
Remote Id     : Disabled
  
```

### DHCP6 Server Details

```
Admin State   : Down
Max. Lease States: 8000
```

### ICMP Details

```

Redirects     : Number - 100
Unreachables  : Number - 100
TTL Expired   : Number - 100
Time (seconds) - 10
Time (seconds) - 10
Time (seconds) - 10
  
```

### IPCP Address Extension Details

```

Peer IP Addr* : Not configured
Peer Pri DNS* : Not configured
Peer Sec DNS* : Not configured
  
```

### Routed VPLS Details

```
VPLS Name      :
Binding Status : Up
```

```
-----
Interfaces : 1
=====
```

```

* indicates that the corresponding row element may have been truncated.
*A:SetupCLIp#
  
```

The Oper Hash Label and Hash Lbl Sig Cap spoke-sdp fields display when signal-capability is enabled and operational state of hash-label in datapath.

### ----- Service Destination Points(SDPs) -----

```
Sdp Id 1:555 -(2.2.2.2)
-----
```

```

Description   : (Not Specified)
SDP Id        : 1:555
Spoke Descr   : (Not Specified)
VC Type       : Ether
Admin Path MTU : 0
Far End       : 2.2.2.2
Tunnel Far End : n/a
Hash Label    : Disabled
Oper Hash Label : Disabled
Type          : Spoke
VC Tag        : n/a
Oper Path MTU : 1568
Delivery      : MPLS
LSP Types     : RSVP
Hash Lbl Sig Cap : Disabled
  
```

```
Admin State   : Up
Oper State    : Up
```

## Show, Clear, Debug Commands

```
Acct. Pol          : None                Collect Stats     : Disabled
Ingress Label     : 131065              Egress Label     : 131059
Ingr Mac Fltr-Id : n/a                Egr Mac Fltr-Id : n/a
Ingr IP Fltr-Id  : n/a                Egr IP Fltr-Id  : n/a
Ingr IPv6 Fltr-Id : n/a              Egr IPv6 Fltr-Id : n/a
Admin ControlWord : Not Preferred      Oper ControlWord : False
Admin BW(Kbps)   : 0                  Oper BW(Kbps)    : 0
Last Status Change : 11/25/2010 13:06:14 Signaling        : TLDP
Last Mgmt Change  : 11/24/2010 13:00:48 Force Vlan-Vc   : Disabled
Endpoint         : N/A                Precedence       : 4
PW Status Sig    : Enabled
Class Fwding State : Down
Flags            : None
Peer Pw Bits     : None
Peer Fault Ip    : None
Peer Vccv CV Bits : lspPing
Peer Vccv CC Bits : mplsRouterAlertLabel
Application Profile: None
Standby Sig Slave : False
```

```
.....
.....
```

```
=====
```

## retailers

**Syntax**    **retailers**

**Context**    show>service>id

**Description**    This command displays the service ID of the retailer subscriber service to which this DHCP lease belongs.

### Sample Output

```
*A:ALA-48>config# show service id 101 retailers
=====
Retailers for service 101
=====
Retailer Svc ID          Num Static Hosts      Num Dynamic Hosts
-----
102                      3                      1
105                      0                      1
-----
Number of retailers : 2
=====
*A:ALA-48>config#
```

## wholesalers

**Syntax**    **wholesalers**

**Context**    show>service>id

**Description**    This command displays service wholesaler information.



**Sample Output**

```
*A:ALA-48>config# show service id 102 wholesalers
=====
Wholesalers for service 102
=====
Wholesaler Svc ID          Num Static Hosts      Num Dynamic Hosts
-----
101                        3                      1
-----
Number of wholesalers : 1
=====
*A:ALA-48>config#
```

Wholesaler information can also be displayed in the lease-state context.

```
*A:ALA-48>config# show service id 105 dhcp lease-state wholesaler 101
=====
DHCP lease state table, service 105
=====
IP Address      Mac Address      Sap/Sdp Id      Remaining Lease  MC
                LifeTime        Origin          Stdby
-----
Wholesaler 101 Leasesok
-----
103.3.2.62     00:00:1f:bd:00:c6 lag-1:105      00h00m39s  Radius
-----
Number of lease states : 1
=====
*A:ALA-48>config#
```

## sap

**Syntax** `sap sap-id [detail]`

**Context** `show>service>id`

**Description** Displays information for the SAPs associated with the service.  
If no optional parameters are specified, a summary of all associated SAPs is displayed.

**Parameters** *sap-id* — The ID that displays SAPs for the service. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

**detail** — Displays detailed information for the SAP.

**Output** **Show Service-ID SAP** — The following table describes show service SAP fields:

### Sample Output

Label	Description
Service Id	The service identifier.
SAP	The SAP and qtag.
Encap	The encapsulation type of the SAP.
Ethertype	Specifies an Ethernet type II Ether type value.
Admin State	The administrative state of the SAP.
Oper State	The operating state of the SAP.
Flags	Specifies the conditions that affect the operating status of this SAP. Display output includes: ServiceAdminDown, SapAdminDown, InterfaceAdminDown, PortOperDown, PortMTUTooSmall, L2OperDown, SapIngressQoSMismatch, SapEgressQoSMismatch, RelearnLimitExceeded, RxProtSrcMac, ParentIfAdminDown, NoSapIpipeCeIpAddr, TodResourceUnavail, TodMssResourceUnavail, SapParamMismatch, CemSapNoEcidOrMacAddr, StandByForMcRing, ServiceMTUTooSmall, SapIngressNamedPoolMismatch, SapEgressNamedPoolMismatch, NoSapEpipeRingNode.
Last Status Change	Specifies the time of the most recent operating status change to this SAP.
Last Mgmt Change	Specifies the time of the most recent management-initiated change to this SAP.
Admin MTU	The desired largest service frame size (in octets) that can be transmitted through the SAP to the far-end router, without requiring the packet to be fragmented.
Oper MTU	The actual largest service frame size (in octets) that can be transmitted through the SAP to the far-end router, without requiring the packet to be fragmented.

Label	Description (Continued)
Ingress qos-policy	The ingress QoS policy ID assigned to the SAP.
Egress qos-policy	The egress QoS policy ID assigned to the SAP.
Ingress Filter-Id	The ingress filter policy ID assigned to the SAP.
Egress Filter-Id	The egress filter policy ID assigned to the SAP.
Acct. Pol	The accounting policy ID assigned to the SAP.
Collect Stats	Specifies whether collect stats is enabled.
Dropped	The number of packets and octets dropped due to SAP state, ingress MAC or IP filter, same segment discard, bad checksum, etc.
Off. HiPrio	The number of high priority packets and octets, as determined by the SAP ingress QoS policy, offered by the Pchip to the Qchip.
Off. LowPrio	The number of low priority packets and octets, as determined by the SAP ingress QoS policy, offered by the Pchip to the Qchip.
Off. Uncolor	The number of uncolored packets and octets, as determined by the SAP ingress QoS policy, offered by the Pchip to the Qchip.
Dro. HiPrio	The number of high priority packets and octets, as determined by the SAP ingress QoS policy, dropped by the Qchip due to: MBS exceeded, buffer pool limit exceeded, etc.
Dro. LowPrio	The number of low priority packets and octets, as determined by the SAP ingress QoS policy, dropped by the Qchip due to: MBS exceeded, buffer pool limit exceeded, etc.
For. InProf	The number of in-profile packets and octets (rate below CIR) forwarded by the ingress Qchip.
For. OutProf	The number of out-of-profile packets and octets discarded by the egress Qchip due to MBS exceeded, buffer pool limit exceeded, etc.
Dro. InProf	The number of in-profile packets and octets discarded by the egress Qchip due to MBS exceeded, buffer pool limit exceeded, etc.
Dro. OutProf	The number of out-of-profile packets and octets discarded by the egress Qchip due to MBS exceeded, buffer pool limit exceeded, etc.
For. InProf	The number of in-profile packets and octets (rate below CIR) forwarded by the egress Qchip.
For. OutProf	The number of out-of-profile packets and octets (rate above CIR) forwarded by the egress Qchip.
Ingress TD Profile	The profile ID applied to the ingress SAP.
Egress TD Profile	The profile ID applied to the egress SAP.
Alarm Cell Handling	The indication that OAM cells are being processed.

Label	Description (Continued)	
AAI-5 Encap	The AAI-5 encapsulation type.	
*A:ALA-12# show service id 321 sap 1/1/4:0		
=====		
Service Access Points(SAP)		
=====		
Service Id	: 321	
SAP	: 1/1/4:0	
Dot1Q Ethertype	: 0x8100	
Admin State	: Up	
Flags	: PortOperDown	
	SapIngressQoSMismatch	
Last Status Change	: 02/03/2007 12:58:37	
Last Mgmt Change	: 02/03/2007 12:59:10	
Admin MTU	: 1518	
Ingress qos-policy	: 100	
Ingress Filter-Id	: n/a	
Multi Svc Site	: None	
Acct. Pol	: None	
Encap	: q-tag	
QinQ Ethertype	: 0x8100	
Oper State	: Down	
Oper MTU	: 1518	
Egress qos-policy	: 1	
Egress Filter-Id	: n/a	
Collect Stats	: Disabled	
=====		
*A:ALA-12#		
*A:ALA-12# show service id 321 sap 1/1/4:0 detail		
=====		
Service Access Points(SAP)		
=====		
Service Id	: 321	
SAP	: 1/1/4:0	
Dot1Q Ethertype	: 0x8100	
Admin State	: Up	
Flags	: PortOperDown	
	SapIngressQoSMismatch	
Last Status Change	: 02/03/2007 12:58:37	
Last Mgmt Change	: 02/03/2007 12:59:10	
Admin MTU	: 1518	
Ingress qos-policy	: 100	
Ingress Filter-Id	: n/a	
Multi Svc Site	: None	
Acct. Pol	: None	
Encap	: q-tag	
QinQ Ethertype	: 0x8100	
Oper State	: Down	
Oper MTU	: 1518	
Egress qos-policy	: 1	
Egress Filter-Id	: n/a	
Collect Stats	: Disabled	
-----		
Sap Statistics		
-----		
	Packets	Octets
Forwarding Engine Stats		
Dropped	: 0	0
Off. HiPrio	: 0	0
Off. LowPrio	: 0	0
Off. Uncolor	: 0	0
Queueing Stats(Ingress QoS Policy 100)		
Dro. HiPrio	: 0	0
Dro. LowPrio	: 0	0
For. InProf	: 0	0
For. OutProf	: 0	0
Queueing Stats(Egress QoS Policy 1)		
Dro. InProf	: 0	0
Dro. OutProf	: 0	0

```

For. InProf          : 0                0
For. OutProf         : 0                0
-----
Sap per Queue stats
-----
                Packets                Octets

Ingress Queue 1 (Unicast) (Priority)
Off. HiPrio         : 0                0
Off. LoPrio         : 0                0
Dro. HiPrio         : 0                0
Dro. LoPrio         : 0                0
For. InProf         : 0                0
For. OutProf        : 0                0

Ingress Queue 10 (Unicast) (Priority)
Off. HiPrio         : 0                0
Off. LoPrio         : 0                0
Dro. HiPrio         : 0                0
Dro. LoPrio         : 0                0
For. InProf         : 0                0
For. OutProf        : 0                0

'''
-----
ATM SAP Configuration Information
-----
Ingress TD Profile : 1 Egress TD Profile : 1
Alarm Cell Handling: Enabled AAL-5 Encap : VC-MUX
-----
...
=====
*A:ALA-12#

```

## sdp

**Syntax** `sdp [sdp-id | far-end ip-addr] [detail]`

**Context** show>service>id

**Description** Displays information for the SDPs associated with the service. If no optional parameters are specified, a summary of all associated SDPs is displayed.

**Parameters** *sdp-id* — Displays only information for the specified SDP ID.

**Default** All SDPs.

**Values** 1 — 17407

*far-end ip-addr* — Displays only SDPs matching with the specified far-end IP address.

**Default** SDPs with any far-end IP address.

**detail** — Displays detailed SDP information.

**Output** **Show Service-ID SDP** — The following table describes show service-id SDP output fields:

Label	Description
Sdp Id	The SDP identifier.
Type	Indicates whether the SDP is a spoke or a mesh.
Split Horizon Group	Name of the split horizon group that the SDP belongs to.
VC Type	Displays the VC type: ether or vlan.
VC Tag	Displays the explicit dot1Q value used when encapsulating to the SDP far end.
I. Lbl	The VC label used by the far-end device to send packets to this device in this service by the SDP.
Admin Path MTU	The operating path MTU of the SDP is equal to the admin path MTU (when one is set) or the dynamically computed tunnel MTU, when no admin path MTU is set (the default case.)
Oper Path MTU	The actual largest service frame size (in octets) that can be transmitted through this SDP to the far-end router, without requiring the packet to be fragmented.
Far End	Specifies the IP address of the remote end of the GRE or MPLS tunnel defined by this SDP.
Delivery	Specifies the type of delivery used by the SDP: GRE or MPLS.
Admin State	The administrative state of this SDP.
Oper State	The operational state of this SDP.
Ingress Label	The label used by the far-end device to send packets to this device in this service by this SDP.

Label	Description (Continued)
Egress Label	The label used by this device to send packets to the far-end device in this service by the SDP.
Last Changed	The date and time of the most recent change to the SDP.
Signaling	Specifies the signaling protocol used to obtain the ingress and egress labels used in frames transmitted and received on this SDP.
Admin State	The administrative state of the keepalive process.
Oper State	he operational state of the keepalive process.
Hello Time	Specifies how often the SDP echo request messages are transmitted on this SDP.
Max Drop Count	Specifies the maximum number of consecutive SDP echo request messages that can be unacknowledged before the keepalive protocol reports a fault.
Hello Msg Len	Specifies the length of the SDP echo request messages transmitted on this SDP.
Hold Down Time	Specifies the amount of time to wait before the keepalive operating status is eligible to enter the alive state.
I. Fwd. Pkts.	Specifies the number of forwarded ingress packets.
I. Dro. Pkts.	Specifies the number of dropped ingress packets.
E. Fwd. Pkts.	Specifies the number of forwarded egress packets.
Associated LSP List	When the SDP type is MPLS, a list of LSPs used to reach the far-end router displays. All the LSPs in the list must terminate at the IP address specified in the far end field. If the SDP type is GRE, then the following message displays: SDP delivery mechanism is not MPLS.

### Sample Output

```
A:Dut-A# show service id 1 sdp detail
=====
Services: Service Destination Points Details
=====
  Sdp Id 1:1  -(10.20.1.2)
-----
Description      : Default sdp description
SDP Id           : 1:1                               Type           : Spoke
VC Type          : Ether                             VC Tag         : n/a
Admin Path MTU   : 0                                 Oper Path MTU  : 9186
Far End          : 10.20.1.2                         Delivery        : MPLS

Admin State      : Up                               Oper State     : Up
Acct. Pol       : None                             Collect Stats  : Disabled
Ingress Label    : 2048                            Egress Label   : 2048
Ing mac Fltr    : n/a                              Egr mac Fltr   : n/a
Ing ip Fltr     : n/a                              Egr ip Fltr    : n/a
Ing ipv6 Fltr   : n/a                              Egr ipv6 Fltr  : n/a
```

## Show, Clear, Debug Commands

```
Admin ControlWord : Not Preferred          Oper ControlWord : False
Last Status Change : 05/31/2007 00:45:43  Signaling         : None
Last Mgmt Change   : 05/31/2007 00:45:43
Class Fwding State : Up
Flags              : None
Peer Pw Bits       : None
Peer Fault Ip      : None
Peer Vccv CV Bits  : None
Peer Vccv CC Bits  : None
Max Nbr of MAC Addr: No Limit
Learned MAC Addr   : 0

MAC Learning       : Enabled
MAC Aging          : Enabled
L2PT Termination   : Disabled
MAC Pinning        : Disabled

MAC Learning       : Enabled
MAC Aging          : Enabled
L2PT Termination   : Disabled
MAC Pinning        : Disabled

KeepAlive Information :
Admin State        : Disabled
Hello Time         : 10
Max Drop Count     : 3

Oper State         : Disabled
Hello Msg Len      : 0
Hold Down Time     : 10

Statistics         :
I. Fwd. Pkts.     : 0
I. Fwd. Octs.     : 0
E. Fwd. Pkts.     : 0
MCAC Policy Name   :
MCAC Max Unconst BW: no limit
MCAC In use Mand BW: 0
MCAC In use Opnl BW: 0

I. Dro. Pkts.     : 0
I. Dro. Octs.     : 0
E. Fwd. Octets    : 0
MCAC Max Mand BW  : no limit
MCAC Avail Mand BW: unlimited
MCAC Avail Opnl BW: unlimited

Associated LSP LIST :
Lsp Name          : A_B_1
Admin State       : Up
Time Since Last Tr*: 00h26m35s

Oper State        : Up

Lsp Name          : A_B_2
Admin State       : Up
Time Since Last Tr*: 00h26m35s

Oper State        : Up

Lsp Name          : A_B_3
Admin State       : Up
Time Since Last Tr*: 00h26m34s

Oper State        : Up

Lsp Name          : A_B_4
Admin State       : Up
Time Since Last Tr*: 00h26m34s

Oper State        : Up

Lsp Name          : A_B_5
Admin State       : Up
Time Since Last Tr*: 00h26m34s

Oper State        : Up

Lsp Name          : A_B_6
Admin State       : Up
Time Since Last Tr*: 00h26m34s

Oper State        : Up

Lsp Name          : A_B_7
Admin State       : Up
Time Since Last Tr*: 00h26m34s

Oper State        : Up

Lsp Name          : A_B_8
Admin State       : Up
Time Since Last Tr*: 00h26m35s

Oper State        : Up
```



```

Lsp Name          : A_B_9
Admin State       : Up                               Oper State       : Up
Time Since Last Tr* : 00h26m34s

Lsp Name          : A_B_10
Admin State       : Up                               Oper State       : Up
Time Since Last Tr* : 00h26m34s
-----
Class-based forwarding :
-----
Class forwarding    : enabled
Default LSP        : A_B_10                        Multicast LSP    : A_B_9
=====
FC Mapping Table
=====
FC Name            LSP Name
-----
af                 A_B_3
be                 A_B_1
ef                 A_B_6
h1                 A_B_7
h2                 A_B_5
l1                 A_B_4
l2                 A_B_2
nc                 A_B_8
=====
Stp Service Destination Point specifics
-----
Mac Move           : Blockable
Stp Admin State   : Up                               Stp Oper State   : Down
Core Connectivity : Down
Port Role         : N/A                             Port State       : Forwarding
Port Number       : 2049                            Port Priority    : 128
Port Path Cost    : 10                             Auto Edge       : Enabled
Admin Edge        : Disabled                        Oper Edge       : N/A
Link Type         : Pt-pt                          BPDU Encap      : Dot1d
Root Guard        : Disabled                        Active Protocol  : N/A
Last BPDU from    : N/A
Designated Bridge : N/A                             Designated Port Id: 0

Fwd Transitions   : 0                             Bad BPDUs rcvd  : 0
Cfg BPDUs rcvd   : 0                             Cfg BPDUs tx    : 0
TCN BPDUs rcvd   : 0                             TCN BPDUs tx    : 0
RST BPDUs rcvd   : 0                             RST BPDUs tx    : 0
-----
Number of SDPs : 1
-----
* indicates that the corresponding row element may have been truncated.
-----
A:Dut-A#

```

## subscriber-hosts

**Syntax** **subscriber-hosts** [sap sap-id] [ip ip-address[/mask]] [mac ieee-address] [sub-profile sub-profile-name] [sla-profile sla-profile-name] [detail]  
**subscriber-hosts** [detail] wholesaler service-id

**Context** show>service>id

## Show, Clear, Debug Commands

- Description** This command displays subscriber host information.
- Parameters** **sap** *sap-id* — Displays the specified subscriber host SAP information. See [Common CLI Command Descriptions on page 2569](#) for command syntax.
- ip-address/mask* — The IP address of the IP interface. The *ip-address* portion of the **address** command specifies the IP host address that will be used by the IP interface within the subnet. This address must be unique within the subnet and specified in dotted decimal notation.
- Values** 1.0.0.0 – 223.255.255.255 (with support of /31 subnets).  
mask: 1 — 32
- ieee-address* — Specifies the 48-bit MAC address for the static ARP in the form aa:bb:cc:dd:ee:ff or aa-bb-cc-dd-ee-ff where aa, bb, cc, dd, ee, and ff are hexadecimal numbers. Allowed values are any non-broadcast, non-multicast MAC and non-IEEE reserved MAC addresses.
- sub-profile** *sub-profile-name* — Specifies an existing subscriber profile name to be associated with the static subscriber host. The subscriber profile is configured in the **config>subscr-mgmt>sub-profile** context.
- sla-profile** *sla-profile-name* — Specifies an existing SLA profile name to be associated with the static subscriber host. The SLA profile is configured in the **config>subscr-mgmt>sla-profile** context.
- detail** — Displays detailed information.
- wholesaler** *service-id* — The VPRN service ID of the wholesaler.
- Values** 1 — 2147483648

## aggregate

- Syntax** **aggregate** [**active**]
- Context** show>router
- Description** This command displays aggregated routes.
- Parameters** **active** — This keyword filters out inactive aggregates.
- Output** **Show Aggregate Output Fields** — The following table describes router aggregate output fields.

Label	Description
Prefix	Displays the destination address of the aggregate route in dotted decimal notation.
Summary	Specifies whether the aggregate or more specific components are advertised.
AS Set	Displays an aggregate where the path advertised for the route consists of all elements contained in all paths that are being summarized.
Aggr AS	Displays the aggregator path attribute to the aggregate route.
Aggr IP-Address	The IP address of the aggregated route.
State	The operational state of the aggregated route.
No. of Aggregates	The total number of aggregated routes.

**Sample Output**

```
*A:ALA-12# show router 3 aggregate
=====
Aggregates (Service: 3)
=====
Prefix                Summary AS Set  Aggr AS    Aggr IP-Address  State
-----
No. of Aggregates: 0
-----
*A:ALA-12#

*A:Dut-A>config>router# show router aggregate

=====
Aggregates (Router: Base)
=====
Prefix                Summary AS Set  Aggr IP-Address  Aggr AS
NextHop                State
NextHopType
-----
1.2.3.0/24            False      0.0.0.0           0
2.2.2.2              Inactive
Indirect

2.2.0.0/16           False      0.0.0.0           0
Active
None
-----
No. of Aggregates: 2
=====

*A:CPM133>config>router# show router aggregate

=====
Aggregates (Router: Base)
=====
Prefix                Summary AS Set  Aggr IP-Address  Aggr AS
NextHop                State
NextHopType
-----
10.0.0.0/8           False      0.0.0.0           0
100:33              Inactive
Blackhole
-----
No. of Aggregates: 1
=====
```

**arp**

**Syntax** **arp** [*ip-address* | *ip-int-name* | *mac ieee-mac-addr*]

**Context** show>router

**Description** This command displays the router ARP table sorted by IP address.

## Show, Clear, Debug Commands

If no command line options are specified, all ARP entries are displayed.

### Parameters

*ip-addr* — Only displays ARP entries associated with the specified IP address.

*ip-int-name* — Only displays ARP entries associated with the specified IP interface name.

*mac ieee-mac-addr* — Only displays ARP entries associated with the specified MAC address.

### Output

**ARP Table Output** — The following table describes ARP table output fields:

Label	Description
IP Address	The IP address of the ARP entry.
MAC Address	The MAC address of the ARP entry.
Expiry	The age of the ARP entry.
Type	Dyn — The ARP entry is a dynamic ARP entry. Inv — The ARP entry is an inactive static ARP entry (invalid). Oth — The ARP entry is a local or system ARP entry. Sta — The ARP entry is an active static ARP entry.
Interface	The IP interface name associated with the ARP entry.
No. of ARP Entries	The number of ARP entries displayed in the list.

### Sample Output

```
*A:ALA-12# show router 3 arp
=====
ARP Table (Service: 3)
=====
IP Address      MAC Address      Expiry          Type            Interface
-----
10.10.10.103    04:67:ff:00:00:01 00h00m00s      Oth             system
10.10.4.3       00:00:00:00:00:00 00h00m00s      Oth             ALA-1-2
10.10.5.3       00:00:00:00:00:00 00h00m00s      Oth             ALA-1-3
10.10.7.3       00:00:00:00:00:00 00h00m00s      Oth             ALA-1-5
10.10.0.16     00:00:00:00:00:00 00h00m00s      Oth             bozo
10.10.3.3       00:00:00:00:00:00 00h00m00s      Oth             gizmo
10.10.2.3       00:00:00:00:00:00 00h00m00s      Oth             hobo
10.10.1.17     00:00:00:00:00:00 00h00m00s      Oth             int-cflowd
10.0.0.92       00:00:00:00:00:00 04h00m00s      Dyn             to-104
10.0.0.103      04:67:01:01:00:01 00h00m00s      Oth[I]          to-104
10.0.0.104      04:68:01:01:00:01 03h59m49s      Dyn[I]          to-104
10.10.36.2      00:00:00:00:00:00 00h00m00s      Oth             tuesday
192.168.2.98    00:03:47:c8:b4:86 00h14m37s      Dyn[I]          management
192.168.2.103   00:03:47:dc:98:1d 00h00m00s      Oth[I]          management
-----
No. of ARP Entries: 14
=====
*A:ALA-12#

*A:ALA-12# show router 3 arp 10.10.0.3
=====
ARP Table
```

```
=====
IP Address      MAC Address      Expiry   Type   Interface
-----
10.10.0.3       04:5d:ff:00:00:00 00:00:00 Oth    system
=====
```

\*A:ALA-12#

\*A:ALA-12# show router 3 arp to-ser1

```
=====
ARP Table
=====
IP Address      MAC Address      Expiry   Type   Interface
-----
10.10.13.1      04:5b:01:01:00:02 03:53:09 Dyn    to-ser1
=====
```

\*A:ALA-12#

## damping

**Syntax** **damping** [*ip-prefix/mask* | *ip-address*] [**detail**]  
**damping** [*damp-type*] [**detail**]

**Context** show>router>bgp

**Description** This command displays BGP routes with have been dampened due to route flapping. This command can be entered with or without a route parameter.

When the keyword **detail** is included, more detailed information displays.

When only the command is entered (without any parameters included except **detail**), then all dampened routes are listed.

When a parameter is specified, then the matching route or routes are listed.

When a **decayed**, **history**, or **suppressed** keyword is specified, only those types of dampened routes are listed.

**Parameters** *ip-prefix/mask* — Displays damping information for the specified IP prefix and mask length.

*ip-address* — Displays damping entry for the best match route for the specified IP address.

*damp-type* — Displays damping type for the specified IP address.

**decayed** — Displays damping entries that are decayed but are not suppressed.

**history** — Displays damping entries that are withdrawn but have history.

**suppressed** — Displays damping entries suppressed because of route damping.

**detail** — Displays detailed information.

**Output** **Show Damping Output Fields** — The following table describes BGP damping output fields:

Label	Description
BGP Router ID	The local BGP router ID.
AS	The configured autonomous system number.
Local AS	The configured or inherited local AS for the specified peer group. If not configured, then it is the same value as the AS.
Network	Route IP prefix and mask length for the route.
Flag(s)	Legend: Status codes: u- used, s-suppressed, h-history, d-decayed, *-valid. If a * is not present, then the status is invalid. Origin codes: i-IGP, e-EGP, ?-incomplete, >-best
Network	The IP prefix and mask length for the route.
From	The originator ID path attribute value.
Reuse time	The time when a suppressed route can be used again.
AS Path	The BGP AS path for the route.

Label	Description (Continued)
Peer	The router ID of the advertising router.
NextHop	BGP nexthop for the route.
Peer AS	The autonomous system number of the advertising router.
Peer Router-Id	The router ID of the advertising router.
Local Pref	BGP local preference path attribute for the route.
Age	The time elapsed since the service was enabled.
Last update	The time when BGP was updated last in second/minute/hour (SS:MM:HH) format.
FOM Present	The current Figure of Merit (FOM) value.
Number of Flaps	The number of flaps in the neighbor connection.
Reuse time	The time when the route can be reused.
Path	The BGP AS path for the route.
Applied Policy	The applied route policy name.

### Sample Output

```
*A:ALA-12# show router 3 bgp damping
=====
BGP Router ID : 10.0.0.14      AS : 65206      Local AS : 65206
=====
Legend -
Status codes : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes : i - IGP, e - EGP, ? - incomplete, - best
=====
BGP Damped Routes
=====
Flag Network          From           Reuse          AS-Path
-----
ud*i 12.149.7.0/24      10.0.28.1     00h00m00s     60203 65001 19855 3356
                                     1239 22406
si   24.155.6.0/23     10.0.28.1     00h43m41s     60203 65001 19855 3356
                                     2914 7459
si   24.155.8.0/22     10.0.28.1     00h38m31s     60203 65001 19855 3356
                                     2914 7459
si   24.155.12.0/22    10.0.28.1     00h35m41s     60203 65001 19855 3356
                                     2914 7459
si   24.155.22.0/23    10.0.28.1     00h35m41s     60203 65001 19855 3356
                                     2914 7459
si   24.155.24.0/22    10.0.28.1     00h35m41s     60203 65001 19855 3356
                                     2914 7459
si   24.155.28.0/22    10.0.28.1     00h34m31s     60203 65001 19855 3356
                                     2914 7459
si   24.155.40.0/21    10.0.28.1     00h28m24s     60203 65001 19855 3356
                                     7911 7459
si   24.155.48.0/20    10.0.28.1     00h28m24s     60203 65001 19855 3356
                                     7911 7459
ud*i 61.8.140.0/24    10.0.28.1     00h00m00s     60203 65001 19855 3356
```

## Show, Clear, Debug Commands

```

                                     4637 17447
ud*i 61.8.141.0/24      10.0.28.1      00h00m00s      60203 65001 19855 3356
                                     4637 17447
ud*i 61.9.0.0/18       10.0.28.1      00h00m00s      60203 65001 19855 3356
                                     3561 9658 6163
. . .
ud*i 62.213.184.0/23  10.0.28.1      00h00m00s      60203 65001 19855 3356
                                     6774 6774 9154
-----
```

\*A:ALA-12#

\*A:ALA-12# **show router 3 bgp damping detail**

```
=====
BGP Router ID : 10.0.0.14          AS : 65206   Local AS : 65206
=====
```

Legend -

Status codes : u - used, s - suppressed, h - history, d - decayed, \* - valid

Origin codes : i - IGP, e - EGP, ? - incomplete, - best

```
=====
BGP Damped Routes
-----
```

Network : 12.149.7.0/24

```
-----
Network      : 12.149.7.0/24      Peer      : 10.0.28.1
NextHop      : 10.0.28.1         Reuse time : 00h00m00s
Peer AS      : 60203             Peer Router-Id : 32.32.27.203
Local Pref   : none
Age          : 00h22m09s         Last update : 02d00h58m
FOM Present  : 738              FOM Last upd. : 2039
Number of Flaps : 2             Flags      : ud*i
Path         : 60203 65001 19855 3356 1239 22406
Applied Policy : default-damping-profile
-----
```

Network : 15.142.48.0/20

```
-----
Network      : 15.142.48.0/20    Peer      : 10.0.28.1
NextHop      : 10.0.28.1         Reuse time : 00h00m00s
Peer AS      : 60203             Peer Router-Id : 32.32.27.203
Local Pref   : none
Age          : 00h00m38s         Last update : 02d01h20m
FOM Present  : 2011             FOM Last upd. : 2023
Number of Flaps : 2             Flags      : ud*i
Path         : 60203 65001 19855 3356 3561 5551 1889
Applied Policy : default-damping-profile
-----
```

Network : 15.200.128.0/19

```
-----
Network      : 15.200.128.0/19   Peer      : 10.0.28.1
NextHop      : 10.0.28.1         Reuse time : 00h00m00s
Peer AS      : 60203             Peer Router-Id : 32.32.27.203
Local Pref   : none
Age          : 00h00m38s         Last update : 02d01h20m
FOM Present  : 2011             FOM Last upd. : 2023
Number of Flaps : 2             Flags      : ud*i
Path         : 60203 65001 19855 1299 702 1889
Applied Policy : default-damping-profile
-----
```

Network : 15.203.192.0/18

```
-----
Network      : 15.203.192.0/18   Peer      : 10.0.28.1
-----
```



```

NextHop          : 10.0.28.1          Reuse time       : 00h00m00s
Peer AS          : 60203              Peer Router-Id   : 32.32.27.203
Local Pref       : none
Age              : 00h00m07s          Last update      : 02d01h20m
FOM Present      : 1018              FOM Last upd.   : 1024
Number of Flaps  : 1                 Flags            : ud*i
Path             : 60203 65001 19855 1299 702 1889
Applied Policy   : default-damping-profile

```

```
-----
*A:ALA-12#
```

```
*A:ALA-12# show router 3 bgp damping 15.203.192.0/18 detail
```

```
=====
BGP Router ID : 10.0.0.14          AS : 65206   Local AS : 65206
=====
Legend -
Status codes  : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes  : i - IGP, e - EGP, ? - incomplete, - best
=====
```

```
BGP Damped Routes 15.203.192.0/18
=====
```

```
Network : 15.203.192.0/18
-----
```

```

Network          : 15.203.192.0/18    Peer           : 10.0.28.1
NextHop          : 10.0.28.1          Reuse time     : 00h00m00s
Peer AS          : 60203              Peer Router-Id : 32.32.27.203
Local Pref       : none
Age              : 00h00m42s          Last update    : 02d01h20m
FOM Present      : 2003              FOM Last upd.  : 2025
Number of Flaps  : 2                 Flags          : ud*i
Path             : 60203 65001 19855 3356 702 1889
Applied Policy   : default-damping-profile

```

```
-----
Paths : 1
=====
```

```
*A:ALA-12#
```

```
*A:ALA-12# show router 3 bgp damping suppressed detail
```

```
=====
BGP Router ID : 10.0.0.14          AS : 65206   Local AS : 65206
=====
Legend -
Status codes  : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes  : i - IGP, e - EGP, ? - incomplete, - best
=====
```

```
BGP Damped Routes (Suppressed)
=====
```

```
Network : 15.142.48.0/20
-----
```

```

Network          : 15.142.48.0/20    Peer           : 10.0.28.1
NextHop          : 10.0.28.1          Reuse time     : 00h29m22s
Peer AS          : 60203              Peer Router-Id : 32.32.27.203
Local Pref       : none
Age              : 00h01m28s          Last update    : 02d01h20m
FOM Present      : 2936              FOM Last upd.  : 3001
Number of Flaps  : 3                 Flags          : si
Path             : 60203 65001 19855 3356 702 1889
Applied Policy   : default-damping-profile

```

```
-----
Network : 15.200.128.0/19
-----
```

```

Network          : 15.200.128.0/19    Peer           : 10.0.28.1
NextHop          : 10.0.28.1          Reuse time     : 00h29m22s

```

## Show, Clear, Debug Commands

```
Peer AS          : 60203          Peer Router-Id   : 32.32.27.203
Local Pref       : none
Age              : 00h01m28s      Last update      : 02d01h20m
FOM Present      : 2936          FOM Last upd.   : 3001
Number of Flaps  : 3             Flags            : si
Path             : 60203 65001 19855 3356 702 1889
Applied Policy   : default-damping-profile
```

-----  
Network : 15.203.240.0/20  
-----

```
Network          : 15.203.240.0/20 Peer              : 10.0.28.1
NextHop          : 10.0.28.1     Reuse time       : 00h29m22s
Peer AS          : 60203        Peer Router-Id   : 32.32.27.203
Local Pref       : none
Age              : 00h01m28s      Last update      : 02d01h20m
FOM Present      : 2936          FOM Last upd.   : 3001
Number of Flaps  : 3             Flags            : si
Path             : 60203 65001 19855 3356 702 1889
Applied Policy   : default-damping-profile
```

-----  
Network : 15.206.0.0/17  
-----

```
Network          : 15.206.0.0/17 Peer              : 10.0.28.1
NextHop          : 10.0.28.1     Reuse time       : 00h29m22s
Peer AS          : 60203        Peer Router-Id   : 32.32.27.203
Local Pref       : none
Age              : 00h01m28s      Last update      : 02d01h20m
FOM Present      : 2936          FOM Last upd.   : 3001
Number of Flaps  : 3             Flags            : si
Path             : 60203 65001 19855 3356 702 1889
Applied Policy   : default-damping-profile
```

-----  
\*A:ALA-12#

## group

**Syntax** `group [name] [detail]`

**Context** `show>router>bgp`

**Description** This command displays group information for a BGP peer group. This command can be entered with or without parameters.

When this command is entered without a group name, information about all peer groups displays.

When the command is issued with a specific group name, information only pertaining to that specific peer group displays.

The 'State' field displays the BGP group's operational state. Other valid states are:

- Up - BGP global process is configured and running.
- Down - BGP global process is administratively shutdown and not running.
- Disabled - BGP global process is operationally disabled. The process must be restarted by the operator.

**Parameters** *name* — Displays information for the BGP group specified.

*detail* — Displays detailed information.

**Output** **Standard and Detailed Group Output** — The following table describes the standard and detailed command output fields for a BGP group:

**Sample Output**

Label	Description
Group	BGP group name
Group Type	No Type — Peer type not configured. External — Peer type configured as external BGP peers. Internal — Peer type configured as internal BGP peers.
State	Disabled — The BGP peer group has been operationally disabled. Down — The BGP peer group is operationally inactive. Up — The BGP peer group is operationally active.
Peer AS	The configured or inherited peer AS for the specified peer group.
Local AS	The configured or inherited local AS for the specified peer group.
Local Address	The configured or inherited local address for originating peering for the specified peer group.
Loop Detect	The configured or inherited loop detect setting for the specified peer group.
Connect Retry	The configured or inherited connect retry timer value.
	Authentication

Label	Description (Continued)
	None — No authentication is configured.
	MD5 — MD5 authentication is configured.
Local Pref	The configured or inherited local preference value.
MED Out	The configured or inherited MED value assigned to advertised routes without a MED attribute.
Min Route Advt.	The minimum amount of time that must pass between route updates for the same IP prefix.
Min AS Originate	The minimum amount of time that must pass between updates for a route originated by the local router.
Multihop	The maximum number of router hops a BGP connection can traverse.
Multipath	The configured or inherited multipath value, determining the maximum number of ECMP routes BGP can advertise to the RTM.
Prefix Limit	No Limit — No route limit assigned to the BGP peer group.  1 - 4294967295 — The maximum number of routes BGP can learn from a peer.
Passive	Disabled — BGP attempts to establish BGP connections with neighbors in the specified peer group.  Enabled — BGP will not actively attempt to establish BGP connections with neighbors in the specified peer group.
Next Hop Self	Disabled — BGP is not configured to send only its own IP address as the BGP nexthop in route updates to neighbors in the peer group.  Enabled — BGP sends only its own IP address as the BGP nexthop in route updates to neighbors in the specified peer group.
Aggregator ID 0	Disabled — BGP is not configured to set the aggregator ID to 0.0.0.0 in all originated route aggregates sent to the neighbor in the peer group.  Enabled — BGP is configured to set the aggregator ID to 0.0.0.0 in all originated route aggregates sent to the neighbor in the peer group.
Remove Private	Disabled — BGP will not remove all private AS numbers from the AS path attribute in updates sent to the neighbor in the peer group.  Enabled — BGP removes all private AS numbers from the AS path attribute in updates sent to the neighbor in the peer group.
Damping	Disabled — The peer group is configured not to dampen route flaps.  Enabled — The peer group is configured to dampen route flaps.
Export Policy	The configured export policies for the peer group.

Label	Description (Continued)
Import Policy	The configured import policies for the peer group.
Hold Time	The configured hold time setting.
Keep Alive	The configured keepalive setting.
Cluster Id	None — No cluster ID has been configured.
Client Reflect	Disabled — The BGP route reflector will not reflect routes to this neighbor. Enabled — The BGP route reflector is configured to reflect routes to this neighbor.
NLRI	The type of NLRI information that the specified peer group can accept. Unicast — IPv4 unicast routing information can be carried.
Preference	The configured route preference value for the peer group.
List of Peers	A list of BGP peers configured under the peer group.
Total Peers	The total number of peers configured under the peer group.
Established	The total number of peers that are in an established state.

```
*A:ALA-12# show router 3 bgp group
```

```
=====
```

```
BGP Groups
```

```
=====
```

```
Group           : To_AS_40000
```

```
-----
```

```
Description      : Not Available
```

```
Group Type       : No Type           State           : Up
```

```
Peer AS          : 40000             Local AS        : 65206
```

```
Local Address    : n/a              Loop Detect     : Ignore
```

```
Export Policy    : direct2bgp
```

```
Hold Time        : 90                Keep Alive     : 30
```

```
Cluster Id       : None              Client Reflect  : Enabled
```

```
NLRI             : Unicast           Preference     : 170
```

```
List of Peers
```

```
- 10.0.0.1       : To_Jukebox
```

```
- 10.0.0.12      : Not Available
```

```
- 10.0.0.13      : Not Available
```

```
- 10.0.0.14      : To_ALA-1
```

```
- 10.0.0.15      : To_H-215
```

```
Total Peers     : 5                Established    : 2
```

```
=====
```

```
*A:ALA-12#
```

## neighbor

**Syntax** `neighbor [ip-address [[family family] filter1]]`

**neighbor** [*as-number* [[**family** *family*] *filter2*]]

**Context** show>router>bgp

**Description** This command displays BGP neighbor information. This command can be entered with or without any parameters.

When this command is issued without any parameters, information about all BGP peers displays.

When the command is issued with a specific IP address or ASN, information regarding only that specific peer or peers with the same AS display.

When either **received-routes** or **advertised-routes** is specified, then the routes received from or sent to the specified peer is listed (see second output example).

Note: This information is not available by SNMP.

When either **history** or **suppressed** is specified, then the routes learned from those peers that either have a history or are suppressed (respectively) are listed.

The 'State' field displays the BGP peer's protocol state. In addition to the standard protocol states, this field can also display the 'Disabled' operational state which indicates the peer is operationally disabled and must be restarted by the operator.

**Parameters** *ip-addr* — Displays the BGP neighbor with the specified IP address.

**family** *family* — Specifies the type of routing information to be distributed by the BGP instance.

**Values** ipv4, vpn-ipv4

*filter1* — Specifies route criteria.

**Values** received-routes, advertised-routes, history, suppressed, detail

*filter2* — Specifies route criteria.

**Values** history, suppressed, detail

**Output** **Standard and Detailed Neighbor** — The following table describes the standard and detailed command output fields for a BGP neighbor:

Label	Description
Peer	The IP address of the configured BGP peer.
Group	The BGP peer group to which this peer is assigned.
Peer AS	The configured or inherited peer AS for the peer group.
Peer Address	The configured address for the BGP peer.
Peer Port	The TCP port number used on the far-end system.
Local AS	The configured or inherited local AS for the peer group.
Local Address	The configured or inherited local address for originating peering for the peer group.
Local Port	The TCP port number used on the local system.
Peer Type	External — Peer type configured as external BGP peers.

Label	Description (Continued)
State	Internal – Peer type configured as internal BGP peers.
	Idle – The BGP peer is not accepting connections.
	Active – BGP is listening for and accepting TCP connections from this peer.
	Connect – BGP is attempting to establish a TCP connection from this peer.
	Open Sent – BGP has sent an OPEN message to the peer and is waiting for an OPEN message from the peer.
	Open Confirm – BGP has received a valid OPEN message from the peer and is awaiting a KEEPALIVE or NOTIFICATION.
	Established – BGP has successfully established a peering and is exchanging routing information.
Last State	Idle – The BGP peer is not accepting connections.
	Active – BGP is listening for and accepting TCP connections from this peer.
	Connect – BGP is attempting to establish a TCP connection with this peer.
	Connect – BGP is attempting to establish a TCP connections from this peer.
	Open Sent – BGP has sent an OPEN message to the peer and is waiting for an OPEN message from the peer.
	Open Confirm – BGP has received a valid OPEN message from the peer and is awaiting a KEEPALIVE or NOTIFICATION.
	Open Confirm – BGP has received a valid OPEN message from the peer and is awaiting a KEEPALIVE or NOTIFICATION.
Last Event	start – BGP has initialized the BGP neighbor.
	stop – BGP has disabled the BGP neighbor.
	open – BGP transport connection opened.
	close – BGP transport connection closed.
	openFail – BGP transport connection failed to open.
	error – BGP transport connection error.
	connectRetry – Connect retry timer expired.
	holdTime – Hold time timer expired.
	keepAlive – Keepalive timer expired.

Label	Description (Continued)
	recvOpen – Receive an OPEN message.
	revKeepalive – Receive an KEEPALIVE message.
	recvUpdate – Receive an UPDATE message.
	recvNotify – Receive an NOTIFICATION message.
	None – No events have occurred.
Last Error	Displays the last BGP error and sub-code to occur on the BGP neighbor.
Connect Retry	The configured or inherited connect retry timer value.
Local Pref.	The configured or inherited local preference value.
Min Route Advt.	The minimum amount of time that must pass between route updates for the same IP prefix.
Min AS Originate	The minimum amount of time that must pass between updates for a route originated by the local router.
Multihop	The maximum number of router hops a BGP connection can traverse.
Multipath	The configured or inherited multipath value, determining the maximum number of ECMP routes BGP can advertise to the RTM.
Damping	Disabled – BGP neighbor is configured not to dampen route flaps. Enabled – BGP neighbor is configured to dampen route flaps.
Loop Detect	Ignore – The BGP neighbor is configured to ignore routes with an AS loop. Drop – The BGP neighbor is configured to drop the BGP peering if an AS loop is detected. Off – AS loop detection is disabled for the neighbor.
MED Out	The configured or inherited MED value assigned to advertised routes without a MED attribute.
Authentication	None – No authentication is configured. MD5 – MD5 authentication is configured.
Next Hop Self	Disabled – BGP is not configured to send only its own IP address as the BGP nexthop in route updates to the specified neighbor. Enabled – BGP will send only its own IP address as the BGP nexthop in route updates to the neighbor.
AggregatorID Zero	Disabled – The BGP Neighbor is not configured to set the aggregator ID to 0.0.0.0 in all originated route aggregates.



Label	Description (Continued)
	Enabled — The BGP Neighbor is configured to set the aggregator ID to 0.0.0.0 in all originated route aggregates.
Remove Private	Disabled — BGP will not remove all private AS numbers from the AS path attribute, in updates sent to the specified neighbor.  Enabled — BGP will remove all private AS numbers from the AS path attribute, in updates sent to the specified neighbor.
Passive	Disabled — BGP will actively attempt to establish a BGP connection with the specified neighbor.  Enabled — BGP will not actively attempt to establish a BGP connection with the specified neighbor.
Prefix Limit	No Limit — No route limit assigned to the BGP peer group.  1 - 4294967295 — The maximum number of routes BGP can learn from a peer.
Hold Time	The configured hold time setting.
Keep Alive	The configured keepalive setting.
Active Hold Time	The negotiated hold time, if the BGP neighbor is in an established state.
Active Keep Alive	The negotiated keepalive time, if the BGP neighbor is in an established state.
Cluster Id	The configured route reflector cluster ID. None — No cluster ID has been configured
Client Reflect	Disabled — The BGP route reflector is configured not to reflect routes to this neighbor.  Enabled — The BGP route reflector is configured to reflect routes to this neighbor.
Preference	The configured route preference value for the peer group.
Num of Flaps	The number of flaps in the neighbor connection.
Recd. Prefixes	The number of routes received from the BGP neighbor.
Active Prefixes	The number of routes received from the BGP neighbor and active in the forwarding table.
Recd. Paths	The number of unique sets of path attributes received from the BGP neighbor.
Suppressed Paths	The number of unique sets of path attributes received from the BGP neighbor and suppressed due to route damping.
Input Queue	The number of BGP messages to be processed.
Output Queue	The number of BGP messages to be transmitted.

Label	Description (Continued)
i/p Messages	Total number of packets received from the BGP neighbor.
o/p Messages	Total number of packets sent to the BGP neighbor.
i/p Octets	Total number of octets received from the BGP neighbor.
o/p Octets	Total number of octets sent to the BGP neighbor.
i/p Updates	Total number of BGP updates received from the BGP neighbor.
o/p Updates	Total number of BGP updates sent to the BGP neighbor.
Export Policy	The configured export policies for the peer group.
Import Policy	The configured import policies for the peer group.

**Sample Output**

```
*A:ALA-12# show router 3 bgp neighbor
=====
BGP Neighbor
=====
-----
Peer : 10.0.0.15          Group : To_AS_40000
-----
Peer AS      : 65205
Peer Address : 10.0.0.15      Peer Port    : 0
Local AS     : 65206
Local Address : 10.0.0.16     Local Port    : 0
Peer Type    : External
State        : Active        Last State    : Connect
Last Event   : openFail
Last Error   : Hold Timer Expire
Hold Time    : 90            Keep Alive    : 30
Active Hold Time : 0        Active Keep Alive: 0
Cluster Id   : None
Preference   : 170          Num of Flaps   : 0
Recd. Prefixes : 0        Active Prefixes : 0
Recd. Paths   : 0        Suppressed Paths : 0
Input Queue   : 0        Output Queue   : 0
i/p Messages  : 0        o/p Messages  : 0
i/p Octets    : 0        o/p Octets    : 0
i/p Updates   : 0        o/p Updates   : 0
Export Policy : direct2bgp
=====
*A:ALA-12#
```

```
*A:ALA-12# show router 3 bgp neighbor detail
=====
BGP Neighbor (detail)
=====
-----
Peer : 10.0.0.15          Group : To_AS_40000
-----
Peer AS      : 65205
Peer Address : 10.0.0.15      Peer Port    : 0
Local AS     : 65206
Local Address : 10.0.0.16     Local Port    : 0
```

```

Peer Type      : External
State         : Active
Last Event    : openFail
Last Error    : Hold Timer Expire
Connect Retry : 20
Min Route Advt. : 30
Multipath     : 1
Damping       : Disabled
MED Out       : No MED Out
Next Hop Self : Disabled
Remove Private : Disabled
Prefix Limit  : No Limit
Hold Time     : 90
Active Hold Time : 0
Cluster Id    : None
Preference    : 170
Recd. Prefixes : 0
Recd. Paths   : 0
Input Queue   : 0
i/p Messages : 0
i/p Octets    : 0
i/p Updates   : 0
Export Policy : direct2bgp

Last State    : Connect
Local Pref.   : 100
Min AS Orig.  : 15
Multihop      : 5
Loop Detect    : Ignore
Authentication : None
AggregatorID Zero: Disabled
Passive       : Disabled

Keep Alive    : 30
Active Keep Alive: 0
Client Reflect : Enabled
Num of Flaps  : 0
Active Prefixes : 0
Suppressed Paths : 0
Output Queue  : 0
o/p Messages  : 0
o/p Octets    : 0
o/p Updates   : 0

```

```

=====
*A:ALA-12#

```

**Output** **Show Advertised and Received Routes Output** — The following table describes the command output fields for both the standard and detailed information for a neighbor:

Label	Description
BGP Router ID	The local BGP router ID.
AS	The configured autonomous system number.
Local AS	The configured local AS setting. If not configured, then it is the same value as the AS.
Flag	u — used s — suppressed h — history d — decayed * — valid i — igp ? — incomplete > — best
Network	Route IP prefix and mask length for the route.
Next Hop	BGP nexthop for the route.

## Show, Clear, Debug Commands

Label	Description (Continued)
LocalPref	BGP local preference path attribute for the route.
MED	BGP Multi-Exit Discriminator (MED) path attribute for the route.
AS Path	The BGP AS path for the route.

### Sample Output

```
*A:ALA-12# show router 3 bgp neighbor 10.0.0.16 received-routes
=====
BGP Router ID : 10.0.0.16      AS : 65206   Local AS : 65206
=====
Legend -
Status codes : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes : i - IGP, e - EGP, ? - incomplete, > - best
=====
BGP Neighbor
=====
Flag  Network          Nexthop          LocalPref  MED      As-Path
-----
?    10.0.0.16/32       10.0.0.16       100        none     No As-Path
?    10.0.6.0/24        10.0.0.16       100        none     No As-Path
?    10.0.8.0/24        10.0.0.16       100        none     No As-Path
?    10.0.12.0/24       10.0.0.16       100        none     No As-Path
?    10.0.13.0/24       10.0.0.16       100        none     No As-Path
?    10.0.204.0/24      10.0.0.16       100        none     No As-Path
=====
*A:ALA-12#
```

## paths

**Syntax** paths**Context** show>router>bgp**Description** This command displays a summary of BGP path attributes.**Output** **Show Path Output** — The following table describes the command output fields for a BGP path.

Label	Description
BGP Router ID	The local BGP router ID.
AS	The configured autonomous system number.
Local AS	The configured local AS setting. If not configured, then the value is the same as the AS.
Path	The AS path attribute.
Origin	EGP — The NLRI is learned by an EGP protocol. IGP — The NLRI is interior to the originating AS. INCOMPLETE — NLRI was learned another way.
Next Hop	The advertised BGP nexthop.
MED	The Multi-Exit Discriminator value.
Local Preference	The local preference value.
Refs	The number of routes using a specified set of path attributes.
ASes	The number of autonomous system numbers in the AS path attribute.
Segments	The number of segments in the AS path attribute.
Flags	EBGP-learned — Path attributes learned by an EBGP peering. IBGP-Learned — Path attributes learned by an IBGP peering.
Aggregator	The route aggregator ID.
Community	The BGP community attribute list.
Originator ID	The originator ID path attribute value.
Cluster List	The route reflector cluster list.

**Sample Output**

```
*A:ALA-12# show router 3 bgp paths
=====
BGP Router ID : 10.0.0.14      AS : 65206   Local AS : 65206
=====
BGP Paths
```

## Show, Clear, Debug Commands

```
-----  
Path: 60203 65001 19855 3356 15412  
-----  
Origin          : IGP                Next Hop        : 10.0.28.1  
MED             : 60203              Local Preference : none  
Refs            : 4                  ASes           : 5  
Segments       : 1  
Flags           : EBGP-learned  
Aggregator     : 15412 62.216.140.1  
-----  
Path: 60203 65001 19855 3356 1 1236 1236 1236 1236  
-----  
Origin          : IGP                Next Hop        : 10.0.28.1  
MED             : 60203              Local Preference : none  
Refs            : 2                  ASes           : 9  
Segments       : 1  
Flags           : EBGP-learned  
-----  
*A:ALA-12#
```

## routes

**Syntax** `routes [family family] [prefix [detail | longer]]`  
`routes [family family] [prefix [hunt | brief]]`  
`routes [family family] [community comm-id]`  
`routes [family family] [aspath-regex reg-exp]`  
`routes [family family] [ipv6-prefix[/prefix-length] [detail | longer] | [hunt [brief]]]`

**Context** `show>router>bgp`

**Description** This command displays BGP route information.

When this command is issued without any parameters, then the entire BGP routing table displays.

When this command is issued with an IP prefix/mask or IP address, then the best match for the parameter displays.

**Parameters** `family family` — Specifies the type of routing information to be distributed by the BGP instance.

**Values** `ipv4` — Displays only those BGP peers that have the IPv4 family enable and not those capable of exchanging IP-VPN routes.  
`vpn-ipv4` — Displays the BGP peers that are IP-VPN capable.  
`ipv6` — Displays the BGP peers that are IPv6 capable.  
`mcast-ipv4` — Displays the BGP peers that are mcast-ipv4 capable.

`prefix` — Specifies the type of routing information to display.

**Values** `rd[[rd:]ip-address[/mask]`

	<code>rd</code>	{ip-address:number1 as-number1:number2 as-number2:number3}
<code>number1</code>	1	— 65535
<code>as-number1</code>	1	— 65535
<code>number2</code>	0	— 4294967295
<code>as-number2</code>	1	— 4294967295
<code>number3</code>	0	— 65535
<code>ip-address</code>		a.b.c.d
<code>mask</code>	0	— 32

`ipv6-prefix[/prefix-length]` — Specifies the type of IPv6 routing information to display.

**Values** `ipv6-prefix:` `x:x:x:x:x:x:x` (eight 16-bit pieces)  
`x:x:x:x:x:d.d.d`  
`x:` [0 — FFFF]H  
`d:` [0 — 255]D  
`prefix-length` 0 — 128

`filter` — Specifies route criteria.

**Values** `hunt` Displays entries for the specified route in the RIB-In, RIB-Out, and RTM.  
`longer` Displays the specified route and subsets of the route.  
`detail` Display the longer, more detailed version of the output.

`aspath-regex "reg-exp"` — Displays all routes with an AS path matching the specified regular expression `reg-exp`.

`community comm.-id` — Displays all routes with the specified BGP community.

## Show, Clear, Debug Commands

<b>Values</b>	<i>[as-number1:comm-val1   ext-comm   well-known-comm]</i>
ext-comm	type: {ip-address:comm-val1   as-number1:comm-val2   as-number2:comm-val1 }
as-number1	0..65535
comm-val1	0..65535
type	keywords: target, origin
ip-address	a.b.c.d
comm-val2	0 — 4294967295
as-number2	0 — 4294967295
	well-known-comm no-export, no-export-subconfed, no-advertise

**Output** **Show BGP Routes** — The following table describes the command output fields for BGP routes.

Label	Description
BGP Router ID	The local BGP router ID.
AS	The configured autonomous system number.
Local AS	The configured local AS setting, if not configured it is the same as the system AS.
Network	The IP prefix and mask length.
Nexthop	The BGP nexthop.
From	The advertising BGP neighbor's IP address.
Res. Nexthop	The resolved nexthop.
Local Pref.	The local preference value.
Flag	u — used s — suppressed h — history d — decayed * — valid i — igp e — egp ? — incomplete > — best
Aggregator AS	The aggregator AS value. none — No aggregator AS attributes are present.
Aggregator	The aggregator attribute value. none — no Aggregator attributes are present.
Atomic Aggr.	Atomic — The atomic aggregator flag is set.



Label	Description
	Not Atomic – The atomic aggregator flag is not set.
MED	The MED metric value. none – No MED metric is present.
Community	The BGP community attribute list.
Cluster	The route reflector cluster list.
Originator Id	The originator ID path attribute value. none – The originator ID attribute is not present.
Peer Router Id	The router ID of the advertising router.
AS-Path	The BGP AS path attribute.
VPRN Imported	Displays the VPRNs where a particular BGP-VPN received route has been imported and installed.

**Sample Output**

```
*A:ALA-12>config>router>bgp# show router 3 bgp routes family ipv4
=====
BGP Router ID : 10.10.10.103      AS : 200      Local AS : 200
=====
Legend -
Status codes : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes : i - IGP, e - EGP, ? - incomplete, > - best
=====
BGP Routes
=====
Flag  Network                Nexthop      LocalPref  MED
     VPN Label                As-Path
-----
No Matching Entries Found
=====
*A:ALA-12>config>router>bgp#

A:SR-12# show router bgp routes 100.0.0.0/31 hunt
=====
BGP Router ID : 10.20.1.1   AS : 100Local AS : 100
=====
Legend -
Status codes : u - used, s - suppressed, h - history, d - decayed, * - valid
Origin codes : i - IGP, e - EGP, ? - incomplete, > - best
=====
BGP Routes
=====
RIB In Entries
-----
Network      : 100.0.0.0/31
Nexthop      : 10.20.1.2
Route Dist.  : 10.20.1.2:1      VPN Label    : 131070
From         : 10.20.1.2
Res. Nexthop : 10.10.1.2
Local Pref.  : 100
Aggregator AS : none
Interface Name: to-sr7
Aggregator   : none
```

## Show, Clear, Debug Commands

```
Atomic Aggr.   : Not Atomic           MED           : none
Community     : target:10.20.1.2:1
Cluster       : No Cluster Members
Originator Id : None                 Peer Router Id: 10.20.1.2
Flags         : Used Valid Best IGP
AS-Path       : No As-Path
VPRN Imported : 1 2 10 12
-----
RIB Out Entries
-----
Routes : 1
=====
A:SR-12#
```

### summary

**Syntax** `summary [all]`

**Context** `show>router>bgp`

**Description** This command displays a summary of BGP neighbor information.

If confederations are not configured, that portion of the output will not display.

The “State” field displays the global BGP operational state. The valid values are:

Up — BGP global process is configured and running.

Down — BGP global process is administratively shutdown and not running.

Disabled — BGP global process is operationally disabled. The process must be restarted by the operator.

For example, if a BGP peer is operationally disabled, then the state in the summary table shows the state ‘Disabled’

**Parameters** `all` — Displays BGP peers in all instances.

**Output** **Show BGP Summary Output** — The following table describes the command output fields for a BGP summary:

Label	Description
BGP Router ID	The local BGP router ID.
AS	The configured autonomous system number.
Local AS	The configured local AS setting, if not configured it is the same as the system AS.
BGP Admin State	Down — BGP is administratively disabled. Up — BGP is administratively enabled.
BGP Oper State	Down — BGP is operationally disabled. Up — BGP is operationally enabled.
Confederation AS	The configured confederation AS.

Label	Description
Member Confederations	The configured members of the BGP confederation.
Number of Peer Groups	The total number of configured BGP peer groups.
Number of Peers	The total number of configured BGP peers.
Total BGP Active Routes	The total number of BGP routes used in the forwarding table.
Total BGP Routes	The total number of BGP routes learned from BGP peers.
Total BGP Paths	The total number of unique sets of BGP path attributes learned from BGP peers.
Total Path Memory	Total amount of memory used to store the path attributes.
Total Suppressed Routes	Total number of suppressed routes due to route damping.
Total History Routes	Total number of routes with history due to route damping.
Total Decayed Routes	Total number of decayed routes due to route damping.
Neighbor	BGP neighbor address.
AS (Neighbor)	BGP neighbor autonomous system number.
PktRcvd	Total number of packets received from the BGP neighbor.
PktSent	Total number of packets sent to the BGP neighbor.
InQ	The number of BGP messages to be processed.
OutQ	The number of BGP messages to be transmitted.
Up/Down	The amount of time that the BGP neighbor has either been established or not established depending on its current state.
State Recv/Actv/Sent	The BGP neighbor's current state (if not established) or the number of received routes, active routes and sent routes (if established).

### Sample Output

```
*A:ALA-12# show router 3 bgp summary
=====
BGP Router ID : 10.0.0.14      AS : 65206   Local AS : 65206
=====
BGP Admin State      : Up           BGP Oper State      : Up
Confederation AS     : 40000
Member Confederations : 65205 65206 65207 65208

Number of Peer Groups : 2           Number of Peers     : 7
Total BGP Active Routes : 86689       Total BGP Routes    : 116999
Total BGP Paths       : 35860       Total Path Memory   : 2749476
```

## Show, Clear, Debug Commands

```

Total Suppressed Routes : 0          Total History Routes : 0
Total Decayed Routes   : 0
=====
BGP Summary
=====
Neighbor          AS PktRcvd PktSent InQ OutQ   Up/Down State|Recv/Actv/Sent
-----
10.0.0.1          65206     5  21849  0   0 00h01m29s 32/0/86683
10.0.0.12         65206     0    0     0   0 00h01m29s Active
10.0.0.13         65206     5  10545  0   50 00h01m29s 6/0/86683
10.0.0.15         65205     0    0     0   0 00h01m29s Active
10.0.0.16         65206     5   9636  0   50 00h01m29s 6/0/86683
10.0.27.1         2         0    0     0   0 00h01m29s Active
10.0.28.1         60203    22512   15    0   0 00h01m29s 116955/86689/9
=====
*A:ALA-12#

```

## ecmp

**Syntax** `ecmp`

**Context** `show>router`

**Description** This command displays the ECMP settings for the router.

**Output** **Show ECMP Settings Output** — The following table describes the output fields for the router ECMP settings.

Label	Description
Instance	The router instance number.
Router Name	The name of the router instance.
ECMP	False — ECMP is disabled for the instance. True — ECMP is enabled for the instance.
Configured-ECMP-Routes	The number of ECMP routes configured for path sharing.

### Sample Output

```

*A:ALA-12# show router 3 ecmp
=====
Router ECMP
=====
Instance      Router Name          ECMP      Configured-ECMP-Routes
-----
1             Base                 True      8
=====
*A:ALA-12#

```

## interface

**Syntax** `interface` `[[ip-address | ip-int-name] [detail]] | [summary] | [exclude-services]`

**Context** `show>router`

**Description** This command displays the router IP interface table sorted by interface index.

**Parameters**

- ip-address* — Only displays the interface information associated with the specified IP address.
- ip-int-name* — Only displays the interface information associated with the specified IP interface name.
- detail** — Displays detailed IP interface information.
- summary** — Displays summary IP interface information for the router.
- exclude-services** — Displays IP interface information, excluding IP interfaces configured for customer services. Only core network IP interfaces are displayed.

**Output** **Standard IP Interface Output** — The following table describes the standard output fields for an IP interface:

Label	Description
Interface-Name	The IP interface name.
Type	n/a — No IP address has been assigned to the IP interface, so the IP address type is not applicable.  Pri — The IP address for the IP interface is the Primary address on the IP interface.  Sec — The IP address for the IP interface is a secondary address on the IP interface.
IP-Address	The IP address and subnet mask length of the IP interface. n/a — Indicates no IP address has been assigned to the IP interface.
Adm	Down — The IP interface is administratively disabled.  Up — The IP interface is administratively enabled.
Opr	Down — The IP interface is operationally disabled.  Up — The IP interface is operationally enabled.
Mode	Network — The IP interface is a network/core IP interface.  Service — The IP interface is a service IP interface.

**Sample Output**

```
*A:ALA-12# show router 3 interface
=====
Interface Table
=====
Interface-Name          Type IP-Address          Adm   Opr   Mode
-----
```

## Show, Clear, Debug Commands

```

system                Pri 10.10.0.3/32      Up    Up    Network
to-ser1              Pri 10.10.13.3/24     Up    Up    Network
to-ser4              Pri 10.10.34.3/24    Up    Up    Network
to-ser5              Pri 10.10.35.3/24    Up    Up    Network
to-ser6              n/a n/a              Up    Down Network
to-web                Pri 10.1.1.3/24      Up    Down Service
management            Pri 192.168.2.93/20  Up    Up    Network
=====

```

\*A:ALA-12#

\*A:ALA-12# **show router 3 interface 10.10.0.3/32**

Interface Table

```

=====
Interface-Name          Type IP-Address      Adm   Opr   Mode
-----
system                  Pri 10.10.0.3/32  Up    Up    Network
=====

```

SR4#

\*A:ALA-12# **show router 3 interface to-ser1**

Interface Table

```

=====
Interface-Name          Type IP-Address      Adm   Opr   Mode
-----
to-ser1                 Pri 10.10.13.3/24  Up    Up    Network
=====

```

\*A:ALA-12#

\*A:ALA-12# **show router 3 interface exclude-services**

Interface Table

```

=====
Interface-Name          Type IP-Address      Adm   Opr   Mode
-----
system                  Pri 10.10.0.3/32  Up    Up    Network
to-ser1                 Pri 10.10.13.3/24  Up    Up    Network
to-ser4                 Pri 10.10.34.3/24  Up    Up    Network
to-ser5                 Pri 10.10.35.3/24  Up    Up    Network
to-ser6                 n/a n/a            Up    Down Network
management              Pri 192.168.2.93/20  Up    Up    Network
=====

```

\*A:ALA-12#

**Detailed IP Interface Output** — The following table describes the detailed output fields for an IP interface.

Label	Description
If Name	The IP interface name.
Admin State	Down — The IP interface is administratively disabled. Up — The IP interface is administratively enabled.

Label	Description (Continued)
Oper State	Down — The IP interface is operationally disabled. Up — The IP interface is operationally disabled.
IP Addr/mask	The IP address and subnet mask length of the IP interface. Not Assigned — Indicates no IP address has been assigned to the IP interface.
Address Type	Primary — The IP address for the IP interface is the Primary address on the IP interface. Secondary — The IP address for the IP interface is a Secondary address on the IP interface.
IGP Inhibit	Disabled — The secondary IP address on the interface will be recognized as a local interface by the IGP. Enabled — The secondary IP address on the interface will not be recognized as a local interface by the IGP.
Broadcast Address	All-ones — The broadcast format on the IP interface is all ones. Host-ones — The broadcast format on the IP interface is host ones.
If Index	The interface index of the IP router interface.
If Type	Network — The IP interface is a network/core IP interface. Service — The IP interface is a service IP interface.
Port Id	The port ID of the IP interface.
Egress Filter	The egress IP filter policy ID associated with the IP interface. none — Indicates no egress filter policy is associated with the interface.
Ingress Filter	The ingress IP filter policy ID associated with the IP interface. none — Indicates no ingress filter policy is associated with the interface.
QoS Policy	The QoS policy ID associated with the IP interface.
SNTP Broadcast	False — Receipt of SNTP broadcasts on the IP interface is disabled. True — Receipt of SNTP broadcasts on the IP interface is enabled.
MAC Address	The MAC address of the IP interface.
Arp Timeout	The ARP timeout for the interface, in seconds, which is the time an ARP entry is maintained in the ARP cache without being refreshed.
IP MTU	The IP Maximum Transmission Unit (MTU) for the IP interface.
ICMP Mask Reply	False — The IP interface will not reply to a received ICMP mask request. True — The IP interface will reply to a received ICMP mask request.

Label	Description (Continued)
Cflowd	Specifies the type of Cflowd analysis that is applied to the interface. acl — ACL Cflowd analysis is applied to the interface. interface — Interface cflowd analysis is applied to the interface. none — No Cflowd analysis is applied to the interface.
Redirects	Specifies the maximum number of ICMP redirect messages the IP interface will issue in a given period of time (Time (seconds)). Disabled — Indicates the IP interface will not generate ICMP redirect messages.
Unreachables	Specifies the maximum number of ICMP destination unreachable messages the IP interface will issue in a given period of time. Disabled — Indicates the IP interface will not generate ICMP destination unreachable messages.
TTL Expired	The maximum number (Number) of ICMP TTL expired messages the IP interface will issue in a given period of time (Time (seconds)). Disabled — Indicates the IP interface will not generate ICMP TTL expired messages.

```
*A:ALA-12# show router 3 interface detail
=====
Interface Table
=====
Interface
-----
If Name      : to-ser1
Admin State  : Up
Oper State   : Up

IP Addr/mask : 10.10.13.3/24      Address Type   : Primary
IGP Inhibit  : Disabled          Broadcast Address: Host-ones

IP Addr/mask : 10.200.0.1/16     Address Type   : Secondary
IGP Inhibit  : Enabled          Broadcast Address: Host-ones
-----
Details
-----
If Index     : 2
Port Id      : 1/1/2
Egress Filter: none
QoS Policy   : 1
MAC Address  : 04:5d:01:01:00:02
IP MTU       : 1500
Cflowd       : none

If Type      : Network
Ingress Filter : 100
SNTP Broadcast : False
Arp Timeout  : 14400
ICMP Mask Reply : True

ICMP Details
Redirects     : Disabled
Unreachables : Number - 100      Time (seconds) - 10
TTL Expired  : Number - 100     Time (seconds) - 10
=====
*A:ALA-12#
```

**Summary IP Interface Output** — The following table describes the summary output fields for the router IP interfaces.



Label	Description
Instance	The router instance number.
Router Name	The name of the router instance.
Interfaces	The number of IP interfaces in the router instance.
Admin-Up	The number of administratively enabled IP interfaces in the router instance.
Oper-Up	The number of operationally enabled IP interfaces in the router instance.

### Sample Output

```
*A:ALA-12# show router 3 interface summary
=====
Router Summary (Interfaces)
=====
Instance  Router Name                Interfaces  Admin-Up  Oper-Up
-----
1         Base                          7          7         5
=====
*A:ALA-12#
```

## mvpn

**Syntax** mvpn

**Context** show>router *router-instance*

**Description** This command displays Multicast VPN related information. The router instance must be specified.

### Sample Output

```
*A:Dut-C# show router 1 mvpn
=====
MVPN 1 configuration data
=====
signaling          : Bgp                auto-discovery    : Enabled
UMH Selection      : Highest-IP        intersite-shared   : Enabled
vrf-import         : N/A
vrf-export         : N/A
vrf-target         : target:1:1
C-Mcast Import RT : target:10.20.1.3:2

ipmsi              : pim-asm 224.1.1.1
admin status       : Up                three-way-hello    : N/A
hello-interval     : N/A               hello-multiplier   : 35 * 0.1
tracking support   : Disabled          Improved Assert    : N/A

spmsi              : pim-ssm 225.0.0.0/32
join-tlv-packing   : N/A
data-delay-interval : 3 seconds
data-threshold     : 224.0.0.0/4 --> 1 kbps
```

database

**Syntax** `database [ip-prefix [/mask] [longer] [peer ip-address]`

**Context** `show>router>rip`

**Description** Displays all routes in the RIP database.

**Output** **Show RIP Database Output** — The following table describes the output fields for the RIP route database.

Label	Description
Destination	The RIP destination for the route.
Peer	The router ID of the peer router.
NextHop	The IP address of the next hop.
Metric	The hop count to rate the value of different hops.
Tag	The value to distinguish between internal routes (learned by RIP) and external routes (learned from other protocols).
TTL	Displays how many seconds the specific route will remain in the routing table. When an entry reaches 0, it is removed from the routing table.
Valid	No — The route is not valid. Yes — The route is valid.

**Sample Output**

```
*A:ALA-1# show rip database
=====
RIP Route Database
=====
Destination      Peer           NextHop        Metric  Tag      TTL  Valid
-----
180.0.0.10/32    180.1.7.15    0.0.0.0        2       0x0000  163  No
180.0.0.10/32    180.1.8.14    0.0.0.0        2       0x0000  179  No
180.0.0.14/32    180.1.8.14    0.0.0.0        1       0x0000  179  Yes
180.0.6.0/24     180.1.7.15    0.0.0.0        11      0x2002  163  No
180.0.6.0/24     180.1.8.14    0.0.0.0        11      0x2002  179  No
180.0.7.0/24     180.1.7.15    0.0.0.0        11      0x2002  163  No
180.0.7.0/24     180.1.8.14    0.0.0.0        11      0x2002  179  No
180.1.5.0/24     180.1.7.15    0.0.0.0        2       0x0000  151  Yes
180.1.5.0/24     180.1.8.14    0.0.0.0        1       0x0000  167  No
180.100.17.16/31 180.1.7.15    0.0.0.0        2       0x0000  151  No
180.100.17.16/31 180.1.8.14    0.0.0.0        2       0x0000  167  No
-----
No. of Routes: 11
=====
*A:ALA-12#
```

## neighbor

**Syntax** `neighbor [ip-address | ip-int-name] [detail] [advertised-routes]`

**Context** `show>router>rip`

**Description** Displays RIP neighbor interface information.

**Parameters** `ip-address | ip-int-name` — Displays information for the specified IP interface.

**Default** All neighbor interfaces.

**advertised-routes** — Displays the routes advertised to RIP neighbors. If no neighbors are specified, then all routes advertised to all neighbors are displayed. If a specific neighbor is given then only routes advertised to the given neighbor/interface are displayed.

**Default** Display RIP information.

**Output** **Standard Show RIP Neighbor Output** — The following table describes the standard command output fields for a RIP group.

Label	Description
Neighbor	The RIP neighbor interface name.
Adm	Down — The RIP neighbor interface is administratively down. Up — The RIP neighbor interface is administratively up.
Opr	Down — The RIP neighbor interface is operationally down. Up — The RIP neighbor interface is operationally up.
Primary IP	The primary IP address of the RIP neighbor interface.
Send Mode	Bcast — Specifies that RIPv2 formatted messages are sent to the broadcast address. Mcast — Specifies that RIPv2 formatted messages are sent to the multicast address. None — Specifies that no RIP messages are sent (i.e., silent listener). RIPv1 — Specifies that RIPv1 formatted messages are sent to the broadcast address.
Recv Mode	Both — Specifies that RIP updates in either version 1 or version 2 format will be accepted. None — Specifies that RIP updates will not be accepted. RIPv1 — Specifies that RIP updates in version 1 format only will be accepted. RIPv2 — Specifies that RIP updates in version 2 format only will be accepted.
Metric In	The metric added to routes received from a RIP neighbor.

**Sample Output**

```
*A:ALA-12# show router 3 rip neighbor
=====
RIP Neighbors
=====
Interface                               Adm  Opr  Primary IP      Send  Recv  Metric
                                     Mode Mode              In
-----
router-21/1                             Up   Up   10.0.3.12       None  Both  1
router-21/2                             Up   Up   10.0.5.12       BCast Both  1
router-21/3                             Up   Up   10.0.6.12       BCast Both  1
router-21/4                             Up   Up   10.0.10.12      BCast Both  1
router-21/5                             Up   Up   10.0.9.12       BCast Both  1
router-21/6                             Up   Up   10.0.17.12      None  Both  1
router-21/7                             Up   Up   10.0.16.12      None  Both  1
=====
*A:ALA-12#
```

**Detailed Show RIP Neighbor Output** — The following table describes the standard command output fields for a RIP group.

Label	Description
Neighbor	The RIP neighbor name.
Description	The RIP neighbor description. No Description Available indicates no description is configured.
Primary IP	The RIP neighbor interface primary IP address.
Group	The RIP group name of the neighbor interface.
Admin State	Down — The RIP neighbor interface is administratively down. Up — The RIP neighbor interface is administratively up.
Oper State	Down — The RIP neighbor interface is operationally down. Up — The RIP neighbor interface is operationally up.
Send Mode	Bcast — Specifies that RIPv2 formatted messages are sent to the broadcast address. Mcast — Specifies that RIPv2 formatted messages are sent to the multicast address. None — Specifies that no RIP messages are sent (i.e., silent listener). RIPv1 — Specifies that RIPv1 formatted messages are sent to the broadcast address.
Recv Mode	Both — Specifies that RIP updates in either version 1 or version 2 format will be accepted. None — Specifies that RIP updates will not be accepted.

Label	Description (Continued)
	RIPv1 — Specifies that RIP updates in version 1 format only will be accepted.
	RIPv2 — Specifies that RIP updates in version 2 format only will be accepted.
Metric In	The metric value added to routes received from a RIP neighbor.
Metric Out	The value added to routes exported into RIP and advertised to RIP neighbors.
Split Horizon	Disabled — Split horizon disabled for the neighbor. Enabled — Split horizon and poison reverse enabled for the neighbor.
Check Zero	Disabled — Checking of the mandatory zero fields in the RIPv1 and RIPv2 specifications are not checked allowing receipt of RIP messages even if mandatory zero fields are non-zero for the neighbor. Enabled — checking of the mandatory zero fields in the RIPv1 and RIPv2 specifications and rejecting non-compliant RIP messages is enabled for the neighbor.
Message Size	The maximum number of routes per RIP update message.
Preference	The preference of RIP routes from the neighbor.
Auth. Type	Specifies the authentication type.
Update Timer	The current setting of the RIP update timer value expressed in seconds.
Timeout Timer	The current RIP timeout timer value expressed in seconds.
Export Policies	The export route policy that is used to determine routes advertised to all peers.
Import Policies	The import route policy that is used to determine which routes are accepted from RIP neighbors.

### Sample Output

```
*A:ALA-12# show router 3 rip peers
=====
RIP Peers
=====
Peer IP Addr      Interface Name      Version      Last Update
-----
10.0.5.13         router-2/2          RIPv2        0
10.0.6.16         router-2/3          RIPv2        2
10.0.9.14         router-2/5          RIPv2        8
10.0.10.15        router-2/4          RIPv2        0
-----
No. of Peers: 4
=====
*A:ALA-12#
```

## Show, Clear, Debug Commands

```
*A:ALA-12# show router 3 rip neighbor detail
=====
RIP Neighbors (Detail)
=====
Neighbor "router-2/7"
-----
Description      : No Description Available
Primary IP       : 10.0.16.12           Group           : seven
Admin State      : Up                  Oper State       : Up
Send Mode        : None                Receive Mode     : Both
Metric In        : 1                   Metric Out       : 1
Split Horizon    : Enabled              Check Zero       : Disabled
Message Size     : 25                   Preference      : 100
Auth. Type       : None                 Update Timer     : 3
Timeout Timer    : 6                     Flush Timer      : 6
Export Policies:
  Rip2Rip
  direct2Rip
  bgp2Rip
Import Policies:
  None
=====
*A:ALA-12#
```

### Sample Output

```
*A:ALA-12# show router 3 rip neighbors interface advertised-routes
=====
RIP Advertised Routes
=====
Destination      Interface      NextHop        Metric  Tag      TTL
-----
180.0.0.2/32     180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.5/32     180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.8/32     180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.9/32     180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.10/32    180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.12/32    180.1.8.12    0.0.0.0        1      0x0000   n/a
180.0.0.13/32    180.1.8.12    0.0.0.0        10     0x2002   n/a
180.0.0.14/32    180.1.8.12    0.0.0.0        16     0x0000   n/a
180.0.0.15/32    180.1.8.12    0.0.0.0        2      0x0000   n/a
180.0.0.16/32    180.1.8.12    0.0.0.0        3      0x0000   n/a
-----
No. of Advertised Routes: 10
=====
*A:ALA-12#
```

## peer

**Syntax** peer [*ip-int-name*]

**Context** show>router>rip

**Description** Displays RIP peer information.

**Parameters** *ip-int-name* — Displays peer information for peers on the specified IP interface.

**Default** Display peers for all interfaces.

**Output** **Show RIP Peer Output** — The following table describes the command output fields for a RIP peer:

Label	Description
Peer IP Addr	The IP address of the peer router.
Interface Name	The peer interface name.
Version	The version of RIP running on the peer.
Last Update	The number of days since the last update.
No. of Peers	The number of RIP peers.

## statistics

**Syntax** **statistics** [*ip-addr* | *ip-int-name*]

**Context** show>router>rip

**Description** Display Interface level statistics for the RIP protocol.

If no IP address or interface name is specified, then all configured RIP interfaces are displayed.

If an IP address or interface name is specified, then only data regarding the specified RIP interface is displayed.

**Parameters** *ip-addr* | *ip-int-name* — Displays statistics for the specified IP interface.

**Output** **Show RIP Statistics Output** — The following table describes the output fields for RIP statistics.

### Sample Output

Label	Description
Learned Routes	The number of RIP-learned routes were exported to RIP neighbors.
Timed Out Routes	The number of routes that have been timed out.
Current Memory	The amount of memory used by this RIP router instance.
Maximum Memory	The amount of memory allocated for this RIP router instance.
Interface	Displays the name of each interface configured in RIP and associated RIP statistics.
Primary IP	The interface IP address.
Update Timer	The current setting of the RIP update timer value expressed in seconds.
Timeout Timer	The current RIP timeout timer value expressed in seconds.

Label	Description (Continued)
Flush Timer	The number of seconds after a route has been declared invalid that it is flushed from the route database.
Updates Sent	<p>Total — The total number of RIP updates that were sent.</p> <p>Last 5 Min — The number of RIP updates that were sent in the last 5 minutes.</p> <p>Last 1 Min — The number of RIP updates that were sent in the last 1 minute.</p>
Triggered Updates	<p>Total — The total number of triggered updates sent. These updates are sent before the entire RIP routing table is sent.</p> <p>Last 5 Min — The number of triggered updates that were sent in the last 5 minutes.</p> <p>Last 1 Min — The number of triggered updates that were sent in the last 1 minute.</p>
Bad Packets Received	<p>Total — The total number of RIP updates received on this interface that were discarded as invalid.</p> <p>Last 5 Min — The number of RIP updates received on this interface that were discarded as invalid in the last 5 minutes.</p> <p>Last 1 Min — The number of RIP updates received on this interface that were discarded as invalid in the last 1 minute.</p>
RIPv1 Updates Received	<p>Total — The total number of RIPv1 updates received.</p> <p>Last 5 Min — The number of RIPv1 updates received in the last 5 minutes.</p> <p>Last 1 Min — The number of RIPv1 updates received in the last 1 minute.</p>
RIPv1 Updates Ignored	<p>Total — The total number of RIPv1 updates ignored.</p> <p>Last 5 Min — The number of RIPv1 updates ignored in the last 5 minutes.</p> <p>Last 1 Min — The number of RIPv1 updates ignored in the last 1 minute.</p>
RIPv1 Bad Routes	<p>Total — The total number of bad routes received from the peer.</p> <p>Last 5 Min — The number of bad routes received from the peer in the last 5 minutes.</p> <p>Last 1 Min — The number of bad routes received from the peer in the last minute.</p>
RIPv1 Requests Received	Total — The total number of times the router received RIPv1 route requests from other routers.



Label	Description (Continued)
	Last 5 Min – The number of times the router received RIPv1 route requests from other routers in the last 5 minutes.
	Last 1 Min – The number of times the router received RIPv1 route requests from other routers in the last 1 minute.
RIPv1 Requests Ignored	Total – The total number of times the router ignored RIPv1 route requests from other routers.
	Last 5 Min – The number of times the router ignored RIPv1 route requests from other routers in the last 5 minutes.
	Last 1 Min – The number of times the router ignored RIPv1 route requests from other routers in the last 1 minute.
RIPv2 Updates Received	Total – The total number of RIPv2 updates received.
	Last 5 Min – The number of RIPv2 updates received in the last 5 minutes.
	Last 1 Min – The number of RIPv2 updates received in the last minute.
RIPv2 Updates Ignored	Total – The total number of RIPv2 updates ignored.
	Last 5 Min – The number of RIPv2 updates ignored in the last 5 minutes.
	Last 1 Min – The number of RIPv2 updates ignored in the last minute.
RIPv2 Bad Routes	Total – The total number of bad routes received from the peer.
	Last 5 Min – The number of bad routes received from the peer in the last 5 minutes.
	Last 1 Min – The number of bad routes received from the peer in the last minute.
RIPv2 Requests Received	Total – The total number of times the router received RIPv2 route requests from other routers.
	Last 5 Min – The number of times the router received RIPv2 route requests from other routers in the last 5 minutes.
	Last 1 Min – The number of times the router received RIPv2 route requests from other routers in the last minute.
RIPv2 Requests Ignored	Total – The total number of times the router ignored RIPv2 route requests from other routers.
	Last 5 Min – The number of times the router ignored RIPv2 route requests from other routers in the last 5 minutes.

Label	Description (Continued)
	Last 1 Min — The number of times the router ignored RIPv2 route requests from other routers in the last minute.
Authentication Errors	Total — The total number of authentication errors to secure table updates.
	Last 5 Min — The number of authentication errors to secure table updates in the last 5 minutes.
	Last 1 Min — The number of authentication errors to secure table updates in the last minute.

```
*A:ALA-12# show router 3 rip statistics
=====
RIP Statistics
=====
Learned Routes      : 0                Timed Out Routes   : 0
Current Memory     : 120624           Maximum Memory     : 262144
-----
Interface "to-web"
-----
Primary IP          : 10.1.1.3          Update Timer       : 30
Timeout Timer      : 180                Flush Timer        : 120
Counter                                     Total              Last 5 Min         Last 1 Min
-----
Updates Sent                0                   0                   0
Triggered Updates           0                   0                   0
Bad Packets Received        0                   0                   0
RIPv1 Updates Received     0                   0                   0
RIPv1 Updates Ignored      0                   0                   0
RIPv1 Bad Routes           0                   0                   0
RIPv1 Requests Received    0                   0                   0
RIPv1 Requests Ignored     0                   0                   0
RIPv2 Updates Received     0                   0                   0
RIPv2 Updates Ignored      0                   0                   0
RIPv2 Bad Routes           0                   0                   0
RIPv2 Requests Received    0                   0                   0
RIPv2 Requests Ignored     0                   0                   0
Authentication Errors       0                   0                   0
=====
*A:ALA-12#
```

## route-table

**Syntax** `route-table [ip-prefix [/mask] [longer] | [protocol protocol] | [summary]]`

**Context** `show>router`

**Description** This command displays the active routes in the routing table.  
If no command line arguments are specified, all routes are displayed, sorted by prefix.

**Parameters** `ip-prefix[/mask]` — Displays routes only matching the specified `ip-prefix` and optional `mask`.

**longer** — Displays routes matching the *ip-prefix/mask* and routes with longer masks.

**protocol protocol** — Displays routes learned from the specified protocol.

**Values**      bgp, isis, local, ospf, rip, static, aggregate

**summary** — Displays a route table summary information.

**Output**      **Standard Show Route Table Output** — The following table describes the standard output fields for the route table.

Label	Description
Dest Address	The route destination address and mask.
Next Hop	The next hop IP address for the route destination.
Type	Local — The route is a local route. Remote — The route is a remote route.
Protocol	The protocol through which the route was learned.
Age	The route age in seconds for the route.
Metric	The route metric value for the route.
Pref	The route preference value for the route.
No. of Routes:	The number of routes displayed in the list.

### Sample Output

```
*A:ALA-12# show router 3 route-table
=====
Route Table
=====
Dest Address      Next Hop          Type   Protocol   Age      Metric  Pref
-----
10.10.0.1/32     10.10.13.1       Remote OSPF       65844    1001    10
10.10.0.2/32     10.10.13.1       Remote OSPF       65844    2001    10
10.10.0.3/32     0.0.0.0          Local  Local      1329261  0       0
10.10.0.4/32     10.10.34.4       Remote OSPF       3523     1001    10
10.10.0.5/32     10.10.35.5       Remote OSPF     1084022  1001    10
10.10.12.0/24    10.10.13.1       Remote OSPF       65844    2000    10
10.10.13.0/24    0.0.0.0          Local  Local      65859   0       0
10.10.15.0/24    10.10.13.1       Remote OSPF     58836    2000    10
10.10.24.0/24    10.10.34.4       Remote OSPF       3523     2000    10
10.10.25.0/24    10.10.35.5       Remote OSPF     399059   2000    10
10.10.34.0/24    0.0.0.0          Local  Local      3543    0       0
10.10.35.0/24    0.0.0.0          Local  Local     1329259  0       0
10.10.45.0/24    10.10.34.4       Remote OSPF       3523     2000    10
10.200.0.0/16    0.0.0.0          Local  Local      4513    0       0
192.168.0.0/20  0.0.0.0          Local  Local     1329264  0       0
192.168.254.0/24 0.0.0.0          Remote Static      11       1       5
-----
*A:ALA-12#

*A:ALA-12# show router 3 route-table 10.10.0.4
```

## Show, Clear, Debug Commands

```

=====
Route Table
=====
Dest Address      Next Hop          Type   Protocol   Age      Metric  Pref
-----
10.10.0.4/32     10.10.34.4      Remote OSPF       3523    1001    10
-----
*A:ALA-12#

*A:ALA-12# show router 3 route-table 10.10.0.4/32 longer
=====
Route Table
=====
Dest Address      Next Hop          Type   Protocol   Age      Metric  Pref
-----
10.10.0.4/32     10.10.34.4      Remote OSPF       3523    1001    10
-----
No. of Routes: 1
=====
+ : indicates that the route matches on a longer prefix
*A:ALA-12#

*A:ALA-12# show router 3 route-table protocol ospf
=====
Route Table
=====
Dest Address      Next Hop          Type   Protocol   Age      Metric  Pref
-----
10.10.0.1/32     10.10.13.1      Remote OSPF       65844   1001    10
10.10.0.2/32     10.10.13.1      Remote OSPF       65844   2001    10
10.10.0.4/32     10.10.34.4      Remote OSPF       3523    1001    10
10.10.0.5/32     10.10.35.5      Remote OSPF      1084022 1001    10
10.10.12.0/24    10.10.13.1      Remote OSPF       65844   2000    10
10.10.15.0/24    10.10.13.1      Remote OSPF       58836   2000    10
10.10.24.0/24    10.10.34.4      Remote OSPF       3523    2000    10
10.10.25.0/24    10.10.35.5      Remote OSPF      399059  2000    10
10.10.45.0/24    10.10.34.4      Remote OSPF       3523    2000    10
-----
*A:ALA-12#

*A:ALA-12# show router 3 route-table summary
=====
Route Table Summary
=====
                                     Active          Available
-----
Static                               1                1
Direct                               6                6
BGP                                  0                0
OSPF                                  9                9
ISIS                                 0                0
RIP                                  0                0
Aggregate                             0                0
-----
Total                                15              15
=====
*A:ALA-12#

```

## service-prefix

**Syntax** `service-prefix`

**Context** `show>router`

**Description** This command displays service-prefix information.

**Output** **Show Service Prefix Output** — The following table describes the service prefix output fields.

Label	Description
IP Prefix	Displays information for the specified IP prefix.
Mask	Displays information for the specified mask length.

### Sample Output

```
*A:ALA-12# show router 3 service-prefix
=====
Address Ranges Reserved for Services (Service: 3)
=====
IP Prefix           Mask           Exclusive
-----
No Matching Entries Found
=====
*A:ALA-12>show>router#
```

## static-arp

**Syntax** `static-arp [ip-address | ip-int-name | mac ieee-mac-addr]`

**Context** `show>router`

**Description** This command displays the router static ARP table sorted by IP address. If no options are present, all ARP entries are displayed.

**Parameters** *ip-address* — Only displays static ARP entries associated with the specified IP address.  
*ip-int-name* — Only displays static ARP entries associated with the specified IP interface name.  
**mac ieee-mac-addr** — Only displays static ARP entries associated with the specified MAC address.

**Output** **Static ARP Table Output** — The following table describes the output fields for the ARP table.

Label	Description
IP Address	The IP address of the static ARP entry.
MAC Address	The MAC address of the static ARP entry.
Age	The age of the ARP entry. Static ARPs always have 00:00:00 for the age.
Type	Inv — The ARP entry is an inactive static ARP entry (invalid). Sta — The ARP entry is an active static ARP entry.
Interface	The IP interface name associated with the ARP entry.
No. of ARP Entries	The number of ARP entries displayed in the list.

### Sample Output

```
*A:ALA-12# show router 3 static-arp
=====
ARP Table
=====
IP Address      MAC Address      Age      Type Interface
-----
10.200.0.253    00:00:5a:40:00:01 00:00:00 Sta  to-ser1
12.200.1.1      00:00:5a:01:00:33 00:00:00 Inv  to-ser1a
-----
No. of ARP Entries: 2
=====
*A:ALA-12#

*A:ALA-12# show router 3 static-arp 12.200.1.1
=====
ARP Table
=====
IP Address      MAC Address      Age      Type Interface
-----
12.200.1.1      00:00:5a:01:00:33 00:00:00 Inv  to-ser1 a
=====
*A:ALA-12#
```

```
*A:ALA-12# show router 3 static-arp to-ser1
=====
ARP Table
=====
IP Address      MAC Address      Age      Type Interface
-----
10.200.0.253   00:00:5a:40:00:01 00:00:00 Sta  to-ser1
=====
S*A:ALA-12#

*A:ALA-12# show router 3 static-arp mac 00:00:5a:40:00:01
=====
ARP Table
=====
IP Address      MAC Address      Age      Type Interface
-----
10.200.0.253   00:00:5a:40:00:01 00:00:00 Sta  to-ser1
=====
*A:ALA-12#
```

## static-route

**Syntax** `static-route [ip-prefix /mask] | [preference preference] | [next-hop ip-addr] [detail]`

**Context** show>router

**Description** This command displays the static entries in the routing table.

If no options are present, all static routes are displayed sorted by prefix.

**Parameters** *ip-prefix /mask* — Displays static routes only matching the specified *ip-prefix* and *mask*.

*preference preference* — Only displays static routes with the specified route preference.

**Values** 0 — 65535

*next-hop ip-addr* — Only displays static routes with the specified next hop IP address.

**detail** — Displays detailed information about the static route.

**Output** **Show Static Route Output** — The following table describes the output fields for the static route table:

Label	Description
IP Addr/mask	The static route destination address and mask.
Pref	The route preference value for the static route.
Metric	The route metric value for the static route.
Type	BH — The static route is a black hole route. The <code>NextHop</code> for this type of route is <code>black-hole</code> .  ID — The static route is an indirect route, where the <code>nextHop</code> for this type of route is the non-directly connected next hop.

Label	Description (Continued)
	NH — The route is a static route with a directly connected next hop. The <code>NextHop</code> for this type of route is either the next hop IP address or an egress IP interface name.
Next Hop	The next hop for the static route destination.
Interface	The egress IP interface name for the static route. n/a — indicates there is no current egress interface because the static route is inactive or a black hole route.
Active	N — The static route is inactive; for example, the static route is disabled or the next hop IP interface is down.  Y — The static route is active.
No. of Routes:	The number of routes displayed in the list.

**Sample Output**

```
*A:ALA-12# show router 3 static-route
=====
Route Table
=====
IP Addr/mask      Pref Metric Type NextHop      Interface      Active
-----
192.168.250.0/24  5    1    ID   10.200.10.1   to-ser1        Y
192.168.252.0/24  5    1    NH   10.10.0.254   n/a            N
192.168.253.0/24  5    1    NH   to-ser1        n/a            N
192.168.253.0/24  5    1    NH   10.10.0.254   n/a            N
192.168.254.0/24  4    1    BH   black-hole     n/a            Y
=====
*A:ALA-12#
```

```
*A:ALA-12# show router 3 static-route 192.168.250.0/24
=====
Route Table
=====
IP Addr/mask      Pref Metric Type NextHop      Interface      Active
-----
192.168.250.0/24  5    1    ID   10.200.10.1   to-ser1        Y
=====
*A:ALA-12#
```

```
*A:ALA-12# show router 3 static-route preference 4
=====
Route Table
=====
IP Addr/mask      Pref Metric Type NextHop      Interface      Active
-----
192.168.254.0/24  4    1    BH   black-hole     n/a            Y
=====
*A:ALA-12#
```

```
*A:ALA-12# show router 3 static-route next-hop 10.10.0.254
=====
```



```
Route Table
=====
IP Addr/mask      Pref Metric Type Nexthop          Interface      Active
-----
192.168.253.0/24  5    1    NH    10.10.0.254      n/a           N
=====
```

\*A:ALA-12#

\*A:Dut-B# show router static-route

```
=====
Static Route Table (Router: Base)  Family: IPv4
=====
Prefix          Tag      Met   Pref Type Act
  Next Hop      Interface
-----
1.2.3.4/32      0        1     5   NH   Y
  10.11.25.6
ip-10.11.25.5_base_to_cpe_static
10.11.15.0/24   0        1     5   NH   Y
  10.11.25.6
ip-10.11.25.5_base_to_cpe_static
-----
No. of Static Routes: 2
=====
```

\*A:Dut-B# show router static-route detail

```
=====
Static Route Table (Router: Base)  Family: IPv4
=====
Network          : 1.2.3.4/32
Nexthop          : 10.11.25.6
Type             : Nexthop          Nexthop Type   : IP
Interface        : ip-10.11.25.5_base_to_cpe_stat* Active         : Y
Metric           : 1                Preference     : 5
Admin State      : Up                Tag            : 0
BFD              : disabled
CPE-check        : enabled           State           : n/a
Target           : 10.11.18.6
Interval         : 1                Drop Count     : 3
Log              : N
CPE Host Up Time : 0d 00:00:02
CPE Echo Req Tx  : 3                CPE Echo Reply Rx : 3
CPE Up Trans     : 1                CPE Down Trans  : 0
CPE TTL          : 2
-----
Network          : 10.11.15.0/24
Nexthop          : 10.11.25.6
Type             : Nexthop          Nexthop Type   : IP
Interface        : ip-10.11.25.5_base_to_cpe_stat* Active         : Y
Metric           : 1                Preference     : 5
Admin State      : Up                Tag            : 0
BFD              : disabled
CPE-check        : disabled
-----
No. of Static Routes: 2
=====
```

\*A:CPM133>config>router# show router static-route 3.3.3.3/32 detail

## Show, Clear, Debug Commands

```
Static Route Table (Router: Base)  Family: IPv4
=====
Prefix                : 3.3.3.3/32
Nexthop               : n/a
Type                  : Blackhole
Interface             : n/a
Prefix List           : n/a
Metric                : 1
Admin State           : Up
BFD                   : disabled
CPE-check             : disabled
Nexthop Type         : IP
Active                : Y
Prefix List Type     : n/a
Preference            : 5
Tag                   : 0
Community             : 100:33
-----
No. of Static Routes: 1
=====
```

## tunnel-table

**Syntax** **tunnel-table** [*ip-address[/mask]*] [**protocol** *protocol* | **sdp** *sdp-id*]  
**tunnel-table** [**summary**]

**Context** show>router

**Description** This command displays tunnel table information.

Note that auto-bind GRE tunnels are not displayed in **show** command output. GRE tunnels are not the same as SDP tunnels that use the GRE encapsulation type. When the **auto-bind** command is used when configuring a VPRN service, it means the MP-BGP NH resolution is referring to core routing instance for IP reachability. For a VPRN service this object specifies the lookup to be used by the routing instance if no SDP to the destination exists.

**Parameters** *ip-address[/mask]* — Displays the specified tunnel table's destination IP address and mask.  
*protocol protocol* — Displays LDP protocol information.  
*sdp sdp-id* — Displays information pertaining to the specified SDP.  
**summary** — Displays summary tunnel table information.

**Output** **Show Tunnel Table Output** — The following table describes tunnel table output fields:

Label	Description
Destination	The route's destination address and mask.
Owner	Specifies the tunnel owner.
Encap	Specifies the tunnel's encapsulation type.
Tunnel ID	Specifies the tunnel (SDP) identifier.
Pref	Specifies the route preference for routes learned from the configured peer(s).
Nexthop	The next hop for the route's destination.
Metric	The route metric value for the route.

**Sample Output**

```
*A:ALA-12>config>service# show router 3 tunnel-table
=====
Tunnel Table
=====
Destination      Owner   Encap   Tunnel  Id     Pref      NexthopMetric
-----
10.0.0.1/32      sdp    GRE     10      5     10.0.0.1    0
10.0.0.1/32      sdp    GRE     21      5     10.0.0.1    0
10.0.0.1/32      sdp    GRE     31      5     10.0.0.1    0
10.0.0.1/32      sdp    GRE     41      5     10.0.0.1    0
=====
*A:ALA-12>config>service#

*A:ALA-12>config>service# show router 3 tunnel-table summary
=====
Tunnel Table Summary (Router: Base)
=====
Active           Available
-----
LDP              1           1
SDP              1           1
=====
*A:ALA-12>config>service#
```

**statistics****Syntax** **statistics** [*ip-int-name* | *ip-address*]**Context** show>router>dhcp**Description** Display statistics for DHCP Relay and DHCP snooping.

If no IP address or interface name is specified, then all configured interfaces are displayed.

If an IP address or interface name is specified, then only data regarding the specified interface is displayed.

**Parameters** *ip-int-name* | *ip-address* — Displays statistics for the specified IP interface.**Output** **Show DHCP Statistics Output** — The following table describes the output fields for DHCP. statistics.

Label	Description
Received Packets	The number of packets received from the DHCP clients.
Transmitted Packets	The number of packets transmitted to the DHCP clients.
Received Malformed Packets	The number of malformed packets received from the DHCP clients.
Received Untrusted Packets	The number of untrusted packets received from the DHCP clients.
Client Packets Discarded	The number of packets received from the DHCP clients that were discarded.

Label	Description (Continued)
Client Packets Relayed	The number of packets received from the DHCP clients that were forwarded.
Client Packets Snooped	The number of packets received from the DHCP clients that were snooped.
Server Packets Discarded	The number of packets received from the DHCP server that were discarded.
Server Packets Relayed	The number of packets received from the DHCP server that were forwarded.
Server Packets Snooped	The number of packets received from the DHCP server that were snooped.

**Sample Output**

```
*A:ALA-1# show router dhcp statistics
=====
DHCP Global Statistics
=====
Rx Packets                : 0
Tx Packets                : 0
Rx Malformed Packets     : 0
Rx Untrusted Packets     : 0
Client Packets Discarded  : 0
Client Packets Relayed   : 0
Client Packets Snooped   : 0
Server Packets Discarded  : 0
Server Packets Relayed   : 0
Server Packets Snooped   : 0
=====
*A:ALA-1#
```

**summary**

**Syntax** summary

**Context** show>router>dhcp

**Description** Display the status of the DHCP Relay and DHCP snooping functions on each interface.

**Output** **Show DHCP Summary Output** — The following table describes the output fields for DHCP summary.

Label	Description
Interface Name	Name of the router interface.
ARP Populate	Indicates whether or nor ARP populate is enabled.
Info Option	Indicates whether Option 82 is enabled.
Admin State	Indicates the administrative status.

**Sample Output**

```
A:ALA-48# show router dhcp summary
=====
Interface Name                Arp      Used/   Info   Admin
                              Populate Provided Option  State
-----
ies-10-10.10.1.1              Yes      1000/8000 Keep   Up
ies-100-100.100.1.1           No        0/0     Keep   Down
ies-11-11.11.1.1              Yes      1000/8000 Keep   Up
ies-12-12.12.1.1              Yes      1000/8000 Keep   Up
ies-13-13.13.1.1              Yes      1000/8000 Keep   Up
ies-14-14.14.1.1              Yes      1000/8000 Keep   Up
ies-15-15.15.1.1              Yes      1000/8000 Keep   Up
ies-16-16.16.1.1              No        0/0     Keep   Down
ies-2-10.17.1.1               No        0/0     Keep   Down
ies-8-8.8.1.1                  Yes      1000/8000 Keep   Up
ies-9-9.9.1.1                  Yes      1000/8000 Keep   Up
-----
Interfaces: 11
=====
```

**wpp**

**Syntax**    **wpp**  
**wpp [portal wpp-portal-name] [host ip-address] hosts**  
**wpp portal wpp-portal-name**  
**wpp statistics**

**Context**    show>router

**Description**    This command displays Web Portal Protocol information.

## VPRN Clear Commands

### apr

<b>Syntax</b>	<b>arp</b>
<b>Context</b>	clear>service>id
<b>Description</b>	This command clears

### arp-host

<b>Syntax</b>	<b>arp-host</b> <b>arp-host</b> { <b>mac</b> <i>ieee-address</i>   <b>sap</b> <i>sap-id</i>   <b>ip-address</b> <i>ip-address</i> [/ <i>mask</i> ] } <b>arp-host</b> [ <b>port</b> <i>port-id</i> ] [ <b>inter-dest-id</b> <i>intermediate-destination-id</i>   <b>no-inter-dest-id</b> ] <b>arp-host statistics</b> [ <b>sap</b> <i>sap-id</i>   <b>interface</b> <i>interface-name</i> ]
<b>Context</b>	clear>service>id
<b>Description</b>	This command clears ARP host data.

### dhcp

<b>Syntax</b>	<b>dhcp</b>
<b>Context</b>	clear>router
<b>Description</b>	This command enables the context to clear and reset DHCP entities.

### statistics

<b>Syntax</b>	<b>statistics</b> [ <b>interface</b> <i>ip-int-name</i>   <i>ip-address</i> ]
<b>Context</b>	clear>router>dhcp
<b>Description</b>	Clears DHCP statistics.

### forwarding-table

<b>Syntax</b>	<b>forwarding-table</b> [ <i>slot-number</i> ]
<b>Context</b>	clear>router
<b>Description</b>	This command clears the route table on the specified IOM with the route table.

If the slot number is not specified, the command forces the route table to be recalculated.

**Parameters** *slot-number* — Clears the specified IOM slot.

**Default** all IOMs

**Values** 1 - 10 (depending on chassis model)

## interface

**Syntax** **interface** [*ip-int-name* | *ip-addr*] [**icmp**]

**Context** clear>router

**Description** This command clears IP interface statistics.

If no IP interface is specified either by IP interface name or IP address, the command will perform the clear operation on all IP interfaces.

**Parameters** *ip-int-name* | *ip-addr* — The IP interface name or IP interface address.

**Default** All IP interfaces.

**icmp** — Specifies to reset the ICMP statistics for the IP interface(s) used for ICMP rate limit.

## damping

**Syntax** **damping** [[*ip-prefix/mask*] [**neighbor** *ip-address*]] | [**group** *name*]

**Context** clear>router>bgp

**Description** This command clears or resets the route damping information for received routes.

**Parameters** *ip-prefix/mask* — Clears damping information for entries that match the IP prefix and mask length.

**neighbor** *ip-address* — Clears damping information for entries received from the BGP neighbor.

**group** *name* — Clears damping information for entries received from any BGP neighbors in the peer group.

## flap-statistics

**Syntax** **flap-statistics** [[*ip-prefix/mask*] [**neighbor** *ip-addr*]] | [**group** *group-name*] | [**regex** *reg-exp*] | [**policy** *policy-name*]

**Context** clear>router>bgp

**Description** This command clears route flap statistics.

**Parameters** *ip-prefix/mask* — Clears route flap statistics for entries that match the specified IP prefix and mask length.

**neighbor** *ip-addr* — Clears route flap statistics for entries received from the specified BGP neighbor.

**group** *group-name* — Clears route flap statistics for entries received from any BGP neighbors in the specified peer group.

## Show, Clear, Debug Commands

**regex** *reg-exp* — Clears route flap statistics for all entries which have the regular expression and the AS path that matches the regular expression.

**policy** *policy-name* — Clears route flap statistics for entries that match the specified route policy.

## neighbor

**Syntax** **neighbor** {*ip-addr* | **as** *as-number* | **external** | **all**} [**soft** | **soft-inbound** | **statistics**]

**Context** clear>router>bgp

**Description** This command resets the specified BGP peer or peers. This can cause existing BGP connections to be shutdown and restarted.

**Parameters** *ip-addr* — Resets the BGP neighbor with the specified IP address.

**as** *as-number* — Resets all BGP neighbors with the specified peer AS.

**external** — Resets all EBGp neighbors.

**all** — Resets all BGP neighbors.

**soft** — The specified BGP neighbor(s) re-evaluates all routes in the Local-RIB against the configured export policies.

**soft-inbound** — The specified BGP neighbor(s) re-evaluates all routes in the RIB-In against the configured import policies.

**statistics** — The BGP neighbor statistics.

## protocol

**Syntax** **protocol**

**Context** clear>router>bgp

**Description** This command resets the entire BGP protocol. If the AS number was previously changed, the BGP AS number does not inherit the new value.

## database

**Syntax** **database**

**Context** clear>router>rip

**Description** This command flushes all routes in the RIP database.

## statistics

**Syntax** **statistics** [**neighbor** {*ip-address* | *ip-int-name*}]

**Context** clear>router>rip



**Description** This command clears statistics for RIP neighbors.

**Parameters** **neighbor** *{ip-address | ip-int-name}* — Clears the statistics for the specified RIP interface.

**Default** Clears statistics for all RIP interfaces.

## id

**Syntax** **id** *service-id*

**Context** clear>service  
clear>service>statistics

**Description** This command clears commands for a specific service.

**Parameters** *service-id* — The ID that uniquely identifies a service.

**Values** 1 — 2147483648

## sap

**Syntax** **sap** *sap-id* {**all** | **counters** | **stp**}

**Context** clear>service>statistics

**Description** Clears SAP statistics for a SAP.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

## dhcp

**Syntax** **dhcp**

**Context** clear>router>dhcp

**Description** This command enables the context to clear DHCP parameters.

## lease-state

**Syntax** **lease-state**  
**lease-state ip-address** *ip-address*  
**lease-state mac** *ieee-address*  
**lease-state sap** *sap-id*  
**lease-state sdp** *sdp-id:vc-id*

**Context** clear>service>id>dhcp

**Description** Clears DHCP lease state information for this service.

## Show, Clear, Debug Commands

**Parameters**

*ip-address* — The IP address of the IP interface. The *ip-address* portion of the **address** command specifies the IP host address that will be used by the IP interface within the subnet. This address must be unique within the subnet and specified in dotted decimal notation. Allowed values are IP addresses in the range 1.0.0.0 – 223.255.255.255 (with support of /31 subnets).

*ieee-address* — Specifies the 48-bit MAC address for the static ARP in the form aa:bb:cc:dd:ee:ff or aa-bb-cc-dd-ee-ff where aa, bb, cc, dd, ee, and ff are hexadecimal numbers. Allowed values are any non-broadcast, non-multicast MAC and non-IEEE reserved MAC addresses.

*sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

*sdp-id* — The SDP ID to be cleared.

**Values** 1 — 17407

*vc-id* — The virtual circuit ID on the SDP ID to be cleared.

**Values** 1 — 4294967295

## site

**Syntax** **site** *service-id*

**Context** clear>service>id

**Description** This command clears site-specific information for the service.

**Parameters** *service-id* — Specifies the service ID or service name up to 64 characters in length.

**Values** 1 — 2147483648

## spoke-sdp

**Syntax** **spoke-sdp** *sdp-id:vc-id ingress-vc-label*

**Context** clear>service>id

**Description** This command clears and resets the spoke SDP bindings for the service.

**Parameters** *sdp-id* — The spoke SDP ID to be reset.

**Values** 1 — 17407

*vc-id* — The virtual circuit ID on the SDP ID to be reset.

**Values** 1 — 4294967295

## sdp

**Syntax** **sdp** *sdp-id keep-alive*

**Context** clear>service>statistics

**Description** This command clears keepalive statistics associated with the SDP ID.

**Parameters** *sdp-id* — The SDP ID for which to clear keepalive statistics.  
**Values** 1 — 17407

## counters

**Syntax** **counters**

**Context** clear>service>statistics>id

**Description** Clears all traffic queue counters associated with the service ID.

## spoke-sdp

**Syntax** **spoke-sdp** *sdp-id[:vc-id]* {**all** | **counters** | **stp**}

**Context** clear>service>statistics>id

**Description** This command clears statistics for the spoke SDP bound to the service.

**Parameters** *sdp-id* — The spoke SDP ID for which to clear statistics.

**Values** 1 — 17407

*vc-id* — The virtual circuit ID on the SDP ID to be reset.

**Values** 1 — 4294967295

**all** — Clears all queue statistics and STP statistics associated with the SDP.

**counters** — Clears all queue statistics associated with the SDP.

**stp** — Clears all STP statistics associated with the SDP.

## stp

**Syntax** **stp**

**Context** clear>service>statistics>id

**Description** Clears all spanning tree statistics for the service ID.

## VPRN Debug Commands

### id

**Syntax** [no] id *service-id*

**Context** debug>service

**Description** This command debugs commands for a specific service.  
The **no** form of the command disables debugging.

**Parameters** *service-id* — The ID that uniquely identifies a service.

### arp-host

**Syntax** [no] arp-host

**Context** debug>service>id

**Description** This command enables and configures ARP host debugging.  
The **no** form of the command disables ARP host debugging.

### dhcp

**Syntax** [no] dhcp

**Context** debug>service>id

**Description** This command enables the context for DHCP debugging.  
The **no** form of the command disables DHCP debugging.

### detail-level

**Syntax** detail-level {low | medium | high}  
no detail-level

**Context** debug>service>id>dhcp

**Description** This command configures the DHCP tracing detail level.  
The **no** form of the command disables debugging.

### mode

**Syntax** mode {dropped-only | ingr-and-dropped | egr-ingr-and-dropped}

**no mode****Context** debug>service>id>dhcp**Description** This command configures the DHCP tracing mode.  
The **no** form of the command disables debugging.

## host-connectivity-verify

**Syntax** [**no**] host-connectivity-verify**Context** debug>service>id**Description** This command enables Subscriber Host Connectivity Verification (SHCV) debugging.  
The **no** form of the command disables the SHCV debugging.

## ip

**Syntax** [**no**] ip *ip-address***Context** debug>service>id>host-connectivity-verify**Description** This command displays Subscriber Host Connectivity Verification (SHCV) events for a particular IP address.**Parameters** *ip-address* — The IP address of the IP interface. The *ip-address* portion of the **address** command specifies the IP host address that will be used by the IP interface within the subnet. This address must be unique within the subnet and specified in dotted decimal notation. Allowed values are IP addresses in the range 1.0.0.0 – 223.255.255.255 (with support of /31 subnets).

## mac

**Syntax** [**no**] mac *ieee-address***Context** debug>service>id>host-connectivity-verify**Description** This command displays Subscriber Host Connectivity Verification (SHCV) events for a particular MAC address.**Parameters** *mac-address* — Specifies the 48-bit MAC address for the static ARP in the form aa:bb:cc:dd:ee:ff or aa-bb-cc-dd-ee-ff where aa, bb, cc, dd, ee, and ff are hexadecimal numbers. Allowed values are any non-broadcast, non-multicast MAC and non-IEEE reserved MAC addresses.

## sap

**Syntax** [**no**] sap *sap-id*

## Show, Clear, Debug Commands

**Context** debug>service>id>host-connectivity-verify

**Description** This command displays Subscriber Host Connectivity Verification (SHCV) events for a particular SAP.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

## sap

**Syntax** [no] **sap** *sap-id*

**Context** debug>service>id  
debug>service>id>dhcp  
debug>service>stp

**Description** This command enables STP debugging for a specific SAP.  
The **no** form of the command disables debugging.

**Parameters** *sap-id* — Specifies the physical port identifier portion of the SAP definition. See [Common CLI Command Descriptions on page 2569](#) for command syntax.

## sdp

**Syntax** [no] **sdp** *sdp-id:vc-id*

**Context** debug>service>id  
debug>service>id>dhcp  
debug>service>stp

**Description** This command enables STP debugging for a specific SDP.  
The **no** form of the command disables debugging.

## event-type

**Syntax** [no] **event-type** {**config-change** | **svc-oper-status-change** | **sap-oper-status-change** | **sdpbind-oper-status-change**}

**Context** debug>service>id

**Description** This command enables debugging for a particular event type.  
The **no** form of the command disables debugging.

## event-type

**Syntax** [no] **event-type** {**config-change** | **oper-status-change**}

**Context** debug>service>id>sap

**Description** This command enables debugging for a particular event type.  
The **no** form of the command disables debugging.

## stp

**Syntax** [no] stp

**Context** debug>service>id

**Description** This command enables the context for debugging STP.  
The **no** form of the command disables debugging.

## all-events

**Syntax** all-events

**Context** debug>service>id>event-type

**Description** This command enables STP debugging for all events.  
The **no** form of the command disables debugging.

## bpdu

**Syntax** [no] bpdu

**Context** debug>service>stp

**Description** This command enables STP debugging for received and transmitted BPDUs.  
The **no** form of the command disables debugging.

## core-connectivity

**Syntax** [no] core-connectivity

**Context** debug>service>stp

**Description** This command enables STP debugging for core connectivity.  
The **no** form of the command disables debugging.

## exception

**Syntax** [no] exception

**Context** debug>service>stp

**Description** This command enables STP debugging for exceptions.

## Show, Clear, Debug Commands

The **no** form of the command disables debugging.

### fsm-state-changes

**Syntax** [no] fsm-state-changes

**Context** debug>service>stp

**Description** This command enables STP debugging for FSM state changes.  
The **no** form of the command disables debugging.

### fsm-timers

**Syntax** [no] fsm-timers

**Context** debug>service>stp

**Description** This command enables STP debugging for FSM timer changes.  
The **no** form of the command disables debugging.

### port-role

**Syntax** [no] port-role

**Context** debug>service>stp

**Description** This command enables STP debugging for changes in port roles.  
The **no** form of the command disables debugging.

### port-state

**Syntax** [no] port-state

**Context** debug>service>stp

**Description** This command enables STP debugging for port states.  
The **no** form of the command disables debugging.

### igmp

**Syntax** [no] igmp

**Context** debug>router

**Description** This command enables debugging for IGMP.



The **no** form of the command disables debugging.

## interface

**Syntax** **[no] interface** [*ip-int-name* | *ip-address*]

**Context** debug>router>igmp

**Description** This command enables debugging on the IGMP interface.

The **no** form of the command disables debugging.

**Parameters** *ip-int-name* — Only displays the information associated with the specified IP interface name.

*ip-address* — Only displays the information associated with the specified IP address.

### Sample Output

```
A:FA# debug router 100 igmp interface
A:FA#
A:FA# show debug
debug
    router "100"
        igmp
            interface
        exit
    exit
exit
*A:FA#
38397 2007/02/01 11:46:40.94 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Querier Timer expired on i/f 2"

38398 2007/02/01 11:46:40.94 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Sending query on i/f 2 to 0.0.0.0"

38399 2007/02/01 11:46:40.94 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Interface 2 already UP, ignoring event"

38400 2007/02/01 11:46:41.64 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.1 in mode EXCLUD
E. Num srcls 0"

38401 2007/02/01 11:46:41.64 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.2 in mode EXCLUD
E. Num srcls 0"

38402 2007/02/01 11:46:41.64 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.3 in mode EXCLUD
E. Num srcls 0"

38403 2007/02/01 11:46:41.64 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.4 in mode EXCLUD
```

## Show, Clear, Debug Commands

```
E. Num srcls 0"

38404 2007/02/01 11:46:41.64 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.5 in mode EXCLUD
E. Num srcls 0"

38405 2007/02/01 11:46:48.93 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.1 in mode EXCLUD
E. Num srcls 0"
38408 2007/02/01 11:46:48.93 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.4 in mode EXCLUD
E. Num srcls 0"

38409 2007/02/01 11:46:48.93 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Process received group rec MODE_IS_EXCL for i/f 2 group 225.1.1.5 in mode EXCLUD
E. Num srcls 0"

38410 2007/02/01 11:46:48.93 UTC MINOR: DEBUG #2001 vprn100 IGMP[85]
"IGMP[85]: INTF
Interface 2 already UP, ignoring event"
A:FA#
```

### mcs

**Syntax** [no] mcs [*ip-int-name*]

**Context** debug>router>igmp

**Description** This command enables debugging for IGMP MCS.  
The **no** form of the command disables debugging.

**Parameters** *ip-int-name* — Only displays the information associated with the specified IP interface name.

#### Sample Output

```
A:BA# debug router 100 igmp mcs
A:BA# show debug
debug
  router "100"
    igmp
      mcs
    exit
  exit
exit
A:BA#
```

### misc

**Syntax** [no] misc

**Context** debug>router>igmp

**Description** This command enables debugging for IGMP miscellaneous. The **no** form of the command disables debugging.

### Sample Output

```
A:BA# debug router 100 igmp misc

A:BA# show debug
debug
  router "100"
    igmp
      misc
    exit
  exit
exit
A:BA#
```

## packet

**Syntax** **[no] packet [query|v1-report|v2-report|v3-report|v2-leave] [ip-int-name | ip-address]**

**Context** debug>router>igmp

**Description** This command enables debugging for IGMP packets. The **no** form of the command disables debugging.

**Parameters** *query v1/v2/v3-report, v2-leave* — Select the type of packet to debug.  
*ip-int-name* — Only displays the information associated with the specified IP interface name.  
*ip-address* — Only displays the information associated with the specified IP address.

### Sample Output

```
A:BA# debug router 100 igmp packet
A:BA#
A:BA# show debug
debug
  router "100"
    igmp
      packet
    exit
  exit
exit
5 2006/09/03 22:20:05.73 UTC MINOR: DEBUG #2001 vprn100 IGMP[2]
"IGMP[2]: TX-PKT
[000 18:25:24.480] ifId:2 ifName:IGMP_to_CE IGMP V3 PDU: 11.1.1.1 -> 224.0.0.1 p
duLen 12
  Type: QUERY maxrespCode 0xa checksum 0xec78
  GroupAddr: 0.0.0.0
    S bit 0, QRV 2, QQIC 125, NumSources 0
  Source Address List:
"
6 2006/09/03 22:20:05.96 UTC MINOR: DEBUG #2001 vprn100 IGMP[2]
"IGMP[2]: RX-PKT
[000 18:25:24.710] ifId:2 ifName:IGMP_to_CE IGMP V3 PDU: 11.1.1.20 -> 224.0.0.22
pduLen 48
```

## Show, Clear, Debug Commands

```
Type: V3 REPORT maxrespCode 0x0 checksum 0x5fe2
Num Group Records: 4
  Group Record 0
    Type: CHG_TO_EXCL, AuxDataLen 0, Num Sources 0
    Mcast Addr: 225.1.1.1
    Source Address List
  Group Record 1
    Type: CHG_TO_EXCL, AuxDataLen 0, Num Sources 0
    Mcast Addr: 225.1.1.2
    Source Address List
  Group Record 2
    Type: CHG_TO_EXCL, AuxDataLen 0, Num Sources 0
    Mcast Addr: 225.1.1.3
    Source Address List
  Group Record 3
    Type: CHG_TO_EXCL, AuxDataLen 0, Num Sources 0
    Mcast Addr: 225.1.1.4
    Source Address List

A:BA#
*A:BA# no debug
Trace disabled for all existing and future clients
*A:BA# show debug
debug
exit
```